

KF760/KF761 Processor Settings

November 13, 2001



KF760 triamp

KF761 triamp

OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

Low	Mid	Hi
4.5	-3.5	4.0
0.00	2.52	2.92
Positive	Positive	Positive
40	193	1059
24	24	24
Butterworth	Butterworth	Butterworth
172	1335	21983
24	24	12
Butterworth	Butterworth	Bessel
54	273	1682
6.0	3.0	-11.5
Parametric	Parametric	Parametric
1.59	2.00	2.67
0.63	0.50	0.51
118	408	3175
-5.0	-1.5	-5.0
Parametric	Parametric	Parametric
2.52	2.83	2.38
0.40	0.35	0.42
236	841	5496
-9.0	-4.0	-3.0
Parametric	Parametric	Parametric
2.24	2.67	3.36
0.53	0.37	0.30
167	1189	16469
6.0	-1.0	9.0
Parametric	Parametric	Parametric
2.12	2.00	1.26
0.47	0.50	0.94
	364	595
	-4.0	-10.0
	Parametric	Parametric
	1.50	4.00
	0.67	0.31

Low	Mid	Hi
4.5	-3.5	3.0
0.00	3.88	2.42
Positive	Positive	Positive
40	198	1297
24	24	24
Butterworth	Butterworth	Butterworth
172	1634	19027
24	24	12
Butterworth	Butterworth	Bessel
54	273	612
6.0	2.0	-5.0
Parametric	Parametric	Parametric
1.59	3.36	2.00
0.63	0.30	0.50
118	944	2059
-5.0	3.5	-11.5
Parametric	Parametric	Parametric
2.52	2.12	1.12
0.40	0.47	1.22
236	1414	5496
-9.0	2.6	-5.0
Parametric	Parametric	Parametric
2.24	1.50	1.68
0.53	0.67	0.60
167	612	10679
6.0	-1.0	8.0
Parametric	Parametric	Parametric
2.12	3.56	1.50
0.47	0.28	0.75
	364	3175
	-4.0	0.5
	Parametric	Parametric
	1.50	3.00
	0.67	0.33

NOTE: To use systems with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.