

JFe Processor Settings

November 13, 2001



JF200e biamp

OUTPUT	Name	Low	Hi
GAIN	(dB)	6.0	0.0
DELAY	(ms)	0.00	0.00
POLARITY		Positive	Positive
HPF	Freq (Hz)	40.5	1542
	Slope (dB)	24	24
	Shape	Butterworth	Linkwitz-Riley
LPF	Freq (Hz)	1782	thru
	Slope (dB)	24	
	Shape	Butterworth	
PEQ1	Freq (Hz)	60	14254
	Level (dB)	6.0	4.5
	Type	Parametric	Parametric
	Q	2.00	1.59
	(Bandwidth)	0.50	0.63
PEQ2	Freq (Hz)	1224	3462
	Level (dB)	-4.0	-4.0
	Type	Parametric	Parametric
	Q	4.00	2.00
	(Bandwidth)	0.25	0.50
PEQ3	Freq (Hz)	354	2119
	Level (dB)	-1.0	-1.5
	Type	Parametric	Parametric
	Q	2.83	3.00
	(Bandwidth)	0.35	0.33
PEQ4	Freq (Hz)		
	Level (dB)		
	Type		
	Q		
	(Bandwidth)		
PEQ5	Freq (Hz)		
	Level (dB)		
	Type		
	Q		
	(Bandwidth)		

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.

JFe Processor Settings

November 13, 2001



JF260e biamp

JF560e biamp

OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

Low	Hi
4.0	0.0
0.50	0.00
Positive	Positive
40.5	1450
24	24
Butterworth	Linkwitz-Riley
1730	thru
24	
Butterworth	
60	6160
6.0	-2.0
Parametric	Parametric
2.00	13.50
0.50	0.07
445	7550
7.0	2.0
Parametric	Parametric
8.98	13.50
0.12	0.07
	20150
	3.0
	Parametric
	4.00
	0.25

Low	Hi
2.5	-4.0
0.36	0.00
Positive	Positive
35	1450
24	24
Butterworth	Butterworth
1370	thru
24	
Linkwitz-Riley	
53	1580
4.5	-2.0
Parametric	Parametric
2.00	5.00
0.50	0.20
944	2990
-4.5	-2.0
Parametric	Parametric
4.00	7.13
0.25	0.14
530	5180
-5.0	4.0
Parametric	Parametric
5.99	8.00
0.17	0.13

NOTE: To use systems with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.