



---

# Summit® Family Switches Hardware Installation Guide

---

**Summit X150 Series**

**Summit X250e Series**

**Summit X350 Series**

**Summit X450 Series**

**Summit X450a Series**

**Summit X450e Series**

**Summit X650 Series**

Extreme Networks, Inc.  
3585 Monroe Street  
Santa Clara, California 95051  
(888) 257-3000  
(408) 579-2800  
<http://www.extremenetworks.com>

Published: November 2009  
Part Number: 100286-00 Rev. 07



AccessAdapt, Alpine, Altitude, BlackDiamond, EPICenter, ExtremeWorks Essentials, Ethernet Everywhere, Extreme Enabled, Extreme Ethernet Everywhere, Extreme Networks, Extreme Standby Router Protocol, Extreme Turbodriven, Extreme Velocity, ExtremeWare, ExtremeWorks, ExtremeXOS, Go Purple Extreme Solution, ExtremeXOS ScreenPlay, ReachNXT, Sentiart, ServiceWatch, Summit, SummitStack, Triumph, Unified Access Architecture, Unified Access RF Manager, UniStack, the Extreme Networks logo, the Alpine logo, the BlackDiamond logo, the Extreme Turbodriven logo, the Summit logos, and the Powered by ExtremeXOS logo are trademarks or registered trademarks of Extreme Networks, Inc. or its subsidiaries in the United States and/or other countries.

sFlow is a registered trademark of InMon Corporation.

Specifications are subject to change without notice.

All other registered trademarks, trademarks, and service marks are property of their respective owners.

© 2007 – 2009 Extreme Networks, Inc. All Rights Reserved.

For safety compliance information, see [Appendix A, "Safety Information."](#)

# Contents

|  |           |
|--|-----------|
| <b>Preface.....</b>  | <b>9</b>  |
| Introduction .....   | 9         |
| Conventions.....   | 10        |
| Related Publications .....                                       | 10        |
| <br><b>Part 1: About the Summit Family Switches</b>              |           |
| <b>Chapter 1: Summit Family Switches.....</b>                    | <b>15</b> |
| Overview of the Summit Switches .....                            | 15        |
| Combination Ports and Failover .....                             | 17        |
| Summit X150 Series Switches .....                                | 18        |
| Summit X150-24t Switch .....                                     | 19        |
| Summit X150-24p Switch .....                                     | 20        |
| Summit X150-48t Switch .....                                     | 21        |
| Summit X150 Series Switch LEDs .....                             | 22        |
| Summit X250e Series Switches.....                                | 23        |
| Summit X250e-24t Switch .....                                    | 24        |
| Summit X250e-24tDC Switch .....                                  | 25        |
| Summit X250e-24p Switch.....                                     | 26        |
| Summit X250e-24x Switch .....                                    | 27        |
| Summit X250e-24xDC Switch.....                                   | 28        |
| Summit X250e-48t Switch .....                                    | 29        |
| Summit X250e-48tDC Switch .....                                  | 30        |
| Summit X250e-48p Switch.....                                     | 32        |
| Summit X250e-48p Power Supplies .....                            | 33        |
| Internal Power Supply.....                                       | 33        |
| External Power Supplies.....                                     | 33        |
| Summit X250e Series Switch LEDs .....                            | 34        |
| Summit X350 Series Switches .....                                | 35        |
| Summit X350-24t Switch .....                                     | 36        |
| Summit X350-48t Switch .....                                     | 37        |
| Summit X350 Series Switch LEDs .....                             | 39        |
| Summit X450 Series, X450a Series, and X450e Series Switches..... | 40        |
| Summit X450 Series Switches .....                                | 41        |
| Summit X450-24t Switch .....                                     | 41        |
| Summit X450-24x Switch .....                                     | 42        |
| Summit X450a Series Switches.....                                | 44        |
| Summit X450a-24t Switch.....                                     | 44        |
| Summit X450a-24tDC Switch .....                                  | 46        |
| Summit X450a-24x Switch .....                                    | 47        |
| Summit X450a-24xDC Switch .....                                  | 49        |
| Summit X450a-48t Switch.....                                     | 50        |
| Summit X450a-48tDC Switch .....                                  | 51        |
| Summit X450e Series Switches.....                                | 53        |
| Summit X450e-24p Switch .....                                    | 53        |

|  |           |
|--|-----------|
| Summit X450e-48p Switch .....  | 55        |
| Summit X450e-48p Power Supplies .....  | 56        |
| Internal Power Supply .....  | 56        |
| External Power Supplies .....  | 56        |
| Summit X450, X450a, and X450e Series Switch LEDs .....                             | 57        |
| Summit X650 Series Switches .....  | 58        |
| Summit X650-24t Switch .....   | 59        |
| Summit X650-24x Switch .....   | 60        |
| VIM1-SummitStack Versatile Interface Module .....                                  | 61        |
| VIM1-10G8X Versatile Interface Module .....  | 61        |
| VIM1-SummitStack512 Versatile Interface Module .....                               | 62        |
| Summit X650 Series Switch LEDs .....   | 63        |
| <b>Chapter 2: Summit Power Supplies.....</b>                                       | <b>65</b> |
| Overview .....   | 65        |
| EPS-160 External Power Module (with EPS-T) .....                                   | 66        |
| EPS-LD External Power Supply Unit .....  | 67        |
| EPS-500 External Power Supply Unit .....   | 68        |
| EPS-150DC External Power Module (with EPS-T2) .....                                | 68        |
| EPS-600LS External Power Module .....  | 69        |
| PoE Redundant Power Configurations .....   | 69        |
| Single 600-LS Module Configuration: Redundant PoE Power .....                      | 69        |
| Dual 600-LS Module Configuration: Full Power .....                                 | 70        |
| Triple 600-LS Module Configuration: Full Redundant Power .....                     | 70        |
| Internal-to-External PSU Transfer .....  | 70        |
| Internal PSU Failure with Single EPS-600LS Module .....                            | 70        |
| Two or Three EPS-600LS Modules .....   | 70        |
| External-to-Internal PSU Transfer .....  | 70        |
| Active Internal PSU with Single 600-LS Module Failure .....                        | 70        |
| Inactive Internal PSU with a Dual EPS-600LS Configuration and Module Failure ..... | 70        |
| Disconnecting the EPS-C/EPS-600LS .....  | 71        |
| Summit X650 Power Supplies .....   | 71        |
| <b>Part 2: Installing the Hardware</b>   |           |
| <b>Chapter 3: Site Preparation.....</b>  | <b>75</b> |
| Planning Your Site .....   | 75        |
| Meeting Site Requirements .....  | 76        |
| Operating Environment Requirements .....   | 76        |
| Building and Electrical Codes .....  | 76        |
| Wiring Closet Considerations .....   | 77        |
| Temperature .....  | 77        |
| Humidity .....   | 78        |
| Spacing Requirements and Airflow .....   | 78        |
| Electrostatic Discharge .....  | 78        |
| Rack Specifications and Recommendations .....                                      | 78        |
| Mechanical Recommendations for the Rack .....                                      | 79        |
| Protective Grounding for the Rack .....  | 79        |
| Space Requirements for the Rack .....  | 79        |
| Securing the Rack .....  | 80        |
| Evaluating and Meeting Cable Requirements .....                                    | 80        |



|   |           |
|---|-----------|
| Cabling Standards .....   | 80        |
| Cable Labeling and Record Keeping .....   | 81        |
| Installing Cable .....  | 81        |
| Fiber Optic Cable .....   | 82        |
| Cable Distances .....   | 83        |
| RJ-45 Connector Jackets .....   | 84        |
| Radio Frequency Interference .....  | 84        |
| Meeting Power Requirements .....  | 85        |
| PoE Devices .....   | 85        |
| Power Supply Requirements .....   | 85        |
| AC Power Cables .....   | 85        |
| Uninterruptible Power Supply Requirements .....   | 86        |
| Selecting a UPS .....   | 86        |
| Calculating Volt-Amperage Requirements .....  | 86        |
| UPS Transition Time .....   | 87        |
| DC Power Requirements .....   | 87        |
| Applicable Industry Standards .....   | 87        |
| <b>Chapter 4: Installing Summit Family Switches .....</b>                                   | <b>89</b> |
| Safety Information .....  | 89        |
| Building a SummitStack Configuration .....  | 90        |
| Slot Numbers .....  | 90        |
| About Redundancy .....  | 91        |
| Placing Summit Family Switches for Stacked Operation .....                                  | 91        |
| Connecting the Switches to Form the Stack Ring .....  | 92        |
| Using Summit X650 Series Switches .....   | 93        |
| Using the VIM1-SummitStack512 Module .....  | 94        |
| Connecting a SummitStack 40G Cable to a Stacking Port .....                                 | 94        |
| Connecting a SummitStack 128G Cable .....   | 95        |
| Connecting the Console Port .....   | 95        |
| Management Port Cabling .....   | 96        |
| Stacking Port LEDs .....  | 96        |
| Installing a Summit Family Switch (Models Other than Summit X650 Series) .....              | 96        |
| Rack-Mounting a Summit Switch (Models Other than Summit X650 Series) .....                  | 97        |
| Free-Standing and Desktop Mounting of Multiple Switches .....                               | 98        |
| Removing an AC-Powered Summit Switch from a Rack (Models Other than Summit X650 Series) ... | 98        |
| Installing and Removing Summit DC-Powered Switches .....                                    | 98        |
| Connecting the Internal DC Power Supply to the DC Source Voltage .....                      | 99        |
| Grounding a Summit DC-Powered Switch .....  | 99        |
| Connecting the DC Wiring Harness to the DC Source Voltage .....                             | 101       |
| Attaching the DC Wiring Harness to the DC Power Socket on the Switch .....                  | 102       |
| Removing a Summit DC-Powered Switch from a Rack .....                                       | 102       |
| Installing a Summit X650 Series Switch .....  | 103       |
| Pre-installation Requirements .....   | 103       |
| Selecting Rear Mounting Brackets .....  | 104       |
| Installing the Switch in a Two-Post Rack .....  | 104       |
| Installing the Switch in a Cabinet or Four-Post Rack .....                                  | 107       |
| Installing Summit X650 Power Supplies .....   | 109       |
| AC Power Supply Cords .....   | 109       |
| Installing a Summit X650 AC Power Supply .....  | 109       |
| Installing a Summit X650 DC Power Supply .....  | 110       |

|   |            |
|---|------------|
| Required Tools and Materials .....  | 111        |
| Preparing the Cables .....  | 111        |
| Installing the Power Supply .....   | 112        |
| Connecting the Ground Cable .....   | 113        |
| Connecting the PSU to the DC Source Voltage.....                              | 114        |
| Removing Summit X650 Series Switches .....                                    | 116        |
| Removing the Power Supplies.....  | 116        |
| Removing a Summit X650 AC Power Supply' .....                                 | 117        |
| Removing a DC Power Supply.....   | 117        |
| Removing a Summit X650 Series Switch from a Two-Post Rack.....                | 118        |
| Removing a Summit X650 Series Switch from a Cabinet or Four-Post Rack .....   | 120        |
| Connecting Network Interface Cables .....                                     | 121        |
| Initial Management Access .....   | 122        |
| Connecting Equipment to the Console Port .....                                | 122        |
| Logging In for the First Time .....   | 123        |
| <b>Chapter 5: Installing Summit External Power Supplies.....</b>              | <b>125</b> |
| Safety .....  | 125        |
| Pre-installation Requirements .....   | 126        |
| Installing an EPS-160 External Power Module (with EPS-T) .....                | 126        |
| Rack-Mounting the EPS-T .....   | 126        |
| Installing an EPS-160 Power Supply into an EPS-T .....                        | 127        |
| Connecting the EPS-160 Power Supply to the Switch .....                       | 127        |
| Removing an EPS-160 Power Supply from an EPS-T .....                          | 129        |
| Installing an EPS-LD External Power Supply .....                              | 129        |
| Rack-mounting the EPS-LD Power Supply .....                                   | 129        |
| Connecting the EPS-LD to the Switch .....                                     | 130        |
| Connecting the EPS-LD to Power .....  | 131        |
| Removing an EPS-LD .....  | 132        |
| Installing an EPS-500 External Power Supply Unit .....                        | 132        |
| Rack-mounting an EPS-500 Power Supply .....                                   | 133        |
| Connecting the EPS-500 Power Supply .....                                     | 133        |
| Removing an EPS-500 Power Supply .....  | 135        |
| Installing an EPS-150DC External Power Module (with EPS-T2) .....             | 135        |
| Rack-mounting the EPS-T2 .....  | 136        |
| Installing an EPS-150DC Power Supply.....                                     | 136        |
| Connecting the DC Wiring Harness to the DC Source Voltage .....               | 137        |
| Installing an EPS-150DC Unit into an EPS-T2 .....                             | 138        |
| Connecting the DC Wiring Harness to the DC Power Socket on the EPS-150DC..... | 138        |
| Connecting the EPS-150DC to a Switch .....                                    | 138        |
| Removing an EPS-150DC Power Module .....                                      | 140        |
| Installing an EPS-600LS External Power Module .....                           | 140        |
| Installing an EPS-C Chassis .....   | 141        |
| Installing an EPS-600LS Power Supply .....                                    | 143        |
| Removing an EPS-600LS Power Module.....                                       | 145        |
| <b>Chapter 6: Summit Option Cards.....</b>                                    | <b>147</b> |
| Overview .....  | 147        |
| Safety Information .....  | 148        |
| Summit XGM-2xn Option Card.....   | 148        |

|   |            |
|---|------------|
| Mixing ZR XENPAKs with Other Types.....                                       | 149        |
| Summit XGM2-2xn Option Card.....  | 149        |
| Summit XGM2-2xf Option Card .....   | 150        |
| Summit XGM2-2sf Option Card .....   | 151        |
| Summit XGM2-2bt Option Card .....   | 151        |
| Installing a Summit Port Option Card .....                                    | 152        |
| <b>Chapter 7: Maintenance Procedures for Summit X650 Series Switches.....</b> | <b>155</b> |
| Replacing a Summit X650 AC PSU.....   | 155        |
| Replacing a Summit X650 DC Power Supply .....                                 | 157        |
| Removing the PSU .....  | 157        |
| Installing the Replacement PSU .....  | 158        |
| Connecting the Ground Wire.....   | 158        |
| Connecting the DC Power Cables .....  | 159        |
| Replacing a Summit X650 Fan Module .....                                      | 162        |
| Replacing a Versatile Interface Module (VIM).....                             | 163        |
| <b>Part 3: Appendices</b>   |            |
| <b>Appendix A: Safety Information .....</b>                                   | <b>167</b> |
| Considerations Before Installing .....  | 167        |
| Installing External Power Supply Units .....                                  | 168        |
| Maintenance Safety.....   | 169        |
| General Safety Precautions .....  | 169        |
| Cable Routing for LAN Systems .....   | 169        |
| PoE Devices .....   | 170        |
| Selecting Power Supply Cords .....  | 170        |
| Battery Replacement and Disposal.....   | 171        |
| Fiber Optic Ports—Optical Safety .....  | 171        |
| SFP (Mini-GBIC), XENPAK, and XFP Regulatory Compliance.....                   | 172        |
| <b>Appendix B: Technical Specifications .....</b>                             | <b>179</b> |
| Summit X150 Series Switches .....   | 179        |
| Summit X250e Series Switches.....   | 183        |
| Summit X350 Series Switches .....   | 189        |
| Summit X450 Series Switches .....   | 192        |
| Summit X450a Series Switches.....   | 194        |
| Summit X450e Series Switches.....   | 198        |
| Summit X650 Series Switches .....   | 201        |
| Summit X650 Power Supplies.....   | 206        |
| Summit External Power Supplies .....  | 207        |
| Console Connector Pinouts.....  | 212        |
| <b>Index.....</b>   | <b>215</b> |



# Preface

This preface provides an overview of this guide, describes guide conventions, and lists other publications that might be useful.



## WARNING!

*Service to all equipment should be performed by trained and qualified service personnel only. Before installing or removing any components of the system, or before carrying out any maintenance procedures, you must thoroughly read the safety information provided in [Appendix A](#) of this guide. Failure to follow this safety information can lead to personal injury or damage to the equipment.*

## Introduction

This guide provides the required information to install the following Extreme Networks® Summit® switches:

- Summit X150 series switches
- Summit X250e series switches
- Summit X350 series switches
- Summit X450 series switches
- Summit X450a series switches
- Summit X450e series switches
- Summit X650 series switches

The guide also contains information about site preparation, switch functionality, and switch operation.



## NOTE

*The Summit X150 series switches, Summit X250e series switches, Summit X350 series switches, Summit X450 series switches, Summit X450e series switches, and Summit X450a series switches are called the Summit family switches when referred to collectively.*

This guide is intended for use by network administrators responsible for installing and setting up network equipment. It assumes a basic working knowledge of:

- Local area networks (LANs)
- Ethernet concepts
- Ethernet switching and bridging concepts
- Routing concepts
- Simple Network Management Protocol (SNMP)

See the *ExtremeXOS Concepts Guide* and the *ExtremeXOS Command Reference Guide* for information about configuring Extreme Networks Summit family switches.

**NOTE**

If the information in the installation note or release note shipped with your Extreme Networks switch differs from the information in this guide, follow the installation or release note.

## Conventions

Table 1 and Table 2 list conventions used throughout this guide.

**Table 1: Notice Icons**

| Icon | Notice Type | Alerts you to...   |
|------|-------------|--|
|      | Note        | Important features or instructions.                      |
|      | Caution     | Risk of personal injury, system damage, or loss of data. |
|      | Warning     | Risk of severe personal injury.                          |

**Table 2: Text Conventions**

| Convention                   | Description   |
|------------------------------|---|
| Screen displays              | This typeface represents information as it appears on the screen, or command syntax.  |
| The words “enter” and “type” | When you see the word “enter” in this guide, you must type something, and then press the Return or Enter key. Do not press the Return or Enter key when an instruction simply says “type.”  |
| [Key] names                  | Key names appear in text in one of two ways: <ul style="list-style-type: none"> <li>Referenced by their labels, such as “the Return key” or “the Escape key”</li> <li>Written with brackets, such as [Return] or [Esc]</li> </ul> If you must press two or more keys simultaneously, the key names are linked with a plus sign (+). Example:<br>Press [Ctrl]+[Alt]+[Del]. |
| Words in italicized type     | Italics emphasize a point of information or denote new terms at the place where they are defined in the text. Book titles are printed in italics.   |

## Related Publications

The Extreme Networks ExtremeXOS® switch documentation set includes:

- *ExtremeXOS Concepts Guide*
- *ExtremeXOS Command Reference Guide*
- *ExtremeXOS Release Notes*
- *BlackDiamond® 20808 Switch Hardware Installation Guide*

- *BlackDiamond 10808 Switch Hardware Installation Guide*
- *BlackDiamond 12800 Series Switches Hardware Installation Guide*
- *BlackDiamond 8800 Series Switches Hardware Installation Guide*
- *Extreme Networks Pluggable Interface Modules Installation Guide*

Documentation for Extreme Networks products is available from the Extreme Networks website at the following location:

<http://www.extremenetworks.com/services/documentation>

You can select and download the following Extreme Networks documentation from the Documentation Overview page:

- Software User Guides
- Hardware Installation Guides

You can find archived user guides for software at:

<http://www.extremenetworks.com/services/documentation/swuserguides.asp>

You can also find archived installation guides for hardware at:

<http://www.extremenetworks.com/services/documentation/hwuserguides.asp>





---

**1**

## **About the Summit Family Switches**

---



# 1 Summit Family Switches

This chapter describes the Summit family switches and includes the following sections:

- [Overview of the Summit Switches on page 15](#)
- [Summit X150 Series Switches on page 18](#)
- [Summit X250e Series Switches on page 23](#)
- [Summit X350 Series Switches on page 35](#)
- [Summit X450 Series, X450a Series, and X450e Series Switches on page 40](#)
- [Summit X650 Series Switches on page 59](#)

## Overview of the Summit Switches

The Summit family switches are compact enclosures 1.75 inches high (1 U). They provide 24 or 48 high-density copper or fiber optic ports operating at speeds up to 10 Gbps, with combination copper/fiber uplink ports. PoE connections and options for adding 10-Gbps or 100 Gbps uplink connections are available on some models. Many Summit switches include high-speed stacking interfaces that allow you to connect up to eight Summit switches into a single SummitStack™ management entity. Summit models are available for AC or DC power connection; all Summit switches make provision for redundant power supplies. Most models have connections for optional external redundant power supplies; the Summit X650 series switches provide two bays for pluggable power supplies.

Most Summit models are available in versions that are compliant with the Trade Agreements Act (TAA); these versions are identified by a -TAA suffix on the model number. Functionally, the TAA-compliant models are completely equivalent to the matching versions that are not TAA-compliant. In all feature descriptions, references to a specific Summit switch model also apply to the equivalent TAA-compliant model.

[Table 3](#) and [Table 4 on page 16](#) list the Summit switch series and summarize the features available in each series.

**Table 3: Summit Switch Features—Summit X150, X250e, and 350 Series**

| Feature   | Summit X150 Series | Summit X250e Series | Summit 350 Series |
|---|--------------------|---------------------|-------------------|
| Maximum autonegotiating 10/100BASE-TX ports       | 26 or 50           | 26 or 50            | —                 |
| Maximum autonegotiating 10/100/1000-BASE-TX ports | 2                  | 24 or 48            | 24 or 48          |
| Maximum 1-Gbps Ethernet ports (SFP)               | 2                  | 2                   | 4                 |
| Maximum 10-Gbps Ethernet ports                    | —                  | 2                   | 2                 |
| SummitStack support                               | No                 | Yes                 | No                |
| Total switching capacity                          | 8.8–17.6 Gbps      | 48.8–97.6 Gbps      | 128–256 Gbps      |
| Redundant power                                   | Yes (external)     | Yes (external)      | Yes (external)    |
| DC power available                                | No                 | Yes                 | Yes               |
| Power over Ethernet (802.3af)                     | Yes                | Yes                 | No                |

**Table 4: Summit Switch Features—Summit X450, X450a, X450e, and X650 Series**

| Feature  | Summit X450 Series | Summit X450a Series | Summit X450e Series | Summit X650 Series                   |
|--|--------------------|---------------------|---------------------|--------------------------------------|
| Maximum autonegotiating 10/100BASE-TX ports        | —                  | —                   | —                   | —                                    |
| Maximum autonegotiating 10/100/1000-BASE-TX ports  | 24 or 48           | 24 or 48            | 24 or 48            | —                                    |
| Maximum 1-Gbps Ethernet ports (SFP)                | 4                  | 4                   | 4                   | 4                                    |
| Maximum 10-Gbps Ethernet ports (XFP, XENPAK, SFP+) | 2                  | 2                   | 2                   | 24 (default)<br>32 (with VIM1-10G8X) |
| SummitStack support                                | Yes                | Yes                 | Yes                 | Yes                                  |
| Total switching capacity                           | 128–256 Gbps       | 128–256 Gbps        | 128–256 Gbps        | 488–680 Gbps                         |
| Redundant power                                    | Yes (external)     | Yes (external)      | Yes (external)      | Yes (hot-swappable)                  |
| DC power available                                 | No                 | Yes                 | No                  | Yes                                  |
| Power over Ethernet (802.3af)                      | Yes                | Yes                 | Yes                 | No                                   |

Table 5 shows the switch models in each Summit series.

**Table 5: Summit Family Switches**

| Summit X150 Series | Summit X250e Series | Summit X350 Series | Summit X450 Series | Summit X450a Series | Summit X450e Series | Summit X650 Series |
|--------------------|---------------------|--------------------|--------------------|---------------------|---------------------|--------------------|
| Summit X150-24t    | Summit X250e-24t    | Summit X350-24t    | Summit X450-24t*   | Summit X450a-24t    | Summit X450e-24p    | Summit X650-24t**  |
| Summit X150-24p    | Summit X250e-24tDC  | Summit X350-48t    | Summit X450-24x*   | Summit X450a-24tDC  | Summit X450e-48p    | Summit X650-24x**  |
| Summit X150-48t    | Summit X250e-24p    |                    |                    | Summit X450a-24x    |                     |                    |
|                    | Summit X250e-24x    |                    |                    | Summit X450a-24xDC  |                     |                    |
|                    | Summit X250e-24xDC  |                    |                    | Summit X450a-48t    |                     |                    |
|                    | Summit X250e-48t    |                    |                    | Summit X450a-48tDC  |                     |                    |
|                    | Summit X250e-48p    |                    |                    |                     |                     |                    |

\*These Summit switch models are not available in TAA versions.

\*\*These Summit switch models do not have separate TAA and non-TAA versions; all Summit X650 series models are TAA-compliant.

Refer to the following sections for specific hardware details about each series:

- [Summit X150 Series Switches on page 18](#)
- [Summit X250e Series Switches on page 23](#)
- [Summit X350 Series Switches on page 35](#)
- [Summit X450 Series, X450a Series, and X450e Series Switches on page 40](#)
- [Summit X650 Series Switches on page 59](#)



#### NOTE

See the *ExtremeXOS Concepts Guide* and the *ExtremeXOS Command Reference Guide* for feature-specific information about the Summit switches and for information regarding switch configuration.

## Combination Ports and Failover

Summit family switches provide two or four uplink ports implemented as combination ports that pair a copper port using RJ-45 connectors with an optical port using LC connectors. The copper port operates as an autonegotiating 10/100/1000BASE-T port. The optical port allows Gigabit Ethernet uplink connections through Extreme Networks small form factor pluggable (SFP) interface modules. See the individual switch descriptions for the port numbers of the combination ports on each switch model.

Summit family switches support automatic failover from an active fiber port to a copper backup or from an active copper port to a fiber port. If one of the uplink connections fails, the Summit uplink connection automatically fails over to the second connection. To set up a redundant link on a combination port, connect the active 1000BASE-T and fiber links to both the RJ-45 and SFP interfaces of that port.

Gigabit Ethernet uplink redundancy on the Summit family switches follows these rules:

- With both the SFP and 1000BASE-T interfaces connected on a combination port, only one interface can be activated. The other is inactive.
- If only one interface is connected, the switch activates the connected interface.
- The switch determines whether the port uses the fiber or copper connection based on the order in which the connectors are inserted into the switch. When the switch senses that an SFP and a copper connector are inserted, the switch enables the uplink redundancy feature. For example, if you first connect copper ports 25 and 26 on a Summit XX250e-24t switch, and then insert SFPs into ports 25 and 26, the switch assigns the copper ports as active ports and the fiber ports as redundant ports.

Hardware determines when a link is lost and swaps the primary and redundant ports to maintain stability. After a failover occurs, the switch keeps the current port assignment until another failure occurs or a user changes the assignment using the CLI. For more information about configuring automatic failover on combination ports, see the *ExtremeXOS Concepts Guide*.

## Summit X150 Series Switches

The Summit X150 series switches provide 24 or 48 fixed 10/100BASE-T Ethernet ports that deliver high-density copper connectivity for 2.4 Gbps or 4.8 Gbps. Models are available with PoE and without PoE. Each Summit X150 series switch has two combination ports that provide 10/100/1000 BASE-T or SFP connectivity for 2 Gbps of copper or fiber connectivity. A serial console port on the front panel allows you to connect a terminal and perform local management. On the back of the switch, an Ethernet management port can be used to connect the system to a parallel management network for administration. Alternatively, you can use an Ethernet cable to connect this port directly to a laptop to view and locally manage the switch configurations.

The rear panel of the switch provides an AC power input socket and a redundant power connector. The internal power supply operates from 100 VAC to 240 VAC. The switch automatically adjusts to the supply voltage. The redundant power connector allows you to connect the switch to the EPS-160 or EPS-500 external power supply. When a compatible external power supply is used with the Summit X150 series switch, the internal and external power supplies are fully fault tolerant and load-sharing. If one power supply fails, the other power supply will provide sufficient power to operate the switch.

The Summit X150e series switches include the following switches:

- [Summit X150-24t Switch](#)
- Summit X150-24t-TAA Switch
- [Summit X150-24p Switch](#)
- Summit X150-24p-TAA Switch
- [Summit X150-48t Switch](#)
- Summit X150-48t-TAA Switch



### NOTE

*In the descriptions that follow, references to a Summit X150 series model number also apply to the equivalent TAA-compliant switch version.*

## Summit X150-24t Switch

The front panel of the Summit X150-24t switch (Figure 1) includes:

- Twenty-four fixed autosensing 10/100BASE-T ports (ports 1–24) that provide 2.4 Gbps of high-density copper connectivity
- Two combination ports (ports 25–26) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “Summit X150 Series Switch LEDs” on page 22.

- Serial console port used to connect a terminal and perform local management.


**Figure 1: Summit X150-24t Switch Front Panel**



The rear panel of the Summit X150-24t switch (Figure 2) includes:

- Ethernet management port with associated LEDs
- Redundant power input connector for optional connection to the EPS-160 External Power Module. See “EPS-160 External Power Module (with EPS-T)” on page 66 for more information. The connecting redundant power supply cable is shipped with the EPS-160 unit.
- AC power input socket

**Figure 2: Summit X150-24t Switch Rear Panel**



## Summit X150-24p Switch

The front panel of the Summit X150-24p switch (Figure 3) includes:

- Twenty-four fixed autosensing 10/100BASE-T PoE ports (ports 1–24). In addition to 4 Gbps of high-density copper connectivity, these ports also provide a full 15.4 Watts of PoE per port.
- Two combination ports (ports 25–26) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “Summit X150 Series Switch LEDs” on page 22.

- Serial console port used to connect a terminal and perform local management.

**Figure 3: Summit X150-24p Switch Front Panel**




The rear panel of the Summit X150-24p switch includes:

- Ethernet management port with associated LEDs
- Redundant power input connector for use optional connection to the EPS-500 External Power Supply (Model No. 10911) with full PoE power support.

See “EPS-500 External Power Supply Unit” on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-500 unit.

- AC power input socket

**Figure 4: Summit X150-24p Switch Rear Panel**





## Summit X150-48t Switch

The front panel of the Summit X150-48t switch (Figure 5) includes:

- Forty-eight fixed autosensing 10/100BASE-T ports (ports 1–48) that provide 4.8 Gbps of high-density copper connectivity
- Two combination ports (ports 49–50) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “Summit X150 Series Switch LEDs” on page 22.

- Serial console port used to connect a terminal and perform local management.


**Figure 5: Summit X150-48t Switch Front Panel**



The rear panel of the Summit X150-48t switch (Figure 6) includes:

- Management port with associated LEDs
- Redundant power input connector for optional connection to the EPS-160 External Power Module. See “EPS-160 External Power Module (with EPS-T)” on page 66 for more information. The connecting redundant power supply cable is shipped with the EPS-160 unit.
- AC power input socket

**Figure 6: Summit X150-48t Switch Rear Panel**



## Summit X150 Series Switch LEDs

Table 6 lists the of LEDs on the Summit X150 switches, along with their associated colors and meanings.

**Table 6: LEDs on the Summit X150 Series Switches**

| Label or Type   | Color/State                 | Meaning  |
|---|-----------------------------|--|
| <b>Front Panel</b>  |                             |  |
| <b>MGMT</b>   | Blinking green (fast)       | Power-on self-test (POST) in progress.   |
|   | Steady green                | POST passed. System is booting image.  |
|   | Blinking green (slow)       | Normal operation.  |
|   | Blinking amber              | Switch diagnostics are running.<br>or<br>System is disabled. POST failed or system overheated. |
|   | Off                         | No external power attached.  |
| <b>FAN</b>  | Steady green                | Normal operation.  |
|   | Blinking amber              | Fan failure. Switch will continue to operate unless it overheats.                              |
|   | Off                         | No power.  |
| <b>PSU-I<br/>(Internal power supply)</b>                            | Steady green                | Normal operation.  |
|   | Blinking amber              | Failure.   |
|   | Off                         | No power.  |
| <b>PSU-E<br/>(External power supply)</b>                            | Steady green                | Normal operation.  |
|   | Blinking amber              | Failure.   |
|   | Off                         | No external power attached.  |
| <b>Port number<br/>1 – 24 or 1 – 48</b>                             | Steady green                | Link is OK.  |
|   | Blinking green              | Port is transmitting packets.  |
|   | Off                         | Link is not present, or port is disabled.  |
| <b>Port number<br/>25, 26 or 49, 50<br/>(Shared ports)</b>          | Steady green                | Link is OK.  |
|   | Blinking green              | Activity.  |
|   | Off                         | Link is not present, or port is disabled.  |
| <b>Additional Port LED Meanings for PoE Switch: Summit X150-24p</b> |                             |  |
| <b>All front-panel ports</b>  | Steady green                | Link OK; port is not powered.  |
|   | Steady amber                | Link is OK; port is powered; no traffic.   |
|   | Blinking green              | Link is OK and transmitting packets; port is not powered.                                      |
|   | Blinking amber              | Link is OK and transmitting packets; port is powered.  |
|   | Slow blinking amber         | No link, or disabled port; port is powered.  |
|   | Alternating amber and green | Port has a power fault.  |
|   | Off                         | Port is not powered, has no link, or is disabled.  |
| <b>Rear Panel</b>   |                             |  |
| <b>Management Port</b>  | Right LED:<br>Steady green  | Link is OK.  |
|   | Left LED:<br>Blinking green | Activity.  |
|   | Both LEDs off               | Link is not present.   |

# Summit X250e Series Switches

The Summit X250e series switches provide 24 or 48 Ethernet ports that deliver high-density fast Ethernet connectivity using fixed 10/100/1000BASE-T ports or installable small form pluggable (SFP) optical modules. Fixed-port models are available either with or without PoE. Each Summit X250e series switch has two combination ports that provide 10/100/1000 BASE-T or SFP connectivity for 2 Gbps of copper or fiber connectivity. A serial console port on the front panel allows you to connect a terminal and perform local management. An Ethernet management port can be used to connect the system to a parallel management network for administration. Alternatively, you can use an Ethernet cable to connect this port directly to a laptop to view and locally manage the switch configurations.

On the back of the switch, two high-speed stacking ports allow you to combine multiple units into a single SummitStack™ management entity. The rear panel also provides an AC or DC power input socket and a redundant power connector. (See specific switch descriptions for more information about the power options.) The switch automatically adjusts to the supply voltage. The redundant power connector allows you to connect the switch to the EPS-160, EPS-500, or EPS-150DC external power supply. When a compatible external power supply is used with the Summit X250e series switch, the internal and external power supplies are fully fault tolerant and load-sharing. If one power supply fails, the other power supply will provide sufficient power to operate the switch.

The Summit X250e series switches include the following switches:

- [Summit X250e-24t Switch](#)
- Summit X250e-24t-TAA Switch
- [Summit X250e-24tDC Switch](#)
- Summit X250e-24tDC-TAA Switch
- [Summit X250e-24p Switch](#)
- Summit X250e-24p-TAA Switch
- [Summit X250e-24x Switch](#)
- Summit X250e-24x-TAA Switch
- [Summit X250e-24xDC Switch](#)
- Summit X250e-24xDC-TAA Switch
- [Summit X250e-48t Switch](#)
- Summit X250e-48t-TAA Switch
- [Summit X250e-48tDC Switch](#)
- Summit X250e-48tDC-TAA Switch
- [Summit X250e-48p Switch](#)
- Summit X250e-48p-TAA Switch



## NOTE

*In the descriptions that follow, references to a Summit X250e series model number also apply to the equivalent TAA-compliant switch version.*

## Summit X250e-24t Switch

The front panel of the Summit X250e-24t switch (Figure 7) includes:

- Twenty-four fixed autosensing 10/100BASE-T ports (ports 1–24) that provide 2.4 Gbps of high-density copper connectivity
- Two combination ports (ports 25–26) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “Summit X250e Series Switch LEDs” on page 34.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 7: Summit X250e-24t Switch Front Panel**



The rear panel of the Summit X250e-24t switch (Figure 8) includes:


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-160 External Power Module.

See “EPS-160 External Power Module (with EPS-T)” on page 66 for more information. The connecting redundant power supply cable is shipped with the EPS-160 unit.

- AC power input socket.

The internal AC power supply operates from 100 VAC to 240 VAC.

**Figure 8: Summit X250e-24t Switch Rear Panel**



## Summit X250e-24tDC Switch

The front panel of the Summit X250e-24tDC switch (Figure 33) includes:

- Twenty-four fixed autosensing 10/100BASE-T ports (ports 1–24) that provide 2.4 Gbps of high-density copper connectivity
- Two combination ports (ports 25–26) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “Summit X250e Series Switch LEDs” on page 34.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 9: Summit X250e-24tDC Switch Front Panel**



The rear panel of the Summit X250e-24tDC switch (Figure 34) includes:

- Ethernet management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-150DC External Power Module (Model No. 10909).


See “EPS-150DC External Power Module (with EPS-T2)” on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-150DC unit.

- DC power input socket  
The power supply operates from -36 VDC to -72 VDC.
- Grounding lug



### NOTE

For centralized DC power connection, this product is intended to be installed in a restricted access location (such as a dedicated equipment room, equipment closet, or central office) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.

**Figure 10: Summit X250e-24tDC Switch Rear Panel**

## Summit X250e-24p Switch

The front panel of the Summit X250e-24p switch (Figure 11) includes:


- Twenty-four fixed autosensing 10/100BASE-T PoE ports (ports 1–24). In addition to 2.4 Gbps of high-density copper connectivity, these ports also provide a full 15.4 Watts of PoE per port.
- Two combination ports (ports 25–26) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see [“Summit X250e Series Switch LEDs” on page 34](#).

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 11: Summit X250e-24p Switch Front Panel**

The rear panel of the Summit X250e-24p switch (Figure 12) includes:


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for use with the EPS-500 External Power Supply (Model No. 10911) with full PoE power support.

See “[EPS-500 External Power Supply Unit](#)” on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-500 unit.

- AC power input socket.

The internal AC power supply operates from 100 VAC to 240 VAC.

**Figure 12: Summit X250e-24p Switch Rear Panel**



## Summit X250e-24x Switch

The front panel of the Summit X250e-24x switch (Figure 7) includes:

- Twenty-four 100BASE-FX ports (ports 1–24) that provide 2.4 Gbps of high-density fiber connectivity
- Two combination ports (ports 25–26) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “[Summit X250e Series Switch LEDs](#)” on page 34.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 13: Summit X250e-24x Switch Front Panel**



The rear panel of the Summit X250e-24x switch (Figure 8) includes:


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for use with the EPS-160 External Power Module.

See “[EPS-160 External Power Module \(with EPS-T\)](#)” on page 66 for more information. The connecting redundant power supply cable is shipped with the EPS-160 unit.

- AC power input socket.

The internal AC power supply operates from 100 VAC to 240 VAC.

**Figure 14: Summit X250e-24x Switch Rear Panel**



SH\_039

## Summit X250e-24xDC Switch

The front panel of the Summit X250e-24xDC switch (Figure 7) includes:

- Twenty-four 100BASE-FX ports (ports 1–24) that provide 2.4 Gbps of high-density fiber connectivity
- Two combination ports (ports 25–26) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “[Summit X250e Series Switch LEDs](#)” on page 34.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 15: Summit X250e-24xDC Switch Front Panel**



SH\_059\_front\_x250e-24xdc



The rear panel of the Summit X250e-24xDC switch (Figure 8) includes:

- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for use with the EPS-150DC External Power Module (Model No. 10909).

See “[EPS-150DC External Power Module \(with EPS-T2\)](#)” on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-150DC unit.


- DC power input socket  
The power supply operates from -36 VDC to -72 VDC.
- Grounding lug



#### NOTE

For centralized DC power connection, this product is intended to be installed in a restricted access location (such as a dedicated equipment room, equipment closet, or central office) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.

**Figure 16: Summit X250e-24xDC Switch Rear Panel**




## Summit X250e-48t Switch

The front panel of the Summit X250e-48t switch (Figure 17):

- Forty-eight fixed autosensing 10/100BASE-T ports (ports 1–48) that provide 4.8 Gps of high-density copper connectivity
- Two combination port ports (ports 49–50) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.  
For a description of the LEDs and their operation, see “[Summit X250e Series Switch LEDs](#)” on page 34.
- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 17: Summit X250e-48t Switch Front Panel**

The rear panel of the Summit X250e-48t switch ([Figure 18](#)) includes:

- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-160 External Power Module. See “[EPS-160 External Power Module \(with EPS-T\)](#)” on [page 66](#) for more information. The connecting redundant power supply cable is shipped with the EPS-160 unit.
- AC power input socket.  
The internal AC power supply operates from 100 VAC to 240 VAC.

**Figure 18: Summit X250e-48t Switch Rear Panel**

## Summit X250e-48tDC Switch


The front panel of the Summit X250e-48tDC switch ([Figure 17](#)):

- Forty-eight fixed autosensing 10/100BASE-T ports (ports 1–48) that provide 4.8 Gps of high-density copper connectivity
- Two combination ports (ports 49–50) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.  
For a description of the LEDs and their operation, see “[Summit X250e Series Switch LEDs](#)” on [page 34](#).
- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 19: Summit X250e-48tDC Switch Front Panel**



The rear panel of the Summit X250e-48tDC switch (Figure 18) includes:

- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for use with the EPS-150DC External Power Module (Model No. 10909).

See “[EPS-150DC External Power Module \(with EPS-T2\)](#)” on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-150DC unit.


- DC power input socket.  
The power supply operates from -36 VDC to -72 VDC.
- Grounding lug



**NOTE**

For centralized DC power connection, this product is intended to be installed in a restricted access location (such as a dedicated equipment room, equipment closet, or central office) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.

**Figure 20: Summit X250e-48tDC Switch Rear Panel**




## Summit X250e-48p Switch

The front panel of the Summit X250e-48p switch (Figure 21) includes:

- Forty-eight fixed autosensing 10/100BASE-T PoE ports (ports 1–48). In addition to 4.8 Gbps of high-density copper connectivity, these ports provide a full 15.4 Watts of PoE per port when used with the EPS-600LS External Power Module.
- Two combination ports (ports 49–50) using RJ-45 connectors and SFPs to provide 2 Gbps of copper or fiber connectivity  
For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.
- LEDs to indicate port status and switch operating conditions.  
For a description of the LEDs and their operation, see “Summit X250e Series Switch LEDs” on page 34.
- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 21: Summit X250e-48p Switch Front Panel**



The rear panel of the Summit X250e-48p switch (Figure 22) includes:


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for use with one or more EPS-600LS External Power Modules (Model No. 10913) installed in an EPS-C chassis (Model No. 10912).

The PoE capability of the Summit X250e-48p switch varies depending on the number of external power modules in use. For more information, see “EPS-600LS External Power Module” on page 69. The connecting redundant power supply cable is shipped with the EPS-C chassis.

- AC power input socket.

The internal AC power supply operates from 100 VAC to 240 VAC.

**Figure 22: Summit X250e-48p Switch Rear Panel**



SH\_043

## Summit X250e-48p Power Supplies

The Summit X250e-48p switch is powered by both an internal power supply and an optional external redundant power supply system.

### Internal Power Supply

The internal Summit X250e-48p internal power supply is capable of 370 W of PoE power. It supplies 15.4 W to each port for a 24-port configuration and 7.7 W to each port for a 48-port configuration or any combination of ports where total PoE power does not exceed 370 watts. If the total system demands exceed this power limit, you can specify one of the following:

- Port priorities to identify which ports should be ranked higher when allocating power
- Port disconnect precedence to specify the method of shutting off ports when not enough PoE power is available



#### NOTE

A full discussion of these concepts can be found in the ExtremeXOS 12.0 Concepts Guide, *Power over Ethernet* section.

### External Power Supplies

The EPS-600LS External Power Module provides optional redundant power for the Summit X250e-48p switch. Through the redundant power input connector on the rear panel, the switch can be powered by one, two, or three external power modules installed in the EPS-C External Power Supply Chassis.

The PoE capability of the Summit X250e-48p varies depending on the number of external power modules in use. [Table 7](#) summarizes the PoE power behavior for the Summit X250e-48p switch based on the number of power supply modules in use.

**Table 7: Number of External Power Modules and Corresponding PoE Behavior**

| Internal Power Supply Status         | EPS-600LS (1x)               | EPS-600LS (2x)   | EPS-600LS (3x)   | External PSU/Chassis Failed/Disconnected |
|--------------------------------------|------------------------------|--|--|--|
| Internal power supply: Power on      | 370 W of redundant power     | 740 W of external power only<br><br>Internal power supply disabled | 740 W of external power only with 2:1 redundancy<br><br>Internal power supply disabled | 370 W of internal power only             |
| Internal power supply: Power Failure | 370 W of external power only | 740 W of external power only                                       | 740 W of external power only with 2:1 redundancy                                       | No PoE power                             |

For specifications and installation instructions for the external power module, see [“EPS-600LS External Power Module” on page 69](#).

## Summit X250e Series Switch LEDs

Table 8 describes the LEDs on the Summit X250e switches.

**Table 8: LEDs on the Summit X250e Series Switches**

| Label or Type  | Color/State                   | Meaning  |
|--|-------------------------------|--|
| <b>Front Panel</b>   |                               |  |
| <b>MGMT</b>  | Blinking green (fast)         | Power-on self-test (POST) in progress  |
|  | Steady green                  | POST passed. System is booting image.  |
|  | Blinking green (slow)         | Normal operation.  |
|  | Blinking amber                | Switch diagnostics are running.<br>or<br>System is disabled. POST failed or system overheated. |
|  | Off                           | No external power attached   |
| <b>FAN</b>   | Steady green                  | Normal operation   |
|  | Blinking amber                | Fan failure. Switch will continue to operate unless it overheats.                              |
|  | Off                           | No power   |
| <b>PSU-I<br/>(Internal power supply)</b>                   | Steady green                  | Normal operation   |
|  | Blinking amber                | Failure  |
|  | Off                           | No power   |
| <b>PSU-E<br/>(External power supply)</b>                   | Steady green                  | Normal operation   |
|  | Blinking amber                | Failure  |
|  | Off                           | No external power attached   |
| <b>Port number<br/>1 – 24 or 1 – 48</b>                    | Steady green                  | Link is OK.  |
|  | Blinking green                | Port is transmitting packets.  |
|  | Off                           | Link is not present, or port is disabled.  |
| <b>Port number<br/>25, 26 or 49, 50<br/>(Shared ports)</b> | Steady green                  | Link is OK   |
|  | Blinking green                | Port is transmitting packets.  |
|  | Off                           | Link is not present, or port is disabled.  |
| <b>Stack 1,2</b>   | Steady green                  | Link OK on the indicated stack port.   |
|  | Blinking green                | Activity on the indicated stack port.  |
| <b>Stack Number Indicator</b>                              | Top half of number blinking   | This switch is the stack master.   |
|  | Lower half of number blinking | This switch is the stack backup.   |
|  | Number lights steadily        | This switch is a standby switch (neither the master nor the backup).                           |

**Table 8: LEDs on the Summit X250e Series Switches (Continued)**

| Label or Type   | Color/State                 | Meaning   |
|---|-----------------------------|---|
| <b>Additional Port LED Meanings for PoE Switches: Summit X250e-24p &amp; Summit X250e-48p</b> |                             |   |
| <b>All front-panel ports</b>  | Steady green                | Link OK. port not powered.                        |
|   | Steady amber                | Link OK, port is powered, no traffic              |
|   | Blinking green              | Link OK, transmitting packets, port not powered.  |
|   | Blinking amber              | Link OK, transmitting packets, port is powered.   |
|   | Slow blinking amber         | No link or disabled port, port is powered         |
|   | Alternating amber and green | Port has a power fault.                           |
|   | Off                         | Port is not powered, has no link, or is disabled. |
| <b>Rear Panel</b>   |                             |   |
| <b>Management Port</b>  | Right LED: Steady green     | Link OK   |
|   | Left LED: Blinking green    | Activity  |
|   | Both LEDs off               | Link is not present.                              |
| <b>Stack Port 1, Stack Port 2</b>   | Steady green                | Link OK   |
|   | Blinking green              | Activity  |
|   | Off                         | No link   |

## Summit X350 Series Switches

The Summit X350 series switches provide 24 or 48 Ethernet ports that deliver high-density fast Ethernet connectivity using fixed 10/100/1000BASE-T ports. Each Summit X350 series switch has four combination ports that provide 10/100/1000 BASE-T or SFP connectivity for 2 Gbps of copper or fiber connectivity. A serial console port on the front panel allows you to connect a terminal and perform local management. An Ethernet management port can be used to connect the system to a parallel management network for administration. Alternatively, you can use an Ethernet cable to connect this port directly to a laptop to view and locally manage the switch configurations.

The rear panel of the switch has an option slot to accommodate one of the following Summit option cards:

- Summit XGM2-2xf option card, which allows you to add one or two 10-Gigabit XFP modules
- Summit XGM2-2xn option card, which allows you to add one or two 10-Gigabit XFP modules
- Summit XGM2-2bt option card, which allows you to add one or two fixed 10GBASE-T ports
- Summit XGM2-2sf option card, which allows you to add one or two 10-Gigabit SFP+ modules

For option card installation instructions, see [Chapter 4, “Summit Option Cards.”](#)

Power connectors on the rear panel of the switch include an AC power input socket and a redundant power connector. The internal AC power supply operates from 100 VAC to 240 VAC. The switch automatically adjusts to the supply voltage. The redundant power connector allows you to connect the switch to the EPS-500 external power supply. When a compatible external power supply is used with the Summit X350 series switch, the internal and external power supplies are fully fault tolerant and load-sharing. If one power supply fails, the other power supply provides sufficient power to operate the switch.

The Summit X350 series switches include the following switches:

- [Summit X350-24t Switch](#)
- Summit X350-24t-TAA Switch
- [Summit X350-48t Switch](#)
- Summit X350-48t-TAA Switch



#### NOTE

In the descriptions that follow, references to a Summit X350 series model number also apply to the equivalent TAA-compliant switch version.

## Summit X350-24t Switch


The front panel of the Summit X350-24t switch ([Figure 23](#)) includes:

- Twenty fixed autosensing 10/100/1000 BASE-T ports (ports 1–20) that provide 20 Gbps of high-density copper connectivity
- Four combination ports (ports 21–24) using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.
- Serial console port used to connect a terminal and perform local management.

**Figure 23: Summit X350-24t Switch Front Panel**



The rear panel of the Summit X350-24t switch ([Figure 24](#)) includes:

- Slot for the one of the following Summit option cards:
  - Summit XGM2-2xf option card, which allows you to add one or two 10-Gigabit XFP modules  
See [“Summit XGM2-2xf Option Card” on page 150](#).
  - Summit XGM2-2xn option card, which allows you to add one or two 10-Gigabit XFP modules  
See [“Summit XGM2-2xn Option Card” on page 149](#)
  - Summit XGM2-2bt option card, which allows you to add one or two fixed 10GBASE-T ports  
See [“Summit XGM2-2bt Option Card” on page 151](#)
  - Summit XGM2-2sf option card, which allows you to add one or two 10-Gigabit SFP+ modules  
See [“Summit XGM2-2sf Option Card” on page 151](#)




- Management port with associated LEDs
- Redundant power input connector for optional connection to the EPS-500 External Power Module (Model No. 10907).

See “[EPS-500 External Power Supply Unit](#)” on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-500 unit.

- AC power input socket

The power supply operates from 100 VAC to 240 VAC.

**Figure 24: Summit X350-24t Switch Rear Panel**



## Summit X350-48t Switch


The front panel of the Summit X350-48t switch ([Figure 39](#)) includes:

- Forty-four fixed autosensing 10/100/1000 BASE-T ports (ports 1-44) that provide 44 Gbps of high-density copper connectivity
- Four combination ports (ports 45-48) using RJ-45 connectors and SFPs to provide 4 Gbps of fiber or copper connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.  
For a description of the LEDs and their operation, see “[Summit X450, X450a, and X450e Series Switch LEDs](#)” on page 57.
- Serial console port used to connect a terminal and perform local management.

**Figure 25: Summit X350-48t Switch Front Panel**




The rear panel of the Summit X350-48t switch ([Figure 40](#)) includes:

- Slot for the one of the following Summit option cards:
  - Summit XGM2-2xn option card, which allows you to add one or two 10-Gigabit XFP modules  
See [“Summit XGM2-2xn Option Card”](#) on page 149.
  - Summit XGM2-2xf option card, which allows you to add one or two 10-Gigabit XFP modules  
See [“Summit XGM2-2xf Option Card”](#) on page 150.
  - Summit XGM2-2sf option card, which allows you to add one or two 10-Gigabit SFP+ modules  
See [“Summit XGM2-2sf Option Card”](#) on page 151.
  - Summit XGM2-2bt option card, which allows you to add one or two fixed 10GBASE-T ports  
See [“Summit XGM2-2bt Option Card”](#) on page 151.
- Management port with associated LEDs
- Redundant power input connector for optional connection to the EPS-500 External Power Supply Unit (Model No. 10911).

See [“EPS-500 External Power Supply Unit”](#) on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-500 power supply.

- AC power input socket  
The power supply operates from 100 VAC to 240 VAC.

**Figure 26: Summit X350-48t Switch Rear Panel**



SH\_067\_rear\_X350-48t

## Summit X350 Series Switch LEDs

Table 11 lists the LEDs and their associated colors and meanings.

**Table 9: LEDs on the Summit X350 Series Switches**

| Label or Type   | Color/State           | Meaning  |
|---|-----------------------|--|
| <b>Front Panel</b>  |                       |  |
| <b>MGMT</b>   | Blinking green (fast) | Power-on self-test (POST) in progress  |
|   | Steady green          | POST passed. System is booting image.  |
|   | Blinking green (slow) | Normal operation.  |
|   | Blinking amber        | Switch diagnostics are running.<br>or<br>System is disabled. POST failed or system overheated. |
| <b>FAN</b>  | Steady green          | Normal operation   |
|   | Blinking amber        | Failure  |
|   | Off                   | No power   |
| <b>PSU-I</b><br>(Internal power supply)   | Steady green          | Normal operation   |
|   | Blinking amber        | Failure  |
|   | Off                   | No power   |
| <b>PSU-E</b><br>(External power supply)   | Steady green          | Normal operation   |
|   | Blinking amber        | Failure  |
|   | Off                   | No external power attached   |
| <b>Front-panel Port LEDs</b>  |                       |  |
| <b>Ethernet Ports</b><br>1 – 24 or 1 – 48 (21 – 24<br>and 45 – 48 are shared ports) | Steady green          | Link OK  |
|   | Blinking green        | Activity   |
|   | Off                   | Link is not present.<br>or<br>Port is disabled.  |
| <b>Rear Panel</b>   |                       |  |
| <b>Management Port</b>  | Steady green          | Link OK  |
|   | Blinking green        | Activity   |
|   | Off                   | Link is not present.   |
| <b>SFP 1G Port</b>  | Steady green          | Link OK  |
|   | Blinking green        | Activity   |
| <b>XENPAK 10G Port</b>  | Steady green          | Link OK  |
|   | Blinking green        | Activity   |
|   | Off                   | Link down  |

## Summit X450 Series, X450a Series, and X450e Series Switches

The Summit X450 series, Summit X450a series, and Summit X450e series switches provide 24 or 48 Ethernet ports. These switches deliver high-density fast Ethernet connectivity using fixed 10/100/1000BASE-T ports or installable small form pluggable (SFP) optical modules. Models in different series are available both with and without PoE and in AC or DC power versions.

Each Summit X450, X450a, or X450e series switch has four combination ports that provide 10/100/1000 BASE-T or SFP connectivity for 4 Gbps of copper or fiber connectivity. A serial console port on the front panel allows you to connect a terminal and perform local management. An Ethernet management port on the back panel can be used to connect the system to a parallel management network for administration. Alternatively, you can use an Ethernet cable to connect the Ethernet management port directly to a laptop to view and locally manage the switch configurations.

The rear panel of the switch has an option slot to accommodate one of the following Summit option cards:

- Summit XGM-2xn option card, which allows you to add one or two 10-gigabit XENPAK modules
- Summit XGM2-2xn option card, which allows you to add one or two 10-gigabit XENPAK modules
- Summit XGM2-2xf option card, which allows you to add one or two 10-Gigabit XFP modules

Option card compatibility depends on the specific switch series. See the individual switch descriptions for the option card supported on each switch. For option card installation instructions, see [Chapter 4, “Summit Option Cards.”](#)

Two high-speed stacking ports allow you to combine multiple units into a single SummitStack™ management entity. Power connectors include an AC or DC power input socket and a redundant power connector. (See specific switch descriptions for more information about the power options.) The switch automatically adjusts to the supply voltage. The redundant power connector allows you to connect the switch to the an external power supply. When a compatible external power supply is used with the Summit X450, X450a, or X450e series switch, the internal and external power supplies are fully fault tolerant. For most switches, if one power supply fails, the other power supply will provide sufficient power to operate the switch. For information about power supply redundancy with the Summit X450a-48p switch, see [“Summit X450e-48p Power Supplies” on page 56.](#)

For information about each switch series, see the following sections:

- [Summit X450 Series Switches on page 41](#)
- [Summit X450a Series Switches on page 44](#)
- [Summit X450e Series Switches on page 53](#)

## Summit X450 Series Switches

The Summit X450 series switches are 24-port switches without PoE options. The ports are implemented as fixed 10/100/1000BASE-t RJ-45 ports or as installable SFP modules. These switches are available only with AC internal power supplies.

The Summit X450 series of switches consists of the following switches:

- [Summit X450-24t Switch](#)
- [Summit X450-24x Switch](#)

### Summit X450-24t Switch


The front panel of the Summit X450-24t switch ([Figure 27](#)) includes:

- Twenty fixed autosensing 10/100/1000 BASE-T ports (ports 5-24) that provide 20 Gbps of high-density copper connectivity
- Four combination ports (ports 1-4) using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.
- For a description of the LEDs and their operation, see [“Summit X450, X450a, and X450e Series Switch LEDs” on page 57](#).
- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 27: Summit X450-24t Switch Front Panel**



The rear panel of the Summit X450-24t switch ([Figure 28](#)) includes:


- Slot for the Summit XGM-2xn option card, which allows you to add one or two 10-Gigabit XENPAK modules
- For information about the Summit XGM-2xn option card, see [“Summit XGM-2xn Option Card” on page 148](#).
- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs

- Redundant power input connector for optional connection to the EPS-160 External Power Module (Model No. 10907).

See “[EPS-160 External Power Module \(with EPS-T\)](#)” on page 66 for more information. The connecting redundant power supply cable is shipped with the EPS-160 unit.

- AC power input socket  
The power supply operates from 100 VAC to 240 VAC.

**Figure 28: Summit X450-24t Switch Rear Panel**




## Summit X450-24x Switch

The front panel of the Summit X450-24x switch ([Figure 29](#)) includes:

- Twenty fixed SFP ports (ports 5-24) that provide 20 Gbps of high-density fiber connectivity  
For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.
- Four combination ports (ports 1-4) using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity
- LEDs to indicate port status and switch operating conditions.  
For a description of the LEDs and their operation, see “[Summit X450, X450a, and X450e Series Switch LEDs](#)” on page 57.
- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 29: Summit X450-24x Switch Front Panel**



The rear panel of the Summit X450-24x switch (Figure 30) includes:

- Slot for the Summit XGM-2xn option card, which allows you to add one or two 10-gigabit XENPAK modules

For information about the Summit XGM-2xn option card, see [“Summit XGM-2xn Option Card” on page 148](#).


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-160 External Power Module (Model No. 10907).

See [“EPS-160 External Power Module \(with EPS-T\)” on page 66](#) for more information. The connecting redundant power supply cable is shipped with the EPS-160 unit.

- AC power input socket

The power supply operates from 100 VAC to 240 VAC.

**Figure 30: Summit X450-24x Switch Rear Panel**



S450\_003A

## Summit X450a Series Switches

The Summit X450a series switches are 24-port or 48-port switches without PoE options. The Ethernet ports are implemented as fixed 10/100/1000BASE-T RJ-45 ports or as installable SFP modules. These switches are available with either AC or DC internal power supplies. The switch automatically adjusts to the supply voltage. The internal AC power supply operates from 100 VAC to 240 VAC. The internal DC power supply operates from -36 VDC to -72 VDC.

The Summit X450a series switches include the following switches:

- [Summit X450a-24t Switch](#)
- Summit X450a-24t-TAA Switch
- [Summit X450a-24tDC Switch](#)
- Summit X450a-24tDC-TAA Switch
- [Summit X450a-24x Switch](#)
- Summit X450a-24x-TAA Switch
- [Summit X450a-24xDC Switch](#)
- Summit X450a-24xDC-TAA Switch
- [Summit X450a-48t Switch](#)
- Summit X450a-48t-TAA Switch
- [Summit X450a-48tDC Switch](#)
- Summit X450a-48tDC-TAA Switch



### NOTE

*In the descriptions that follow, references to a Summit X450a series model number also apply to the equivalent TAA-compliant switch version.*

### Summit X450a-24t Switch

The front panel of the Summit X450a-24t switch ([Figure 31](#)) includes:

- Twenty fixed autosensing 10/100/1000 BASE-T ports (ports 1-20) that provide 20 Gbps of high-density copper connectivity
- Four combination ports (ports 21-24) using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.


- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see [“Summit X450, X450a, and X450e Series Switch LEDs”](#) on page 57.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.



**Figure 31: Summit X450a-24t Switch Front Panel**



The rear panel of the Summit X450a-24t switch (Figure 32) includes:

- Slot for one of the following Summit option cards:
  - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
  - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules


For information about these Summit option cards, see [“Summit XGM2-2xn Option Card” on page 149](#) or [“Summit XGM2-2xf Option Card” on page 150](#).

- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to a redundant power supply, either the EPS-LD External Power Supply Unit (Model No. 45019) or the EPS-500 External Power Supply (Model 10911). The connecting redundant power supply cable is shipped with the external power supply.

For more information about the external power supplies, see [“EPS-LD External Power Supply Unit” on page 67](#) or [“EPS-500 External Power Supply Unit” on page 68](#).

- AC power input socket  
The power supply operates from 100 VAC to 240 VAC.

**Figure 32: Summit X450a-24t Switch Rear Panel**



SH\_028

## Summit X450a-24tDC Switch

The front panel of the Summit X450a-24tDC switch ([Figure 33](#)) includes:

- Twenty fixed autosensing 10/100/1000 BASE-T ports (ports 1-20) that provide 20 Gbps of high-density copper connectivity
- Four combination ports (ports 21-24) using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “[Summit X450, X450a, and X450e Series Switch LEDs](#)” on page 57.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 33: Summit X450a-24tDC Switch Front Panel**



The rear panel of the Summit X450a-24tDC switch ([Figure 34](#)) includes:

- Slot for one of the following Summit option cards:
  - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
  - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules

For information about these Summit option cards, see “[Summit XGM2-2xn Option Card](#)” on page 149 or “[Summit XGM2-2xf Option Card](#)” on page 150.

- Ethernet management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-150DC External Power Module (Model No. 10909).

See “[EPS-150DC External Power Module \(with EPS-T2\)](#)” on page 68 for more information. The connecting redundant power supply cable is shipped with the EPS-150DC unit.

- DC power input socket  
The power supply operates from -36 VDC to -72 VDC.
- Grounding lug



The rear panel of the Summit X450a-24x switch ([Figure 36](#)) includes:

- Slot for one of the following Summit option cards:
  - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
  - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules

For information about these Summit option cards, see [“Summit XGM2-2xn Option Card” on page 149](#) or [“Summit XGM2-2xf Option Card” on page 150](#).


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to an external redundant power supply, either the EPS-LD External Power Supply Unit (Model No. 45019) or the EPS-500 External Power Supply (Model 10911). The connecting redundant power supply cable is shipped with the external power supply.

For more information about the external power supplies, see [“EPS-LD External Power Supply Unit” on page 67](#) or [“EPS-500 External Power Supply Unit” on page 68](#).

- AC power input socket

The power supply operates from 100 VAC to 240 VAC.

**Figure 36: Summit X450a-24x Switch Rear Panel**



SH\_031

## Summit X450a-24xDC Switch

The front panel of the Summit X450a-24xDC switch ([Figure 37](#)) includes:

- Twenty fixed autosensing 1000BASE-X ports (ports 1-20) that provide 20 Gbps of high-density fiber (SFP) connectivity
- Four combination ports (ports 21-24). using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see [“Summit X450, X450a, and X450e Series Switch LEDs”](#) on page 57.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 37: Summit X450a-24xDC Switch Front Panel**



The rear panel of the Summit X450a-24xDC switch ([Figure 38](#)) includes:

- Slot for one of the following Summit option cards
  - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
  - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules

For information about these Summit option cards, see [“Summit XGM2-2xn Option Card”](#) on page 149 or [“Summit XGM2-2xf Option Card”](#) on page 150.

- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-150DC External Power Module (Model No. 10909). The connecting redundant power supply cable is shipped with the EPS-150DC unit.


See [“EPS-150DC External Power Module \(with EPS-T2\)”](#) on page 68 for more information.

- DC power input socket  
The power supply operates from -36 V DC to -72 V DC.
- Grounding lug

**NOTE**

For centralized DC power connection, this product is intended to be installed in a restricted access location (such as a dedicated equipment room, equipment closet, or central office) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.

**Figure 38: Summit X450a-24xDC Switch Rear Panel**



## Summit X450a-48t Switch

The front panel of the Summit X450a-48t switch (Figure 39) includes:

- Forty-four fixed autosensing 10/100/1000 BASE-T ports (ports 1-44) that provide 44 Gbps of high-density copper connectivity
- Four combination ports (ports 45-48) using RJ-45 connectors and SFPs to provide 4 Gbps of fiber or copper connectivity


For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see [“Summit X450, X450a, and X450e Series Switch LEDs”](#) on page 57.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 39: Summit X450a-48t Switch Front Panel**



The rear panel of the Summit X450a-48t switch ([Figure 40](#)) includes:

- Slot for one of the following Summit option cards
  - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
  - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules

For information about these Summit option cards, see [“Summit XGM2-2xn Option Card” on page 149](#) or [“Summit XGM2-2xf Option Card” on page 150](#).


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-500 External Power Supply Unit (Model No. 10911). The connecting redundant power supply cable is shipped with the EPS-500 power supply.

See [“EPS-500 External Power Supply Unit” on page 68](#) for more information.

- AC power input socket

The power supply operates from 100 VAC to 240 VAC.

**Figure 40: Summit X450a-48t Switch Rear Panel**




SH\_029

## Summit X450a-48tDC Switch

The front panel of the Summit X450a-48tDC switch ([Figure 39](#)) includes:

- Forty-four fixed autosensing 10/100/1000 BASE-T ports (ports 1-44) that provide 44 Gbps of high-density copper connectivity
  - Four combination ports (ports 45-48) using RJ-45 connectors and SFPs
- For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.
- LEDs to indicate port status and switch operating conditions.
- For a description of the LEDs and their operation, see [“Summit X450, X450a, and X450e Series Switch LEDs” on page 57](#).
- Stack number indicator showing the position of this switch in a stacked configuration.
  - Serial console port used to connect a terminal and perform local management.


**Figure 41: Summit X450a-48tDC Switch Front Panel**

The rear panel of the Summit X450a-48tDC switch (Figure 40) includes:

- Slot for one of the following Summit option cards:
    - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
    - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules
 For information regarding these compatible Summit option cards, see [“Summit XGM2-2xn Option Card” on page 149](#) or [“Summit XGM2-2xf Option Card” on page 150](#).
  - Management port with associated LEDs
  - Two high-performance stacking ports with associated LEDs
  - Redundant power input connector for optional connection to the EPS-150DC External Power Module (Model No. 10909). The connecting redundant power supply cable is shipped with the EPS-150DC unit.
- See [“EPS-500 External Power Supply Unit” on page 68](#) for more information.
- DC power input socket
- The power supply operates from -36 V DC to -72 V DC.
- Grounding lug

**NOTE**

For centralized DC power connection, this product is intended to be installed in a restricted access location (such as a dedicated equipment room, equipment closet, or central office) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.

**Figure 42: Summit X450a-48tDC Switch Rear Panel**



## Summit X450e Series Switches

The Summit X450e series switches are 24-port or 48-port PoE-capable switches. The Ethernet ports are implemented as fixed 10/100/1000BASE-T RJ-45 ports. These switches are available only with AC internal power supplies.

The Summit X450e series of switches consists of the following switches:

- [Summit X450e-24p Switch](#)
- Summit X450e-24p-TAA Switch
- [Summit X450e-48p Switch](#)
- Summit X450e-48p-TAA Switch



### NOTE

In the descriptions that follow, references to a Summit X450e series model number also apply to the equivalent TAA-compliant switch version.

### Summit X450e-24p Switch

The front panel of the Summit X450e-24p switch ([Figure 43](#)) includes:

- Twenty fixed autosensing 10/100/1000 BASE-T PoE ports (ports 1-20) that provide high-density copper connectivity and a full 15.4 Watts of PoE per port
- Four combination ports (ports 21-24) using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.




### NOTE

All 24 ports can provide PoE power.

- LEDs to indicate port status and switch operating conditions.  
For a description of the LEDs and their operation, see [“Summit X450, X450a, and X450e Series Switch LEDs”](#) on page 57.
- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 43: Summit X450e-24p Switch Front Panel**



The rear panel of the Summit X450e-24p switch (Figure 44) includes:

- Slot for one of the following Summit option cards:
  - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
  - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules

For information about these Summit option cards, see “Summit XGM2-2xn Option Card” on page 149 or “Summit XGM2-2xf Option Card” on page 150.


- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to an external redundant power supply with full PoE power support, either the EPS-LD External Power Supply Unit (Model 45019) or the EPS-500 External Power Supply (Model 10911). The connecting redundant power supply cable is shipped with the power supply.

See “EPS-LD External Power Supply Unit” on page 67 or “EPS-500 External Power Supply Unit” on page 68 for more information.

- AC power input socket

The power supply operates from 100 VAC to 240 VAC.

**Figure 44: Summit X450e-24p Switch Rear Panel**



SH\_027

## Summit X450e-48p Switch

The front panel of the Summit X450e-48p switch (Figure 45) includes:

- Forty-four fixed autosensing 10/100/1000 BASE-T PoE ports (ports 1-44) that provide high-density copper connectivity and a full 15.4 Watts of PoE per port when used with the EPS-C/EPs-600LS
- Four combination ports (ports 45-48) using RJ-45 connectors and SFPs to provide 4 Gbps of copper or fiber connectivity

For information about SFPs, see the *Extreme Networks Pluggable Interface Modules Installation Guide*.



### NOTE


All 48 ports are capable of providing PoE power

- LEDs to indicate port status and switch operating conditions.

For a description of the LEDs and their operation, see “[Summit X450, X450a, and X450e Series Switch LEDs](#)” on page 57.

- Stack number indicator showing the position of this switch in a stacked configuration.
- Serial console port used to connect a terminal and perform local management.

**Figure 45: Summit X450e-48p Switch Front Panel**



The rear panel of the Summit X450e-48p switch (Figure 46) includes:


- Slot for one of the following Summit option cards:
  - Summit XGM2-2xn option card, which allows you to add up to two 10-Gigabit XENPAK modules
  - Summit XGM2-2xf option card, which allows you to add up to two 10-Gigabit XFP modules

For information about these Summit option cards, see “[Summit XGM2-2xn Option Card](#)” on page 149 or “[Summit XGM2-2xf Option Card](#)” on page 150.

- Management port with associated LEDs
- Two high-performance stacking ports with associated LEDs
- Redundant power input connector for optional connection to the EPS-C chassis (Model No. 10912). This chassis can hold up to three EPS-600LS External Power Modules (Model No. 10913). The connecting redundant power supply cable is shipped with the EPS-C chassis.

The PoE capability of the Summit X450e-48p switch varies depending on the number of external power modules in use. For more information, see “[Summit X450e-48p Power Supplies](#)” on page 56 and “[EPS-600LS External Power Module](#)” on page 69.

- AC power input socket  
The power supply operates from 100 VAC to 240 VAC.

**Figure 46: Summit X450e-48p Switch Rear Panel**

## Summit X450e-48p Power Supplies

The Summit X450e-48p switch is powered by both an internal power supply and an optional external redundant power supply system.

**Internal Power Supply.** The internal Summit X450e-48p power supply is capable of 370 W of PoE power: 15.4 W supplied to each port for a 24-port configuration and 7.7 W supplied to each port for a 48-port configuration or any combination of ports where total PoE power does not exceed 370 watts. If the total system demands exceed this power limit, you can specify:

- Port priorities to identify which ports should be ranked higher when allocating power
- Port disconnect precedence to specify the method of shutting off ports when not enough PoE power is available



### NOTE

A full discussion of these concepts is in the *ExtremeXOS 12.0 Concepts Guide, Power over Ethernet* section.

**External Power Supplies.** The Summit X450e-48p switch can be powered by one, two, or three external power modules through the redundant power input connector on the rear of the switch.

The EPS-C (External Power Supply Chassis) is shipped with the redundant power supply cable that connects to the redundant input connector on the rear of the switch. The EPS-C chassis can hold from one to three 600-Watt EPS-600LS (External Power Module) units.

The PoE capability of the Summit X450e-48p switch varies depending on the number of external power modules in use. [Table 10](#) summarizes the PoE power behavior for the Summit X450e-48p switch based on the number of power supply modules in use.

**Table 10: Number of External PSUs and Corresponding PoE Behavior**

| Internal PSU Status                | EPS-600LS (1x)               | EPS-600LS (2x)  | EPS-600LS (3x)  | External PSU/Chassis Failed/Disconnected |
|------------------------------------|------------------------------|---|---|--|
| <b>Internal PSU: Power On</b>      | 370 W of redundant power     | 740 W of external power only<br>Internal PSU disabled | 740 W of external power only with 2:1 redundancy<br>Internal PSU disabled | 370 W of internal power only             |
| <b>Internal PSU: Power Failure</b> | 370 W of external power only | 740 W of external power only                          | 740 W of external power only with 2:1 redundancy                          | No PoE power                             |

For more information, see [“EPS-600LS External Power Module” on page 69](#).

## Summit X450, X450a, and X450e Series Switch LEDs

Table 11 describes the LEDs for the Summit X450, X450a, and X450e switches.

**Table 11: LEDs on the Summit X450, X450a, and X450e Switches**

| Label or Type   | Color/State  | Meaning  |
|---|--|--|
| <b>Front Panel</b>  |  |  |
| <b>MGMT</b>   | Blinking green (fast)  | Power-on self-test (POST) in progress.   |
|   | Steady green   | POST passed. System is booting image.  |
|   | Blinking green (slow)  | Normal operation   |
|   | Blinking amber   | Switch diagnostics running.<br>or<br>System is disabled. POST failed or system overheated.   |
|   | Off  | No external power attached   |
| <b>FAN</b>  | Steady green   | Normal operation   |
|   | Steady amber*  | A single fan in the array has failed. The switch can continue to operate indefinitely.*  |
|   | Blinking amber   | Failure<br>or<br>Two or more fans in the array have failed. Because system cooling is compromised, you should replace the switch.* |
|   | Off  | No power   |
|   | * These states for the Fan LED occur only on Summit X450a-48tDC switches with a manufacturing part number of 800294-00 and X450a-48tDC-TAA switches with a manufacturing part number of 800337-00. |  |
| <b>PSU-I</b><br>(Internal power supply)   | Steady green   | Normal operation   |
|   | Blinking amber   | Failure  |
|   | Off  | No power   |
| <b>PSU-E</b><br>(External power supply)   | Steady green   | Normal operation   |
|   | Blinking amber   | Failure  |
|   | Off  | No external power attached   |
| <b>Ethernet Ports</b><br>1 – 24 or 1 – 48 (21 –24 and 45 – 48 are shared ports) | Steady green   | Link OK  |
|   | Blinking green   | Activity   |
|   | Off  | Link is not present or port is disabled.   |
| <b>Stack Number Indicator</b>   | Top half of number blinking  | This switch is the stack master.   |
|   | Lower half of number blinking  | This switch is the stack backup.   |
|   | Number lights steadily   | This switch is a standby node (neither the master nor the backup).   |
|   | LED dark   | This stackable switch is not in stacking mode.   |

**Table 11: LEDs on the Summit X450, X450a, and X450e Switches (Continued)**

| Label or Type   | Color/State                 | Meaning                                  |
|---|-----------------------------|--|
| <b>Additional Port LED meanings for PoE switches: Summit X450e-24p &amp; Summit X450e-48p</b> |                             |  |
| <b>All front-panel ports</b>  | Steady amber                | Port is powered with link, no traffic    |
|   | Blinking amber              | Port is powered with link, traffic       |
|   | Slow blinking amber         | Port is powered, with no link            |
|   | Alternating amber and green | Port is faulted                          |
|   | Off                         | Port is not powered, no link or disabled |
| <b>Rear Panel</b>   |                             |  |
| <b>Management Port</b>  | Steady green                | Link OK                                  |
|   | Blinking green              | Activity                                 |
| <b>Stacking Port</b>  | Steady green                | Link OK                                  |
|   | Blinking green              | Activity                                 |
| <b>SFP 1G Port</b>  | Steady green                | Link OK                                  |
|   | Blinking green              | Activity                                 |
| <b>XENPAK 10G Port</b>  | Steady green                | Link OK                                  |
|   | Blinking green              | Activity                                 |
|   | Off                         | Link down                                |

# Summit X650 Series Switches

The Summit X650 series switches provide 24 front-panel Ethernet ports that deliver 10-Gigabit Ethernet connectivity using fixed 10GBASE-T RJ-45 ports or installable SFP+ optical modules.

The Summit X650 series switches include the following base models:

- [Summit X650-24t Switch](#)
- [Summit X650-24x Switch](#)

The rear panel of the switch requires an installed option card called a versatile interface module or VIM. The available types of VIM are:

- VIM1-SummitStack versatile interface module
- VIM1-10G8X versatile interface module
- VIM1-SummitStack512 versatile interface module



## NOTE

---

*VIMs are not hot-swappable. You must power off the switch before you remove or install a VIM.*

A serial console port on the front panel of the Summit X650 series switch allows you to connect a terminal and perform local management. An Ethernet management port can be used to connect the system to a parallel management network for administration. Alternatively, you can use an Ethernet cable to connect this port directly to a laptop to view and locally manage the switch configurations. The Ethernet management port supports 10/100/1000 Mbps speeds.

The rear panel of the switch has a replaceable versatile interface module (VIM) that provides one of the following port options:


- Two 40-Gigabit stacking ports and four 1-gigabit SFP ports
- Two 40-Gigabit stacking ports and eight 10-gigabit SFP+ ports
- Four 128-Gbps stacking ports

Cooling is provided by a replaceable fan module. Two power supply bays accommodate either AC or DC power supplies.

## Summit X650-24t Switch

The front panel of the Summit X450-24t switch ([Figure 47](#)) includes:


- Twenty-four fixed autosensing 1000/10000 BASE-T ports (ports 1-24) that provide high-density copper connectivity
- 10/100/1000 Mbps management port
- Console port
- LEDs
- Stack number indicator

**Figure 47: Summit X650-24t Front Panel**

SH\_075

The rear panel of the Summit X650-24t switch (Figure 48) includes:

- Installed virtual interface module (VIM) (VIM1-SummitStack shown)
- Replaceable fan tray
- Two power supply bays for either AC or DC power supplies

**Figure 48: Summit X650-24t Rear Panel**

SH\_077



## Summit X650-24x Switch


The front panel of the Summit X650-24x switch (Figure 49) includes:

- Twenty-four ports that can use 10GBASE-X SFP+ optical modules. (Ports 1-24 can also be populated with 1000BASE-X SFP modules.)

For information about supported optical modules, see the latest version of the ExtremeXOS release notes.

- 10/100/1000 Mbps management port
- Console port
- LEDs
- Stack number indicator

**Figure 49: Summit X650-24x Front Panel**




SH\_076

The rear panel of the Summit X650-24x switch (Figure 50) includes:

- Installed virtual interface module (VIM) (VIM1-SummitStack shown)
- Replaceable fan tray
- Two power supply bays for either AC or DC power supplies

**Figure 50: Summit X650-24x Rear Panel**



SH\_077


## VIM1-SummitStack Versatile Interface Module

The VIM1-SummitStack versatile interface module (Figure 51) provides four cages for installed SFP optical modules. These ports (numbered 25 through 28) function the same as the front-panel ports. The VIM1-SummitStack module supports 1000-BASE SFPs. For a complete list of supported SFPs, refer to the most recent version of the ExtremeXOS release notes.

The VIM1-SummitStack module also provides two high-performance stacking ports that allow you to combine multiple units into a single SummitStack management entity. The VIM1-SummitStack module is the default VIM1 module shipped with the base Summit X650 platform. Ports 23 and 24 of the front panel are shared with the two rear-panel stacking ports on the VIM1-SummitStack module.

By default, stacking is not enabled, and all 24 front panel ports are available. When stacking is enabled, you have access to 22 10GBASE ports and 2 stacking ports. For more information about configuring and operating a SummitStack configuration, refer to the *ExtremeXOS Concepts Guide* and the *ExtremeXOS Command Reference Guide*.

**Figure 51: VIM1-SummitStack Versatile Interface Module**




## VIM1-10G8X Versatile Interface Module

The VIM1-10G8X versatile interface module (Figure 52) provides eight cages for installed SFP or SFP+ optical modules. For information about the supported optical modules, refer to the most recent version of the ExtremeXOS release notes.

The VIM1-10G8X module also provides two high-performance stacking ports that allow you to combine multiple units into a single SummitStack management entity. The stacking ports on the VIM1-10G8X module are not shared with the front panel ports.

**Figure 52: VIM1-10G8X Versatile Interface Module**




## VIM1-SummitStack512 Versatile Interface Module

The VIM1-SummitStack512 versatile interface module (Figure 53) provides four 128-Gbps stacking ports that are used to cross-connect two Summit X650 series switches. Each switch must have an installed VIM1-SummitStack512 module. To connect these ports, you must use stacking cables with compatible connectors, available from Extreme Networks.

The VIM1-SummitStack512 module requires ExtremeXOS® 12.3.3 software (or later) installed on the Summit X650 series switch.

**Figure 53: VIM1-SummitStack512 Versatile Interface Module**



## Summit X650 Series Switch LEDs

Table 12 describes the LEDs on the Summit X650 series switches.

**Table 12: LEDs on the Summit X650 Series Switches**

| Label or Type                         | Color/State         | Meaning   |
|---------------------------------------|---------------------|---|
| <b>Front Panel LEDs</b>               |                     |   |
| <b>MGMT</b>                           | Blinking Green      | Normal operation  |
|                                       | Blinking Amber      | Power-on self test (POST) failed; diagnostic test in progress           |
|                                       | Off                 | No external power attached  |
| <b>FAN</b>                            | Steady Green        | Normal operation  |
|                                       | Blinking Amber      | Failure   |
|                                       | Off                 | No power  |
| <b>PSU-1</b>                          | Steady Green        | Normal operation  |
|                                       | Blinking Amber      | Failure   |
|                                       | Off                 | No power  |
| <b>PSU-2</b>                          | Steady Green        | Normal operation  |
|                                       | Blinking Amber      | Failure   |
|                                       | Off                 | No power  |
| <b>Stack 1 – 4</b>                    | Steady green        | Link OK on the indicated stack port.                                    |
|                                       | Blinking green      | Activity on the indicated stack port.                                   |
| <b>2-digit Stack number Indicator</b> |                     |   |
| <b>Left digit (1)</b>                 | Blinking            | This switch is the stack master node (see description of right digit).  |
|                                       | Off                 | This switch is the stack backup node.                                   |
| <b>Right digit (1 – 8)</b>            |                     | Indicates the position of this switch in the SummitStack configuration. |
|                                       | Upper half blinking | This switch is the stack master node.                                   |
|                                       | Lower half blinking | This switch is the stack backup node.                                   |
|                                       | Lit steadily        | This switch is a standby node in the stack.                             |
| <b>Ethernet Ports 1 – 24</b>          | Steady Green        | Link OK   |
|                                       | Blinking Green      | Activity  |
| <b>Management Port</b>                | Steady Green        | Link OK   |
|                                       | Blinking Green      | Activity  |
| <b>Back Panel</b>                     |                     |   |
| <b>Stacking Port LED</b>              | Steady Green        | Link OK   |
|                                       | Blinking Green      | Activity  |
| <b>SFP/SFP+ port LED</b>              | Steady Green        | Link OK   |
|                                       | Blinking Green      | Activity  |
| <b>Power supply LED</b>               | Blinking Green      | AC in; no output  |
|                                       | Steady Green        | Normal operation  |
|                                       | Blinking Red        | Output error  |
|                                       | Steady Red          | Critical error  |

## 2 Summit Power Supplies

This chapter describes Extreme Networks power supplies available for use with the Summit family switches. The Summit X650 series switches have replaceable power supplies; redundant external power supplies are available for the other Summit series.

This chapter includes the following sections:

- [Overview on page 65](#)
- [EPS-160 External Power Module \(with EPS-T\) on page 66](#)
- [EPS-LD External Power Supply Unit on page 67](#)
- [EPS-500 External Power Supply Unit on page 68](#)
- [EPS-150DC External Power Module \(with EPS-T2\) on page 68](#)
- [EPS-600LS External Power Module on page 69](#)
- [Summit X650 Power Supplies on page 71](#)

### Overview

Summit family switches are shipped with an internal power supply (replaceable on the Summit X650 series switches) that supplies all of the power needed for most switch operation. An optional redundant power supply can be added to most Summit models to protect against a power supply failure and to provide increased support for PoE operation on applicable switches.

[Table 13](#) lists the Summit family switches and compatible external power supplies.

**Table 13: Summit Switch and EPS Compatibility**

| Switch Model                        | Compatible EPS   | Model Number                                |
|-------------------------------------|--|---|
| <b>Summit X450 Series Switches</b>  |  |   |
| Summit X450-24t                     | EPS-160 External Power Module with EPS-T   | EPS-160: 10907<br>EPS-T: 10906              |
| Summit X450-24x                     | EPS-160 External Power Module with EPS-T<br><br>EPS-500 External Power Supply Unit | EPS-160: 10907<br>EPS-T: 10906<br><br>10911 |
| <b>Summit X450a Series Switches</b> |  |   |
| Summit X450a-24t                    | EPS-LD External Power Supply Unit<br>EPS-500 External Power Supply Unit            | 45019<br>10911                              |
| Summit X450a-24tDC                  | EPS-150DC External Power Module with EPS-T2  | EPS-150DC: 10909<br>EPS-T2: 10910           |
| Summit X450a-24x                    | EPS-LD External Power Supply Unit<br>EPS-500 External Power Supply Unit            | 45019<br>10911                              |
| Summit X450a-24xDC                  | EPS-150DC External Power Module with EPS-T2  | EPS-150DC: 10909<br>EPS-T2: 10910           |
| Summit X450a-48t                    | EPS-500 External Power Supply Unit   | 10911                                       |

**Table 13: Summit Switch and EPS Compatibility (Continued)**

| Switch Model                        | Compatible EPS                                     | Model Number                     |
|-------------------------------------|--|----------------------------------|
| <b>Summit X450e Series Switches</b> |  |                                  |
| Summit X450e-24p                    | EPS-LD External Power Supply Unit                  | 45019                            |
|                                     | EPS-500 External Power Supply Unit                 | 10911                            |
| Summit X450e-48p                    | EPS-600LS External Power Module with EPS C Chassis | EPS-600LS: 10913<br>EPS-C: 10912 |
| <b>Summit X250e Series Switches</b> |  |                                  |
| Summit X250e-24t                    | EPS-160 External Power Module with EPS-T           | EPS-160: 10907<br>EPS-T: 10906   |
| Summit X250e-24p                    | EPS-500 External Power Supply Unit                 | 10911                            |
| Summit X250e-24x                    | EPS-160 External Power Module with EPS-T           | EPS-160: 10907<br>EPS-T: 10906   |
| Summit X250e-48t                    | EPS-160 External Power Module with EPS-T           | EPS-160: 10907<br>EPS-T: 10906   |
| Summit X250e-48p                    | EPS-600LS External Power Module with EPS C chassis | EPS-600LS: 10913<br>EPS-C: 10912 |
| <b>Summit X150 Series Switches</b>  |  |                                  |
| Summit X150-24t                     | EPS-160 External Power Module with EPS-T           | EPS-160: 10907<br>EPS-T: 10906   |
| Summit X150-24x                     | EPS-160 External Power Module with EPS-T           | EPS-160: 10907<br>EPS-T: 10906   |
| Summit X150-24p                     | EPS-500 External Power Supply Unit                 | 10911                            |
| Summit X150-48t                     | EPS-160 External Power Module with EPS-T           | EPS-160: 10907<br>EPS-T: 10906   |
| Summit X650 Series Switches         | N/A  |                                  |

**NOTE**

The Summit switches listed in each section of this chapter run ExtremeXOS software. For information about compatible switches running ExtremeWare® software, refer to the Consolidated “i” and “e” Series Hardware Installation Guide.

## EPS-160 External Power Module (with EPS-T)

The EPS-160 External Power Module (Model 10907) is a modular power supply for use with the EPS-T chassis. You can use the EPS-160 as a redundant power supply with the following Extreme Networks switches:

- Summit X150-24t switch
- Summit X150-24x switch
- Summit X150-48t switch
- Summit X250e-24t switch
- Summit X250e-24x switch
- Summit X250e-48t switch

- Summit X450-24t switch
- Summit X450-24x switch

The EPS-T is a rack-mountable chassis or tray that holds one or two EPS-160 power supplies. Each EPS-160 power supply provides one-to-one redundancy for an attached Extreme Networks switch.


You can order the EPS-T chassis with one or two EPS-160 power supplies already installed. You can also order an additional power supply from your Extreme Networks reseller.



#### NOTE

Each EPS-160 power supply is shipped with a special redundant power supply cord (Figure 54). An AC power input cord is not provided; you can order an appropriate cord from Extreme Networks or from your local supplier. The power cord must meet the requirements listed in “[Selecting Power Supply Cords](#)” on page 170.

**Figure 54: Redundant Power Cord Connector**



## EPS-LD External Power Supply Unit

You can use the Extreme Networks EPS-LD External Power Supply Unit (Model 45019) as a redundant power supply with the following Extreme Networks switches:

- Summit X450a-24t switch
- Summit X450e-24p switch

When attached to the Summit X450e-24p, the EPS-LD provides 465 W total power with 375 W dedicated for PoE applications.

## EPS-500 External Power Supply Unit

The Extreme Networks EPS-500 External Power Supply Unit (Model 10911) provides additional power to compatible Power over Ethernet (PoE) switches and other Extreme switches. You can use the EPS-500 power supply as a redundant power supply with the following Extreme Networks switches:

- Summit X150-24p switch
- Summit X250e-24p switch
- Summit X350-24t switch
- Summit X350-48t switch
- Summit X450a-24t switch
- Summit X450a-24x switch
- Summit X450a-48t switch
- Summit X450e 24p switch

The EPS-500 power supply provides up to 500 W of total power and up to 375 W of power dedicated to PoE applications. When this power supply is used one of the listed Summit switches, the internal and external power supplies are fully fault tolerant and load-sharing. If one power supply fails, the other power supply will provide sufficient power to operate the switch.

## EPS-150DC External Power Module (with EPS-T2)

The EPS-150DC External Power Module (Model 10909) is a modular power supply for use in the EPS-T2 External Power System Tray. You can use the EPS-150DC as a redundant power supply with the following Extreme Networks switches:

- Summit X250e-24tDC switch
- Summit X250e-24xDC switch
- Summit X250e-48tDC switch
- Summit X450a-24tDC switch
- Summit X450a-24xDC switch
- Summit X450a-48tDC switch

When this power supply is used one of the listed Summit switches, the internal and external power supplies are fully fault tolerant and load-sharing. If one power supply fails, the other power supply will provide sufficient power to operate the switch.

The EPS-T2 is a rack-mountable chassis or tray that holds one or two EPS-150DC power supplies. Each EPS-150DC provides one-to-one redundancy to an attached Extreme switch. You must install the EPS-150DC power supply in the EPS-T2 tray.



### NOTE

*For centralized DC power connection, this product is intended to be installed in restricted access locations (dedicated equipment rooms, equipment closets, or the like) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.*



# EPS-600LS External Power Module

The EPS-600LS External Power Module (Model 10913) is a 600-watt redundant power supply unit that can be used with the following Extreme Networks switches:

- Summit X450e-48p switch
- Summit X250e-48p switch



## NOTE

An AC power input cord is not provided with the EPS-600LS power module. You can order an appropriate cord from Extreme Networks or from your local supplier. The power cord must meet the requirements listed in [“Selecting Power Supply Cords” on page 170](#).

Each EPS-C chassis is shipped with a special redundant power supply cord for connection to the Summit switch. Make sure that the EPS-C chassis is installed in the equipment rack before installing an EPS-600LS power module.

## PoE Redundant Power Configurations

You install one, two, or three EPS-600LS power modules in the EPS-C chassis (Model 10912) to build an external redundant power system for the Summit switch. A redundant power cable shipped with the EPS-C chassis provides the connection between the external power system and the redundant power input connector on the back of the switch.

The PoE capability of the Summit X450e-48p or X250e-48p varies depending on the number of external power modules in use. [Table 14](#) summarizes the PoE power behavior for the Summit X450e-48p or X250e-48p switch based on the number of power modules in use.

**Table 14: External Power Modules and Corresponding PoE Behavior**

| Internal PSU Status                | EPS-600LS (1x)               | EPS-600LS (2x)  | EPS-600LS (3x)  | External PSU/Chassis Failed/Disconnected |
|------------------------------------|------------------------------|---|---|--|
| <b>Internal PSU: Power On</b>      | 370 W of redundant power     | 740 W of external power only<br>Internal PSU disabled | 740 W of external power only with 2 + 1 redundancy<br>Internal PSU disabled | 370 W of internal power only             |
| <b>Internal PSU: Power Failure</b> | 370 W of external power only | 740 W of external power only                          | 740 W of external power only with 2 + 1 redundancy                          | No PoE power                             |

## Single 600-LS Module Configuration: Redundant PoE Power

A single EPS-600LS power module provides redundant PoE power capability with the same 370-watt capacity as the internal power supply. The internal Summit X450e-48p or X250e-48p power supply is capable of 370 W of PoE power: 15.4 W supplied to each port for a 24-port configuration and 7.7 W supplied to each port for a 48-port configuration.

- If the internal power supply fails, the external power module will provide power to PoE devices at the same power levels as the internal power supply without any power interruptions.
- If the EPS-600LS power module fails or is removed, the internal power supply continues to provide PoE power without any power interruptions.

## Dual 600-LS Module Configuration: Full Power

Two EPS-600LS power modules provide full power at 740 W, which allows 15.4 W of PoE power to all 48 ports. In this full-power configuration, the internal power supply is disabled, and therefore redundant power is not available.

## Triple 600-LS Module Configuration: Full Redundant Power

Three EPS-600LS power modules provide the full 740 W of power for 15.4 W of PoE power to all 48 ports. In addition, this configuration provides 2:1 redundancy. Should one of the EPS-600LS power modules fail, the third power module continues to provide uninterrupted full PoE power. The internal power supply is disabled in this configuration.

## Internal-to-External PSU Transfer

This section describes the conditions that would cause the Summit X450e-48p or X250e-48p switch to draw power from the external power unit.

**Internal PSU Failure with Single EPS-600LS Module.** When an EPS-C with a single EPS-600LS is connected to the Summit X450e-48p or X250e-48p switch and the internal PSU fails, power is drawn from the EPS-600LS without power interruption to the PoE connected devices.

**Two or Three EPS-600LS Modules.** When the Summit X450e-48p or X250e-48p switch detects that an EPS-C is connected and providing stable power from two or three EPS-600LS power modules, the PoE power budget is automatically recalculated to enable 740 W of PoE power. The internal PSU is disabled to prevent damage from excessive current demands beyond the internal PSU's capabilities.

## External-to-Internal PSU Transfer

This section describes the conditions where power from an external power module either fails or is disconnected.

**Active Internal PSU with Single 600-LS Module Failure.** When an EPS-C configured with a single EPS-600LS module is connected to the Summit X450e-48p or X250e-48p switch and the EPS-600LS fails or is disconnected, power is drawn from the internal PSU without power interruption to the PoE connected devices.

**Inactive Internal PSU with a Dual EPS-600LS Configuration and Module Failure.** This section describes the PoE behavior when an EPS-C chassis configured with two EPS-600LS modules is connected to the Summit X450e-48p or X250e-48p switch and one or both EPS-600LS modules fail or are disconnected.

It is possible for one external power module to fail while the second power module continues to function. If one EPS-600LS fails, the PoE power budget is automatically reduced to 370 W for the Summit X450e-48p or X250e-48p switch. PoE port power management occurs as described in the *ExtremeXOS 12.0 Concepts Guide*, Power over Ethernet section. With only a single operating power module, the remaining EPS-600LS behaves as a redundant power module. The internal PSU is returned to an active state to provide redundant capability.

If both external power modules fail or are disconnected, PoE power is interrupted while transferring PoE power back to the internal PSU. The internal PSU is then limited to 370 W of PoE power. The PoE power budget is automatically adjusted accordingly. Power management will occur as described in the *ExtremeXOS 12.0 Concepts Guide*, Power over Ethernet section.

**Disconnecting the EPS-C/EPS-600LS.** To manually disconnect an EPS-C or to remove the EPS-600LS modules, the recommended practice is to disconnect the EPS-600LS modules one at a time, pausing two seconds between each EPS-600LS disconnect. This enables a graceful power transition from the external PSUs to the internal PSU.

**Example: Two active EPS-600LS modules in an EPS-C**

- a Unplug one EPS-600LS unit from its power source.  
PoE power is automatically reduced to 370 watts and the internal PSU is enabled providing redundant 370 watt PoE power.
- b Wait at least two seconds before disconnecting the remaining EPS-600LS unit.
- c Unplug the second EPS-600LS unit from its power source.  
The internal PSU is already enabled and provides uninterrupted 370 watts of PoE power.



**NOTE**

*After an EPS-600LS unit is disconnected from its power source, it may be removed from the EPS-C. See [“Removing an EPS-600LS Power Module” on page 145](#) for complete disconnect and removal details.*

- d Disconnect the EPS-C from the switch.

## Summit X650 Power Supplies

The Summit X650 series switches can be powered by either of the following power supplies:

- Summit X650 AC PSU (Model 10914)
- Summit X650 DC PSU (Model 10915)

Either power supply provides 850 W of power to the switch.

The Summit X650 series switches accommodate one or two Summit X650 PSUs. In a redundant power configuration, both power supplies are fully fault-tolerant and load-sharing. You can remove one power supply without interrupting switch operation.

An AC power input cord is not provided with the Summit X650 AC power supply. You can order an appropriate cord from Extreme Networks or from your local supplier. The power cord must meet the requirements listed in [“Selecting Power Supply Cords” on page 170](#).



**NOTE**

*Extreme Networks does not recommended using the Summit X650 DC PSU in combination with a Summit X650 AC PSU in the same Summit X650 series switch.*



---

## 2

# Installing the Hardware

---



## 3 Site Preparation

This chapter includes the following sections:

- [Planning Your Site on page 75](#)
- [Meeting Site Requirements on page 76](#)
- [Evaluating and Meeting Cable Requirements on page 80](#)
- [Meeting Power Requirements on page 85](#)
- [Applicable Industry Standards on page 87](#)

By carefully planning your site, you can maximize the performance of your existing network and ensure that it is ready to migrate to future networking technologies.

The information in this chapter is intended for the system administrator, network equipment technician, network manager, or facilities manager responsible for installing and managing the network hardware. The chapter assumes a working knowledge of local area network (LAN) operations, and a familiarity with communications protocols that are used on interconnected LANs.

Installation, maintenance, and removal of a switch, chassis, or its components must be done by qualified service personnel only. Qualified service personnel have had appropriate technical training and experience that is necessary to be aware of the hazards to which they are exposed when performing a task and of measures to minimize the danger to themselves or other people.



### NOTE

---

*Before installing or removing any components of the system, or before carrying out any maintenance procedures, read the safety information in [Appendix A](#) of this guide.*

## Planning Your Site

To install your equipment successfully, you should plan your site carefully. The site planning process has three major parts:

- Meeting site requirements

The physical installation site must meet the following requirements for a safe and successful installation:

  - Building and electrical code requirements
  - Environmental, safety, and thermal requirements for the equipment you plan to install
  - Equipment rack requirements
- Evaluating and meeting cable requirements

After examining your physical site and verifying that all environment requirements are met, evaluate and compare your existing cable plant with the requirements of the Extreme Networks equipment to determine if you need to install new cables.

- Meeting power requirements

To run your equipment safely, you must meet the specific power requirements for each switch and external power supply unit installed in the system. For power specifications of the switches, see the specific switch listings in [Appendix B, “Technical Specifications.”](#) For power specifications of the external power supplies, see [“Summit External Power Supplies” on page 207.](#)

## Meeting Site Requirements

This section requirements to consider when preparing your installation site, including:

- [Operating Environment Requirements](#)
- [Rack Specifications and Recommendations](#)

## Operating Environment Requirements

Verify that your site meets all environmental and safety requirements.

Virtually all areas of the United States are regulated by building codes and standards. During the early planning stages of installing or modifying your LAN, it is important that you develop a thorough understanding of the regulations that pertain to your location and industry.

## Building and Electrical Codes

Building and electrical codes vary depending on your location. Comply with all code specifications when planning your site and installing cable. This section lists resources for obtaining additional information.

Information about major building codes is located at the following websites:

- International Code Council (ICC); 5203 Leesburg Pike; Falls Church, Virginia 22041 USA.  
<http://www.iccsafe.org>  
<http://www.sbcci.org>

Five authorities on electrical codes are:

- National Electrical Code (NEC) Classification (USA only)—a recognized authority on safe electrical wiring. Federal, state, and local governments use NEC standards to establish their own laws, ordinances, and codes on wiring specifications. The NEC classification is published by the National Fire Protection Association (NFPA). The address is NFPA; 1 Batterymarch Park; Quincy, Massachusetts 02169 USA. <http://www.nfpa.org>
- Underwriters’ Laboratory (UL) (USA only)—an independent research and testing laboratory. UL evaluates the performance and capability of electrical wiring and equipment to determine whether they meet certain safety standards when properly used. Acceptance is usually indicated by the words “UL Approved” or “UL Listed.” The address is UL; 333 Pfingsten Road; Northbrook, Illinois 60062-2096 USA. <http://www.ul.com>
- National Electrical Manufacturing Association (NEMA) (USA only)—an organization of electrical product manufacturers. Members develop consensus standards for cables, wiring, and electrical components. The address is NEMA; 1300 N. 17th Street; Rosslyn, Virginia 22209. <http://www.nema.org>
- Electronics Industries Alliance (EIA)—a trade association that develops technical standards, disseminates marketing data, and maintains contact with government agencies in matters relating to



the electronics industry. The address is EIA; 2500 Wilson Boulevard; Arlington, Virginia 22201 USA. <http://www.eia.org>

- Federal Communications Commission (FCC) (USA only)—a commission that regulates all interstate and foreign electrical communication systems that originate in the United States according to the Communications Act of 1934. The FCC regulates all U.S. telephone and cable systems. The address is FCC; 445 12th Street S.W.; Washington, D.C. 20554 USA. <http://www.fcc.gov>

## Wiring Closet Considerations

Be aware of the following recommendations for your wiring closet:

- Be sure that your system is easily accessible for installation and service. See “[Rack Specifications and Recommendations](#)” on page 78 for information.
- Use appropriate AC or DC power, power distribution, and grounding for your specific installation.
- Use a vinyl floor covering in your wiring closet. (Concrete floors accumulate dust, and carpets can cause static electricity.)
- Prevent unauthorized access to wiring closets by providing door locks. Install the equipment in a secured, enclosed, and restricted access location, ensuring that only qualified service personnel have access to the equipment.
- Provide adequate overhead lighting for easy maintenance.
- Be sure that each wiring closet has a suitable ground. All equipment racks and equipment installed in the closet should be grounded.
- Be sure that all system environmental requirements are met, such as ambient temperature and humidity.



### NOTE

---

*Extreme Networks recommends that you consult an electrical contractor for commercial building and wiring specifications.*

## Temperature

Extreme Networks equipment generates a significant amount of heat. It is essential that you provide a temperature-controlled environment for both performance and safety.

Install the equipment only in a temperature- and humidity-controlled indoor area that is free of airborne materials that can conduct electricity. Too much humidity can cause a fire. Too little humidity can produce electrical shock and fire.

Follow these general thermal recommendations for your wiring closet:

- Be sure that the ventilation in the wiring closet is adequate to maintain a temperature below 104° F (40° C).
- Install a reliable air conditioning and ventilation system.
- Keep the ventilation in the wiring closet running during non-business hours; otherwise, the equipment can overheat.
- Maintain an ambient operating temperature of 32° to 104° F (0° to 40° C).
- Maintain a storage temperature of -40° to 158° F (-40° to 70° C).

**NOTE**

*As with all electrical equipment, Extreme Networks product lifetimes degrade with increased temperature. If possible, temperatures should be kept at approximately 78° F (25° C) or lower.*

## Humidity

To maximize equipment life, keep operating humidity between 50% and 70% relative humidity (non-condensing) during typical operation. The equipment can operate between 10% and 95% relative humidity (non-condensing) for short intervals.

## Spacing Requirements and Airflow

Be sure that cables and other equipment do not block the air intake or outflow on an Extreme Networks Summit family switch. It is best to have at least 3 inches (8 cm) of clear space in front of the air intake and outflow vents on the sides of the switch; airflow moves from side to side. For proper airflow through a Summit family switch, leave clear space on the left and right sides of the switch.

Depending on other conditions in the equipment room, it may be possible to install the switches closer to each other; consult your Extreme Networks Customer Support representative for guidance.

## Electrostatic Discharge

Your system must be protected from static electricity or electrostatic discharge (ESD). Take the following measures to ensure optimum system performance:

- Remove materials that can cause electrostatic generation (such as synthetic resins) from the wiring closet. Check the appropriateness of floor mats and flooring.
- Connect metal chassis, conduit, and other metals to ground using dedicated grounding lines.
- Use electrostatically safe equipment. If you are working with pluggable interface modules, wear an ESD-preventive wrist strap and connect the metal end to a grounded equipment rack or other source of ground.

## Rack Specifications and Recommendations

Racks should conform to conventional standards. In the United States, use EIA Standard RS-310C: Racks, Panels, and Associated Equipment. In countries other than the United States, use IEC Standard 297. In addition, verify that your rack meets the basic mechanical, space, and earthquake requirements that are described in this section.

## Mechanical Recommendations for the Rack

Use equipment racks that meet the following mechanical recommendations:

- Use an open style, 19-inch rack to facilitate easy maintenance and to provide proper ventilation.
- Use a rack made of steel or aluminum.
- The rack should use the universal mounting rail hole pattern that is identified in IEC Standard 297.
- The rack should have designated earth grounding connections (typically on the base).
- The rack must meet earthquake safety requirements equal to that of the installed chassis.
- The mounting holes should be flush with the rails to accommodate the chassis.
- The rack should support approximately 600 pounds (272 kilograms).

## Protective Grounding for the Rack

Use a rack grounding kit and a ground conductor that is carried back to earth or to another suitable building ground.

At a minimum, follow these guidelines to ground equipment racks to the earth ground:

- CAD weld appropriate wire terminals to building I-beams or earth ground rods.
- For a Summit DC-powered switch, use a minimum 14 AWG stranded copper wire for grounding. AC-powered Summit switches do not need separate chassis grounding.
- Position the earth ground as close to the equipment rack as possible to maintain the shortest wiring distance possible.
- Use a ground impedance tester or micro-ohm meter to test the quality of earth ground connection at the chassis. This will ensure good grounding between the chassis, rack, and earth ground.



### NOTE

---

*Because building codes vary worldwide, Extreme Networks strongly recommends that you consult an electrical contractor to ensure proper equipment grounding for your specific installation.*

## Space Requirements for the Rack

Provide enough space in front of and behind the switch so that you can service it easily. Allow a minimum of 48 inches (122 cm) in front of the rack and 30 inches (76 cm) behind the rack. When using a relay (two-post) rack, provide a minimum of 24 inches (61 cm) of space behind the mounted equipment. Extra room on each side is optional.



### WARNING!

---


*Extreme Networks switches do not have a switch for turning power to the unit on and off. For systems using an AC power supply, power to the switch is disconnected by removing the wall plug from the electrical outlet.*

*For DC-powered Summit switches (X450a-24tDC, X450a-24xDC, and X450a-48tDC) and the EPS-150DC power supply, turn off power to the chassis by de-energizing the circuit that feeds the power supply; this is usually accomplished by turning off a circuit breaker. Disconnecting the DC wiring harness from the DC power source requires the performance of a qualified, licensed electrician.*

## Securing the Rack

The rack should be attached to the wiring closet floor with 3/8-inch (9.5 mm) lag screws or equivalent hardware. The floor under the rack should be level within 3/16-inch (5 mm). Use a floor-leveling cement compound if necessary or bolt the racks to the floor as shown in [Figure 55](#).

**Figure 55: Properly Secured Rack**



Brace open equipment racks if the channel thickness is less than 1/4 inch (6.4 mm).

## Evaluating and Meeting Cable Requirements

This section addresses requirements for the cable you should use when installing your network equipment. It includes:

- [Cabling Standards](#)
- [Cable Labeling and Record Keeping](#)
- [Installing Cable](#)
- [RJ-45 Connector Jackets](#)
- [Radio Frequency Interference](#)

### Cabling Standards

Extreme Networks recommends using the Building Industry Consulting Service International (BICSI) Registered Communications Distribution Designer (RCDD), which is globally recognized as a standard in site planning and cabling. For information, go to:

<http://www.bicsi.org>

## Cable Labeling and Record Keeping

A reliable cable labeling system is essential when planning and installing a network. Maintaining accurate records helps you to:

- Relocate devices easily.
- Make changes quickly.
- Isolate faults in the distribution system.
- Locate the opposite end of any cable.
- Know the types of network devices that your cabling infrastructure can support.

Follow these guidelines when setting up a cable labeling system suitable for your installation:

- Identify cables by securely attaching labels to all cable ends.
- Assign a unique block of sequential numbers to the group of cables that run between each pair of wiring closets.
- Assign a unique identification number to each equipment rack.
- Identify all wiring closets by labeling the front panel of your Extreme Networks equipment and other hardware.
- Keep accurate and current cable identification records.
- Post records near each equipment rack. Include the following cable drop information: the cable source, destination, and jumper location.

## Installing Cable

Consider the following recommendations when you connect cable to your network equipment:

- Examine cable for cuts, bends, and nicks.
- Support cable using a cable manager that is mounted above connectors to avoid unnecessary weight on the cable bundles.
- Use cable managers to route cable bundles to the left and right of the network equipment to maximize accessibility to the connectors.
- Provide enough slack, approximately 2 to 3 inches (5.08 to 7.62 cm), to provide proper strain relief as shown in [Figure 56](#).
- Bundle cable using hook-and-loop straps to avoid injuring cables.
- If you build your own cable, be sure that connectors are properly crimped.
- When installing a patch panel using twisted pair wiring, untwist no more than 1 inch (2.54 cm) of the cable to avoid radio frequency (RF) interference.
- Discharge the RJ-45 Ethernet cable before plugging it into a port on the switch.




### CAUTION

*Unshielded twisted pair (UTP) cable can build up ESD charges when being pulled into a new installation. Before connecting any category 5 UTP cable to the switch, discharge ESD from the cable by plugging the RJ-45 connector into a LAN static discharge device or use an equivalent method.*

- Use plenum-rated cable when it is necessary for safety and fire rating requirements. Consult your local building codes to determine when it is appropriate to use plenum-rated cable, or refer to IEC standard 850.
- Keep all ports and connectors free of dust.

**Figure 56: Properly Installed and Bundled Cable**



SPG\_008

## Fiber Optic Cable


Fiber optic cable must be handled carefully during installation. Every cable has a minimum bend radius, for example, and fibers will be damaged if the cables are bent too sharply. It is also important not to stretch the cable during installation. We recommend that the bend radius for fiber optic cable equal 2 inches (5.08 cm) minimum for each 90-degree turn as shown in [Figure 57](#).



## NOTE

Kinks and sharp bends can destroy or impair the cable's ability to convey light pulses accurately from one end of the cable to the other. Use care in dressing the optical fiber cables: provide satisfactory strain relief to support the cable and maintain an adequate bend radius at all cable turns, particularly where the cable connects to the I/O module.

**Figure 57: Bend Radius for Fiber Optic Cable**



SPG\_002

## Cable Distances

Table 15 shows cable media types and maximum distances that support reliable transmission in accordance with international standards except where noted.

**Table 15: Media Types and Maximum Distances**

| Standard                                  | Media Type                      | Mhz•Km Rating | Maximum Distance (Meters) |
|---|---------------------------------|---------------|---------------------------|
| 1000BASE-SX<br>(850 nm optical window)    | 50/125 µm multimode fiber       | 400           | 500                       |
|   | 50/125 µm multimode fiber       | 500           | 550                       |
|   | 62.5/125 µm multimode fiber     | 160           | 220                       |
|   | 62.5/125 µm multimode fiber     | 200           | 275                       |
| 1000BASE-LX<br>(1300 nm optical window)   | 50/125 µm multimode fiber       | 400           | 550                       |
|   | 50/125 µm multimode fiber       | 500           | 550                       |
|   | 62.5/125 µm multimode fiber     | 500           | 550                       |
|   | 10/125 µm single-mode fiber     | –             | 5,000                     |
|   | 10/125 µm single-mode fiber*    | –             | 10,000                    |
| 1000BASE-LX70<br>(1550 nm optical window) | 10/125 µm single-mode fiber     | –             | 70,000                    |
| 1000BASE-T                                | Category 5 and higher UTP cable | –             | 100                       |
| 100BASE-TX                                | Category 5 and higher UTP cable | –             | 100                       |
| 10BASE-T                                  | Category 3 and higher UTP cable | –             | 100                       |

\* Proprietary to Extreme Networks. Connections between two Extreme Networks 1000BASE-LX interfaces that use 10/125 µm single-mode fiber can use a maximum distance of 10,000 meters.

## RJ-45 Connector Jackets


Use RJ-45 cable with connector jackets that are flush with the connector or that have connectors with a no-snag feature.

Using cable with jackets that are wider than the connectors can cause:

- Connectors that are not properly aligned with the port.
- Crowded cable installation, which can cause connectors to pop out of the port.

Figure 58 shows examples of connector jacket types that are not recommended as well as those that are recommended.

**Figure 58: RJ-45 Connector Jacket Types**



SPG\_001

## Radio Frequency Interference

If you use UTP cabling in an installation, take precautions to avoid RF interference. RF interference can cause degradation of signal quality, and, in an Ethernet network environment, can cause excessive collisions, loss of link status, or other physical layer problems that can lead to poor performance or loss of communication.

To prevent RF interference, avoid the following situations:

- Attaching UTP cable to AC power cables
- Routing UTP cable near antennas, such as a ham radio antenna
- Routing UTP cable near equipment that could exhibit RF interference, such as ARC welding equipment
- Routing UTP cable near electrical motors that contain coils
- Routing UTP cable near air conditioner units
- Routing UTP cable near electrical transformers

In areas or applications where these situations cannot be avoided, use fiber optic cabling or shielded twisted pair cabling (STP).



# Meeting Power Requirements

This section describes power requirements, including:

- [PoE Devices](#)
- [Power Supply Requirements](#)
- [AC Power Cables](#)
- [Uninterruptible Power Supply Requirements](#)

## PoE Devices

When connecting power over Ethernet (PoE) devices to a PoE switch, all connections between the PoE device and the switch must remain within the same building and use a low-voltage power distribution system per IEEE 802.3af.

## Power Supply Requirements

Follow these recommendations when you plan power supply connections for the Summit family switches:

- Place the equipment in an area that accommodates the power consumption and component heat dissipation specifications.
- Be sure that your power supply meets the site DC power or AC power requirements of the network equipment.
- When you connect power to installed equipment, do not make this connection through an extension cord or power strip.
- If your switch includes more than one power supply, connect each power supply to a different, independent power source.

If a power source fails, it will affect only the switch power supply to which it is connected. If all switch power supplies are connected to a single power source, the entire switch is vulnerable to a power source failure.

- In regions that are susceptible to electrical storms, we recommend that you plug your system into a surge suppressor.

For power specifications for the Summit family switches, see [Appendix B, “Technical Specifications.”](#)

## AC Power Cables

AC power input cords are not provided with Summit switches and power supplies. You can purchase AC power cords for use in the US and Canada from Extreme Networks or from your local supplier.

Power supply cords for use outside of the United States and Canada are typically provided separately by third-party distribution centers. Make sure that the power cord you use is certified for the country of end use and suitable for the device.

The power cord must meet the requirements listed in [“Selecting Power Supply Cords”](#) on page 170.

## Uninterruptible Power Supply Requirements

An uninterruptible power supply (UPS) is a device that sits between a power supply (such as a wall outlet) and a device (such as a switch) to prevent outages, sags, surges, and bad harmonics from adversely affecting the performance of the device.

A UPS traditionally can perform the following functions:

- Absorb relatively small power surges.
- Smooth out noisy power sources.
- Continue to provide power to equipment during line sags.
- Provide power for a period of time after a blackout has occurred.

In addition, some UPS devices or UPS-plus-software combinations provide the following functions:

- Automatically shut down equipment during long power outages.
- Monitor and log power supply status.
- Display the voltage (current draw) of the equipment.
- Restart equipment after a long power outage.
- Display the voltage currently on the line.
- Provide alarms on certain error conditions.
- Provide short-circuit protection.

### Selecting a UPS

To determine UPS requirements for your switch, answer these questions:

- What are the amperage requirements?
- What is the longest potential time period that the UPS would be required to supply backup power?
- Where will the UPS be installed?
- What is the maximum transition time that the installation will allow? (See [“UPS Transition Time” on page 87](#))



#### NOTE

*Extreme Networks recommends that you use a UPS that provides online protection.*

### Calculating Volt-Amperage Requirements

To determine the size of UPS that you need:

- 1 Locate the voltage and amperage requirements for each piece of equipment. These numbers are usually located on a sticker on the back or bottom of your equipment. Then multiply the numbers together to get Volt-Amperes (VA):  

$$VA = \text{Volts} \times \text{Amperes}$$
- 2 Add the VA from all the pieces of equipment together to find the total VA requirement.  
 To determine the minimum volt-amperage requirements for your UPS, Extreme Networks recommends that you add 30% to the total.

## UPS Transition Time

Transition time is the time that is necessary for the UPS to transfer from utility power to full-load battery power. For Extreme Networks products, a transition time of less than 20 milliseconds is required for optimum performance.

## DC Power Requirements

This system should be installed in a DC-I battery return configuration. In a DC-I configuration, the battery return conductor should be connected directly to the central office power return bus, and not to the equipment frame or the grounding means of the equipment.

## Applicable Industry Standards

For more information, see the following ANSI/TIA/EIA standards:

- ANSI/TIA/EIA-568-A—discusses the six subsystems of a structured cabling system.
- ANSI/TIA/EIA-569-A—discusses design considerations.
- ANSI/TIA/EIA-606—discusses cabling system administration.
- ANSI/TIA/EIA-607—discusses commercial building grounding and bonding requirements.

You can access these standards at:

<http://www.ansi.org>

or

<http://www.tiaonline.org>



## 4

# Installing Summit Family Switches

This chapter describes the installation process for the Summit family switches and provides information about how to build a SummitStack configuration.

The chapter includes the following topics:

- [Safety Information on page 89](#)
- [Building a SummitStack Configuration on page 90](#)
- [Installing a Summit Family Switch \(Models Other than Summit X650 Series\) on page 97](#)
- [Installing and Removing Summit DC-Powered Switches on page 99](#)
- [Installing a Summit X650 Series Switch on page 104](#)
- [Installing Summit X650 Power Supplies on page 110](#)
- [Removing Summit X650 Series Switches on page 117](#)
- [Connecting Network Interface Cables on page 122](#)
- [Initial Management Access on page 123](#)



### NOTE

---

*Read the information in this chapter thoroughly before you attempt to install or remove a Summit switch.*

## Safety Information

Only trained service personnel should perform service to Extreme Networks switches and their components. Trained service personnel have read all related installation manuals, have the technical training and experience necessary to be aware of the hazards to which they are exposed in performing a task, and are aware of measures to minimize the danger to themselves or other persons.



### NOTE

---

See [Appendix A, “Safety Information”](#) for additional safety information and [Appendix B, “Technical Specifications”](#) for additional information regarding regulatory compliance certifications.



### CAUTION

---

*Be sure that proper ESD controls are in use before switch maintenance is performed. This includes but is not limited to wrist straps that are grounded to the switch chassis and earth grounds.*



### WARNING!


---

*Be sure to connect the chassis ground wire before you connect any DC power cables.  
Be sure to disconnect the ground wire after you disconnect all DC power cables.*

## Building a SummitStack Configuration

If you intend to use the SummitStack feature, read this section before installing the set of Summit family switches that will be included in the SummitStack configuration. A stack consists of a group of up to eight Summit switches that are connected together using stacking cables to form a connected ring, as shown in [Figure 59](#).

**Figure 59: Summit Switches Connected in a SummitStack Configuration**



Depending on the switch model and type of stacking port, the bidirectional stacking link provides either 40 Gbps or 256 Gbps full duplex bandwidth. Stacking connections are made using stacking cables that are specific to the type of stacking port. These cables are available from Extreme Networks in lengths from 0.5 meter to 5 meters. [Table 16](#) lists the cable types and compatible Summit switches or modules.

**Table 16: Available Stacking Cables**

| Model Number | Manufacturing Part Number | Cable Type, Length          | Compatible Ports and Devices   |
|--------------|---------------------------|-----------------------------|--|
| 16105        | 900449-10                 | SummitStack, 5 meter        | 40-Gbps fixed stacking ports on Summit X250e, X450, X450a, X450e series switches |
| 16106        | 900296-00/10/11           | SummitStack, 0.5 meter      |  |
| 16107        | 900297-00/10/11           | SummitStack, 1.5 meter      |  |
| 16108        | 900298-00/10/11           | SummitStack, 3 meter        |  |
| 17021        | 900610-10                 | SummitStack 128G, 0.5 meter | 128-Gbps ports on VIM1-SummitStack512 module in Summit X650 series switches      |
| 17022        | 900611-10                 | SummitStack 128G, 1.0 meter |  |
| 17023        | 900612-10                 | SummitStack 128G, 3.0 meter |  |

NOTE: Additional types of stacking cables may have been released since this guide was published. Contact your Extreme Networks sales representative for the most recent information about available cables.

## Slot Numbers

Each switch (or node) in the stack is assigned a “slot number” during the initial software configuration of the stack. Starting at the switch with the console connection, numbers are assigned in numerical order following the physical path of the connected stacking cables. For example, if you follow the cabling recommendations presented in [“Connecting the Switches to Form the Stack Ring” on page 92](#) and configure the stack from the console on the switch at the top of the physical stack, the switches will be assigned numbers 1 through 8 from the top down.

Each Summit switch has a seven-segment LED on its front panel, called the stack number indicator. When a stack is operating, the indicator displays the slot number for the switch. This LED does not light on switches that are not operating in stacking mode. A quick way to verify that the cable connections match the software configuration is to check the stack number indicator on each switch. If the slot numbers do not line up in the order you arranged the switches, this may indicate that the stacking cable setup differs from what you intended when you configured the software. In this case, reconnect the cables in the correct order and perform the software configuration again.

## About Redundancy

When your stack is operational, one switch is the primary (or master) switch that is responsible for running network protocols and managing the stack. To provide recovery in case of a break in the stack connections, you can configure redundancy by designating a backup switch to take over as master if the master switch fails. When you perform the initial software configuration of the stack, the “easy setup” configuration option automatically configures redundancy, with slot 1 as the master and slot 2 as the backup. You can also configure additional switches as “master-capable” to become a stack master in case the initial backup switch fails.

In a stack with multiple master-capable switches, it is possible for more than one switch to try become the stack master if the stack is physically severed. Such a dual-master condition would cause confusion and loss of connectivity in your networks. To resolve a dual-master condition, you must be able to log in to each severed stack segment, either over the management network (using the Ethernet management port on a switch in the segment) or through a direct console port connection to each switch in the segment.

Stack configuration, easy setup, and redundancy are fully described in the *ExtremeXOS 12.0 Concepts Guide*.

## Placing Summit Family Switches for Stacked Operation

This section summarizes the recommended best practices for installing Summit switches for a SummitStack configuration. For detailed information about how to configure and manage the stack and how a stack operates, refer to the *ExtremeXOS Concepts Guide*.

When you install switches for a SummitStack configuration, follow these recommendations:

- Use the shortest possible stacking cables to connect the switches in the stack; this reduces the likelihood that the stacking cables might be accidentally damaged or disconnected. Stacking cables are available in lengths from 0.3 meters to 5 meters (see [Table 16 on page 90](#)).
- When possible, place all switches for the stack in the same rack; this facilitates using shorter stacking cables.
- Because the switches will form a ring, make sure that no two switches in the stack are located more than 5 meters apart.

- For simplicity and ease of connecting the stacking cables, plan to designate the top switch in the physical stack as the stack master. This is the switch through which you will perform the initial stack configuration, using the console port.
- For easier software configuration of the stack, connect the stacking cables in the order and arrangement shown in [Table 17](#) and [Table 18](#).
- On the stack master switch, connect the Ethernet management port to your management network.
- To provide management access to the stack in case of a failure in the master switch, connect all switches that will participate in redundancy to your management network using the Ethernet management port on each switch.
- Because of the weight of the SummitStack 128G cable, Extreme Networks strongly recommends the use of cable management hardware to support the cables and provide strain relief at the connectors.

## Connecting the Switches to Form the Stack Ring

After you have installed the individual Summit switches, connect the switches together using the stacking cables. [Figure 60](#) and [Figure 61](#) show cable connections for two sample configurations using SummitStack 40G cables; [Table 17](#) and [Table 18](#) list the recommended order for connecting the stacking ports in these two examples. Connect Stack Port 2 on one switch to Stack Port 1 on the switch with the next higher slot number.

Although you can connect the switches in any order, connecting them as shown in these examples will produce better predictability and easier software configuration. It is essential to create an unbroken data path through all the switches in the stack.



### NOTE


*The connection recommendations in this section do not apply to Summit X650 series switches with installed VIM1-SummitStack512 modules. For information about connecting the ports on the VIM1-SummitStack512 modules, see “Using the VIM1-SummitStack512 Module” on page 94.*

**Table 17: Recommended Order for Stacking Connections (8-Switch Stack)**

| Slot Number | Connect Stack Port 1 on this switch to . . . | Connect Stack Port 2 on this switch to . . . |
|-------------|--|--|
| 1           | Slot 8 Port 2                                | Slot 2 Port 1                                |
| 2           | Slot 1 Port 2                                | Slot 3 Port 1                                |
| 3           | Slot 2 Port 2                                | Slot 4 Port 1                                |
| 4           | Slot 3 Port 2                                | Slot 5 Port 1                                |
| 5           | Slot 4 Port 2                                | Slot 6 Port 1                                |
| 6           | Slot 5 Port 2                                | Slot 7 Port 1                                |
| 7           | Slot 6 Port 2                                | Slot 8 Port 1                                |
| 8           | Slot 7 Port 2                                | Slot 1 Port 1                                |



**Figure 60: SummitStack Cable Connections Using Eight Summit Switches and SummitStack 40G Cables**




BD\_159B

**Table 18: Recommended Stacking Port Connections (4-Switch Stack)**

| Slot Number | Connect Stack Port 1 on this switch to . . . | Connect Stack Port 2 on this switch to . . . |
|-------------|--|--|
| 1           | Slot 4 Port 2                                | Slot 2 Port 1                                |
| 2           | Slot 1 Port 2                                | Slot 3 Port 1                                |
| 3           | Slot 2 Port 2                                | Slot 4 Port 1                                |
| 4           | Slot 3 Port 2                                | Slot 1 Port 1                                |

**Figure 61: SummitStack Cable Connections Using Four Summit Switches and SummitStack 40G Cables**



BD\_164A


## Using Summit X650 Series Switches

When you combine X650 switches and other switches in a stack, the following rules apply:

- A Summit X650 series switch must be the master node.
- A Summit X650 series switch must be the backup node.
- Only the VIM1-SummitStack and the VIM1-10G8X versatile interface modules support connection to other Summit series switches.
- Stacking connections in a mixed stack with Summit X650 series switches require the SummitStack 40G cables.

Figure 62 shows an example of a four-switch stack that includes two Summit X650 series switches.

**Figure 62: SummitStack Configuration Using SummitStack X650 Series Switches and SummitStack 40G Cables**




## Using the VIM1-SummitStack512 Module

The VIM1-SummitStack512 versatile interface module allows you to connect two Summit X650 series switches in a cross-over or back-to-back configuration, using SummitStack 128G cables. This configuration provides two bidirectional links operating at 256 Gbps between the two switches.

When you connect stacking cables to installed VIM1-SummitStack512 modules, match the stacking ports as follows (Figure 63):

- Stack Port 1 connected to Stack Port 1
- Stack Port 2 connected to Stack Port 2
- Stack Port 3 connected to Stack Port 3
- Stack Port 4 connected to Stack Port 4

**Figure 63: Stacking Connections Using VIM1-SummitStack512 Modules and SummitStack 128G Cables**




## Connecting a SummitStack 40G Cable to a Stacking Port

SummitStack 40G cables are used for stacking connections among Summit To connect a SummitStack 40G stacking cable:

- 1 Align the cable connector with the stacking port connector on the back of the first switch ([Figure 64](#)).
- 2 Firmly press the cable connector into place on the mating stacking port connector.
- 3 Align and tighten the retaining screws on the cable connector.

Repeat steps 1 through 3 to connect the cable to the second switch.

**Figure 64: Connecting a Summit Stacking Cable**



### CAUTION


Avoid making sharp bends in the cable. Sharp bends can stress the cable and cause damage.

## Connecting a SummitStack 128G Cable

To connect a SummitStack 128G cable:

- 1 Holding the cable connector with the release tab on top, align the connector with the stacking port on the VIM1 module in the Summit X650 series switch (figure).

**Figure 65: Connecting a SummitStack 128G Cable**



- 2 Firmly press the cable connector into the stacking port until the spring latch on top of the connector clicks into place.
- 3 Repeat steps 1 and 2 to connect the other end of the cable.



### NOTE

*Because of the weight of the SummitStack 128G cable, Extreme Networks strongly recommends the use of cable management hardware to support the cables and provide strain relief at the connectors.*

## Connecting Console Ports for a Stack

To begin the software configuration for a new stack, you must have at least one console port connected. Connect a console to the console port of the switch that you intend to become the master of the stack. If you are going to configure redundancy, you may wish to connect to the console ports of all switches in the stack that you will configure to be master-capable. If you followed the cabling examples in [Table 17](#) and [Table 18](#), and you use the easy-setup configuration procedure, only slots 1 and 2 will be allowed to become master.

## Management Port Cabling

Connect the master, backup, and all other master-capable switches to your management network using the Ethernet management port on the rear panel of each switch. If you choose the default redundancy setup, only slots 1 and 2 are allowed to become master. You may connect all switch management ports in the stack if you choose to do so. There is an alternate IP address configuration that will allow you to directly log into an individual switch in the stack through its management port.

## Stacking Port LEDs

Each stacking port has an LED. The LED is steady green if the link is OK, blinking green if traffic is present, and off if no signal is present.

## Installing a Summit Family Switch (Models Other than Summit X650 Series)

This section describes how to install the following Summit family switches:

- Summit X150 series
- Summit X250e series
- Summit X350 series
- Summit X450 series
- Summit X450a series
- Summit X450e series

For instructions to install the Summit X650 series switches, see [“Installing a Summit X650 Series Switch” on page 104](#).

A Summit family switch can be mounted in a standard 19-inch (48.26 cm) rack or placed free-standing on a tabletop. The installation process includes the following tasks:

- 1 Install the switch in a rack or on a table.
- 2 Ground the switch (DC-powered units only).
- 3 Connect a redundant power supply (if applicable).
- 4 Connect power cables.
- 5 Connect network interface cables.

If you are installing Summit family switches for use in a SummitStack configuration, read [“Building a SummitStack Configuration” on page 90](#) before you install the switches.

For information about grounding and connecting DC-powered Summit family switches, see [“Installing and Removing Summit DC-Powered Switches” on page 99](#).

For information about installing and connecting redundant power supplies, see [Chapter 5, “Installing Summit External Power Supplies.”](#)

## Rack-Mounting a Summit Switch (Models Other than Summit X650 Series)

This section describes how to install Summit switches in the following series:

- Summit X150
- Summit X250e
- Summit X350
- Summit X450
- Summit X450a
- Summit X450e

To install the switch in a rack, you need the following tools and equipment:

- Mounting brackets (provided)
- Screws (provided) to secure the mounting brackets to the switch
  - Eight M3 screws for Summit X350, X450, X450a, and X450e series switches
  - Twelve M4 screws for Summit X150 and X250e series switches
- Four rack mounting screws
 

The screw size will vary based on your organization's rack system; screws are not provided.
- Screwdriver for securing the switch to your organization's rack
 



The screwdriver size will vary based on the requirements of your organization's rack system.
- AC power cord
 

An AC power cord is not included with the Summit family switch. You must obtain a power supply cord that meets the requirements listed under ["Selecting Power Supply Cords"](#) on page 170.

To rack-mount a Summit switch:

- 1 Place the switch upright on a secure work surface.
- 2 Place a mounting bracket over the mounting holes on one side of the unit.
- 3 Insert the screws and fully tighten with a suitable screwdriver, as shown in [Figure 66](#).

**Figure 66: Attaching the Mounting Bracket**



- 4 Repeat steps 2 and 3 for the other side of the switch.

- 5 Insert the switch into the rack.
  - Take care to load the rack so that it is not top-heavy. Start from the bottom and work up.
  - Do not cover vents that would restrict airflow. Leave a half-rack space between the units for adequate ventilation.
- 6 Secure the switch with suitable screws (not provided).
- 7 Connect the switch to the redundant power supply (if applicable). For instructions on installing and connecting redundant power supplies, see [Chapter 2, “Summit Power Supplies.”](#)
- 8 Connect the power cables.
  - For AC-powered units, connect the power cable to the AC power connector on the back of the switch. Then connect the power cable to an AC power socket.
  - For information about DC-powered units, see [“Installing and Removing Summit DC-Powered Switches”](#) on page 99.

## Free-Standing and Desktop Mounting of Multiple Switches

Summit family switches are supplied with four self-adhesive rubber pads. Apply the pads to the underside of each device by placing the pad in the marked area at each corner of the switch, ensuring that all corners aligned. You can safely place up to four Summit family switches on top of one another.

## Removing an AC-Powered Summit Switch from a Rack (Models Other than Summit X650 Series)

To remove an AC-powered Summit switch from a rack:

- 1 Remove power from the switch.
  - Unplug the power cables from the from the wall outlets first and then from the switch.
- 2 Disconnect the Summit switch from the redundant power supply (if applicable).
- 3 Loosen and remove the four screws holding the switch in place in the system rack.
- 4 Carefully remove the switch from the rack and place it on a secure, flat surface.



### NOTE

For information about DC-powered units, see [“Removing a Summit DC-Powered Switch from a Rack”](#) on page 103.

For information about removing a Summit X650 series switch from a rack, see [“Removing a Summit X650 Series Switch from a Two-Post Rack”](#) on page 119.

## Installing and Removing Summit DC-Powered Switches

This section provides additional details about installing or removing the following Summit DC-powered switches:

- Summit X250e-24tDC
- Summit X250e-24xDC
- Summit X250e-48tDC
- Summit X450a-24tDC

- Summit X450a-24xDC
- Summit X450a-48xDC

You must adhere to specific safety requirements when you connect or disconnect a DC power source for one of these Summit switches.

**NOTE**

*For centralized DC power connection, these products are intended to be installed in Restricted Access Locations (Dedicated Equipment Rooms, Equipment Closets, or the like) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.*

**NOTE**

*An optional redundant power supply, the EPS-150DC, is available for use with the Summit DC-powered switches. When the EPS-150DC is used with a DC-powered Summit switch, the power supplies (internal and redundant) are fully fault tolerant and load-sharing. If one power supply fails, the other power supply will provide sufficient power to operate the switch. Refer to “[EPS-150DC External Power Module \(with EPS-T2\)](#)” on page 68 for further details.*

## Connecting the Internal DC Power Supply to the DC Source Voltage

Before you connect the switch to a power source, complete the physical installation of the switch in the equipment rack, as described in “[Rack-Mounting a Summit Switch \(Models Other than Summit X650 Series\)](#)” on page 98.

If you are installing a Summit DC-powered switch, you must ground the chassis before connecting the switch to the DC source voltage (see “[Grounding a Summit DC-Powered Switch](#)” below).

## Grounding a Summit DC-Powered Switch

Before you connect the power input cable to a Summit DC-powered switch, you must ground the chassis, following the instructions in this section.

Gather the following materials to ground the Summit DC-powered switch:

- Stranded copper wire cable, minimum size 14 AWG, maximum size 6 AWG  
The wire should be long enough to reach from the installed switch to the facility ground point
- Torque screwdriver with 1/4-inch flat blade
- Additional grounding hardware appropriate to the earth ground connection at your site

**WARNING!**


*Be sure to connect the chassis ground wire before you connect any power cables.*

To ground the switch:

- 1 At one end of the wire, strip the insulation to expose 1/2 inch (12 mm) of bare wire.
- 2 Identify the grounding lug on the back of the switch. The grounding lug is next to the edge of the back panel, identified by the international symbol for earth ground. Depending on the switch model, the grounding lug may be on either side (see [Figure 67](#)).




**Figure 67: Location of the Grounding Lug**




- 3 Insert the stripped wire into the grounding lug (see [Figure 68](#) and [Figure 69](#)).

**Figure 68: Attaching the Ground Wire to a Summit x450a Series Switch**



**Figure 69: Attaching the Ground Wire to a Summit X250e Series Switch**



- 4 Using a straight-tip torque screwdriver, tighten the retaining screw to 20 pound-inches (2.25 Newton-meters).
- 5 Connect the other end of the wire to a known reliable earth ground point at your site.

## Connecting the DC Wiring Harness to the DC Source Voltage

After the internal DC power supply is installed, it must be connected to a DC power source. A three-wire, 6-foot long DC wiring harness is included with the Summit DC switch and internal DC power supply. The DC wiring harness *must* be properly connected to the DC source voltage at your facility by a qualified electrician before the connector on the wiring harness can be attached to the DC power supply socket on the switch. [Figure 70](#) shows the wiring harness and connector. For information about the wire-to-pin connection, see [Table 41 on page 211](#).



### WARNING!

*The Summit X450a-24tDC or Summit X450a-24xDC switch and rack must be connected to protective earth ground before installing any switch components.*



### WARNING!

*Wiring the DC input power harness to your facilities DC source voltage must be performed by a qualified, licensed electrician. After the wiring harness is connected to a permanent DC voltage source by a qualified, licensed electrician, you can remove, replace and maintain a Summit DC-powered switch without further electrician assistance. However, always be sure that the DC circuit is de-energized before connecting or disconnecting the DC power connections at the rear of the switch.*



### CAUTION


*The DC wiring harness must be properly connected to a DC main circuit breaker rated no greater than 20 A.*



### CAUTION

*Provide proper connection and strain relief on the DC wiring harness in accordance with all local and national electrical codes.*

**Figure 70: Three-wire Cable Harness**



EWUG005



### NOTE

*Each wire on the harness has been properly marked for proper attachment to the DC power source. Leave these labels on each lead wire for future reference.*

## Attaching the DC Wiring Harness to the DC Power Socket on the Switch

After the DC wiring harness is connected to a permanent DC voltage source by a qualified, licensed electrician, you can remove, replace, and maintain the Summit DC-powered switch without further electrician assistance.



### NOTE

Be sure that the DC circuit is de-energized before you connect the DC wiring harness to the DC power socket.



### CAUTION


Be sure that proper ESD controls are in use before switch maintenance is performed. This includes but is not limited to wrist straps that are grounded to the switch chassis and earth grounds.

To attach the DC wiring harness to the internal DC power supply:

- 1 Plug the DC wiring harness connector into the DC power supply socket on the rear of the switch (see [Figure 71](#))

The pins must align properly for the cable to completely connect. Do not force the cable into the socket until the keyway is aligned properly. Refer to [Figure 70](#) for the DC wiring harness connector.

**Figure 71: DC Power Socket on a Summit X250e Series DC-Powered Switch**



### NOTE

[Figure 71](#) shows the rear panel of a Summit X250e series DC-powered switch. The rear panel of other Summit DC-powered switches may vary slightly; however, the DC power socket is of the same type and the connection process is the same for all DC-powered switches.

- 2 Tighten the retainer nut on the connector until it is finger-tight.
- 3 Energize the DC circuit.

## Removing a Summit DC-Powered Switch from a Rack



### WARNING!

Be sure to disconnect all DC power cables before you disconnect the chassis ground wire.

**CAUTION**

*Be sure that proper ESD controls are in use before switch maintenance is performed. This includes but is not limited to wrist straps that are grounded to the switch chassis and earth grounds.*

To remove a DC-powered Summit switch from an equipment rack:

- 1 De-energize the DC circuit for all power connections.
- 2 Loosen the retainer nut and unplug the DC power connector from the DC power socket on the rear of the switch.
- 3 Disconnect the Summit switch from the redundant power supply (if applicable).
- 4 At the back of the switch, loosen the retaining screw on the ground lug and pull the ground wire out of the lug. Move the ground wire out of the way.
- 5 Loosen and remove the four rack system mount screws holding the switch in place against the system rack.
- 6 Carefully remove the switch from the rack and place it on a secure, flat surface.

**WARNING!**

*Removing the DC wiring harness from your facilities DC source voltage requires the performance of a qualified, licensed electrician.*

## Installing a Summit X650 Series Switch

The Summit X650 series switch fits into a standard 19-inch equipment rack. The provided rack-mounting brackets are adaptable to either two-post or four-post (cabinet) mounting.

The installation process includes the following tasks:

- 1 Install the switch in the rack.
- 2 Install one or two power supplies and connect power cables.
- 3 Connect network interface cables.

If you are installing Summit X650 series switches for use in a SummitStack configuration, read [“Building a SummitStack Configuration” on page 90](#) before you install the switches.

**NOTE**

*Take care to load the rack so that it is not top-heavy. Start installing equipment at the bottom and work up.*

## Pre-installation Requirements

Installing the Summit X650 switch requires two people to maneuver the switch and attach mounting hardware.

To allow safe handling of the switch during the installation process, make sure you have the following available space around the rack:

- Back: Minimum 30 inches behind the rack posts or back of the cabinet.

- Sides: For a two-post rack installation, allow adequate space for access to the sides of the switch so that the front mounting brackets can be attached to the switch.

## Selecting Rear Mounting Brackets

To allow installation of the switch in cabinets of different depths, the Summit X650 series switch has two sets of rear mounting brackets. Use the bracket that best suits the cabinet depth or rack depth where the switch will be installed:

- Shorter brackets—cabinets or racks 25 inches to 31 inches (63.5 cm to 76.7 cm) deep
- Longer brackets—cabinets or racks 25 inches to 36 inches (63.5 cm to 91.4 cm) deep

For a two-post rack installation, the shorter brackets are recommended.


## Installing the Switch in a Two-Post Rack

To install the switch in a two-post rack:

- 1 Attach an ESD-preventive wrist strap to your wrist and connect the metal end to an appropriate ground point on the rack.
- 2 Using rack-mounting screws suitable for your rack, attach a rear mounting bracket to the back of each rack post ([Figure 72](#))

Do not tighten the screws all the way. You should be able to move the brackets against the rack post.


**Figure 72: Attaching a Rear Mounting Bracket—Two-Post Rack Installation**



SH\_097

- 3 From the back of the equipment rack, slide the switch into place over the mounting brackets (see [Figure 73](#)). Make sure the brackets slide between the support pegs on both sides of the switch.


**Figure 73: Sliding the Switch onto the Rear Mounting Brackets**



- 4 Push the switch forward as far as it will go, until the bracket support pegs are against the T of the mounting bracket ([Figure 74](#)).

Securely tighten the rack mounting screws.


**Figure 74: Fastening the Rear Mounting Brackets—Two-Post Rack**



- 5 At the front of the switch, place a front mounting bracket against each side of the switch, in front of the ventilation openings in the side of the switch (Figure 75)


Make sure there is space between the bracket and the ventilation openings.

**Figure 75: Positioning the Front Mounting Brackets—Two-Post Rack**



- 6 Using the provided screws, attach each front bracket to the switch (Figure 75).
  - 7 Slide the switch back in the rack until the front mounting brackets are against the front of the rack post (Figure 76).
- Make sure that the ventilation holes in the side of the switch are within the open channel of the rack post.

**Figure 76: Securing the Front Mounting Brackets to the Rack**




- 8 Using mounting screws suitable for your equipment rack, secure the mounting brackets to the front of the rack post.

## Installing the Switch in a Cabinet or Four-Post Rack

To install the switch in a cabinet or four-post rack:


- 1 At the back of the cabinet, attach a rear mounting bracket to each rear post, as shown in [Figure 77](#)

**Figure 77: Attaching Rear Mounting Brackets—Cabinet Installation**



- 2 Attach an ESD-preventive wrist strap to your wrist and connect the metal end to an appropriate ground point on the rack.
- 3 Set the switch on a secure work surface.
- 4 At the front of the switch, attach a rack-mounting bracket to each side ([Figure 78](#)).  
Position the bracket with the flange at the front edge of the switch.


**Figure 78: Attaching the Front Mounting Brackets—Cabinet Installation**



- 5 From the front of the cabinet, slide the switch onto the rear mounting brackets ().




**Figure 79: Installing the Switch—Cabinet Installation**



- 6 Slide the switch all the way into the cabinet and secure the mounting brackets to the front rack posts using suitable screws ([Figure 80](#)).

**Figure 80: Securing the Switch to the Front Rack Posts—Cabinet Installation**



- 7 At each side, fasten the mounting bracket to the back rack post using suitable screws.

## Installing Summit X650 Power Supplies

The Summit X650 series switch is shipped without installed power supplies. The switch accommodates one or two Summit X650 power supply units (PSUs).

### AC Power Supply Cords

An AC power cord is not included with the Summit X650 AC PSU. AC power cords for use in the US and Canada from Extreme Networks or from your local supplier. The cord must meet the following requirements:

- The power cord must be agency-certified for the country of use and rated for 100-240 V AC.
- The power cord must have an IEC 320 C13 connector for connection to the PSU.
- The power cord must have an appropriately rated and approved wall plug applicable to the country of installation.
- For cords up to 6 feet (2 m) long, the wire size must be 18 AWG (.75 mm<sup>2</sup>) minimum; over 6 feet, the minimum wire size is 16 AWG (1.0 mm<sup>2</sup>).

For additional power cord requirements, see [“Selecting Power Supply Cords”](#) on page 170.

### Installing a Summit X650 AC Power Supply




#### CAUTION

*Make sure that the AC PSU circuit is not overloaded. Use proper over-current protection, such as a circuit-breaker, to prevent over-current conditions.*

To install a Summit X650 AC PSU:

- 1 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate grounding point.
- 2 If necessary, remove a blank panel from the back of the Summit X650 series switch ([Figure 81](#)).

**Figure 81: Removing a Blank Panel**



- 3 Verify that the PSU is right side up, with the latching tab at the right of the unit (see [Figure 82](#)).


- Carefully slide the PSU all the way into the power supply bay (see [Figure 82](#)). Push the PSU in until the latch snaps into place.



#### CAUTION

*Do not slam the PSU into the switch.*

**Figure 82: Installing a PSU**



- To install a second PSU, repeat steps [3](#) and [4](#).



#### NOTE

*If PSUs are not installed in both power supply bays, be sure to install a cover over the unoccupied bay. Unoccupied bays must always be covered to maintain proper system ventilation and EMI levels.*

- Connect an appropriate AC power cord to the power input socket; connect the other end of the power cord to a grounded AC power outlet.



#### WARNING!

*Always be sure that the source outlet is properly grounded before plugging the AC power cord into the AC PSU.*

## Installing a Summit X650 DC Power Supply



#### CAUTION

*Make sure that the Summit X650 DC PSU circuit is not overloaded. Use proper over-current protection, such as a circuit-breaker, to prevent over-current conditions. You may use up to a 30-Amp breaker.*

To install the Summit X650 DC PSU, perform the following tasks in the order listed:

- Prepare the power cables and ground cable by attaching the provided connection lugs to the cables (see next section).
- Insert the PSU into the Summit X650 series switch (see [“Installing the Power Supply”](#) on page 113).
- Connect the ground (see [“Connecting the Ground Cable”](#) on page 114).

- 4 Have a qualified licensed electrician connect the PSU to the DC source voltage (see [“Connecting the PSU to the DC Source Voltage”](#) on page 115).
- 5 Energize the DC circuit.

## Required Tools and Materials

You need the following tools and materials to install or remove a Summit X650 DC PSU:

- Two spade terminals (Tyco part number 130496 or equivalent) for connecting the input power cables (provided)
- One ring terminal (Tyco part number 130496 or equivalent) and screw with captive lock washer (type M3.5) for connecting the ground wire (both provided)
- #12 AWG stranded copper cable for grounding the PSU and connecting the PSU to the DC power source

A DC power cord is not included with the Summit X650 DC PSU. You must provide the #12 AWG stranded copper cable. Recommended insulation colors are:

- Red for the –48V connection (–)
- Black for the –48V RTN connection (+)
- Green or green with yellow stripe for the ground connection
- Connection hardware appropriate to the installation site:
  - Hardware for connecting the power wires to the DC source
  - Hardware for connecting the ground wire to the site grounding point
- Stripping tool
- Crimping tool for attaching the lug to the ground wire
- #1 Phillips screwdriver
- Torque screwdriver and wrench or torque driver with attachments for tightening screws and nuts
- ESD-preventive wrist strap
- Thermal protective gloves (required for removal of a PSU)

Connection lugs for power and ground and a screw for connecting the ground wire are shipped with the power supply.


## Preparing the Cables

A ring terminal and two spade terminals are provided with the PSU. You need a crimping tool to attach the terminals to the power and ground cables.

To prepare the cables:

- 1 On each wire, strip 0.25 inch of insulation from one end.
- 2 Insert the stripped wire end all the way into the barrel of the terminal ([Figure 83](#)) and crimp the terminal securely to the wire.

**Figure 83: Attaching Terminals to Cables**



## Installing the Power Supply




### CAUTION

*The handle on the Summit X650 DC PSU is not designed to be used to lift or carry the Summit X650 series switch.*

To install a Summit X650 DC PSU:

- 1 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate ground point on the rack.
- 2 If necessary, remove a blank panel from the back of the Summit X650 series switch ([Figure 84](#)).

**Figure 84: Removing a Blank Panel**




- 3 Verify that the PSU is right side up (see [Figure 85](#)).
- 4 Carefully slide the PSU all the way into the power supply bay (see [Figure 85](#)). Push the PSU in until the latch snaps into place.



### CAUTION

*Do not slam the PSU into the switch.*

**Figure 85: Installing a Summit X650 DC PSU**

SH\_107

- 5 To install more PSUs, repeat steps 3 and 4.

## Connecting the Ground Cable




### WARNING!

*Be sure to connect the chassis ground wire before you connect any power cables.  
Be sure to disconnect the ground wire after you disconnect all power cables.*

To connect the ground wire:

- 1 Verify that the DC circuit is de-energized.
- 2 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate ground point on the rack.
- 3 Identify the grounding point on the front panel of the PSU (see [Figure 86](#)).
- 4 Insert an M3.5 screw (provided) through the ring terminal and into the grounding point on the PSU.
- 5 Tighten the screw to 12.6 inch-pounds.
- 6 Connect the other end of the wire to a known reliable earth ground point at your site.

**Figure 86: Connecting the Ground Wire**



## Connecting the PSU to the DC Source Voltage

The DC power connection at your facility *must* be made by a qualified electrician, following the instructions in this section.



### WARNING!

*Always make sure that the DC circuit is de-energized before connecting or disconnecting the DC power cables on the Summit X650 DC PSU.*




### CAUTION

*Provide proper connection and strain relief on the DC power cables in accordance with all local and national electrical codes.*

To connect the DC power input cables:


- 1 Verify that the DC circuit is de-energized.
- 2 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate ground point on the rack.
- 3 Slide the cover off the terminal block ([Figure 87](#)).
- 4 Connect the DC power input cables as follows:
  - a On each terminal, loosen the screw enough to allow the spade terminal to slide underneath the captive square washer.
  - b Slide the spade terminal of the **negative** wire (–48 V) under the captive square washer on the **negative** terminal (labeled –48V).
  - c Slide the spade terminal of the **positive** wire (–48 V RTN) under the captive square washer on the **positive** terminal (labeled RTN).

**Figure 87: Connecting the DC Power Cables (Part 1)**

- d Tighten both screws on the terminal block to 11 inch-pounds ([Figure 88](#)).
- 5 Slide the cover into place over the terminal block ([Figure 88](#)).



**Figure 88: Connecting the DC Power Cables (Part 2)**



SH\_112

- 6 Connect the cables to the DC source voltage, using hardware appropriate to the installation site and following local and national electrical codes.
- 7 Energize the DC circuit.

Leave the ESD strap permanently connected to the rack, so that the strap is always available when you need to handle ESD-sensitive components.

## Removing Summit X650 Series Switches

This section provides procedures for removing a Summit X650 series switch from a two-post or four-post equipment rack.

### Removing the Power Supplies


Before you remove a Summit X650 series switch from the rack, remove all installed power supplies, as described in this section.

## Removing a Summit X650 AC Power Supply'

To remove an AC power supply:

- 1 Attach an ESD-preventive wrist strap to your wrist and connect the metal end to an appropriate ground point on the rack.
- 2 Disconnect all power cords from the back of the switch.
- 3 Remove all installed power supplies (Figure 89):
  - a On each power supply, push the latching tab to the left as you pull the handle to disengage the power supply from its internal connectors.
  - b Carefully slide the power supply out of the switch and set it aside.

**Figure 89: Removing an AC Power Supply**



## Removing a DC Power Supply



### WARNING!

*Be sure to disconnect all power cables before you disconnect the chassis ground wire.*



### CAUTION


*The DC PSU may be hot to the touch; use thermal protective gloves when handling the PSU during removal.*

To remove a Summit X650 DC PSU:

- 1 De-energize the DC circuit.
- 2 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate ground point on the rack.
- 3 Disconnect the DC power cables as follows:
  - a Slide the cover off the terminal block.
  - b Loosen the screws that secure the cable terminals to the terminal block.
  - c Slide the wires out from under the captive washers.

- 4 Disconnect the ground wire as follows:
  - a Remove the screw that secures the ground wire to the PSU.
  - b Move the wire away from the PSU.
- 5 Push the latching tab to the left as you pull outward on the handle to disengage the PSU internal connectors (see [Figure 90](#)).

**Figure 90: Removing a DC PSU**



## Removing a Summit X650 Series Switch from a Two-Post Rack

Removing the Summit X650 switch from a rack requires two people to maneuver the switch and disconnect the mounting hardware.




### CAUTION


*Make sure that proper ESD controls are in use before maintenance is performed. This includes but is not limited to wrist straps that are grounded to the switch chassis and earth grounds.*

To remove the Summit X650 series switch from a two-post rack:

- 1 Attach an ESD-preventive wrist strap to your wrist and connect the metal end to an appropriate ground point on the rack.
- 2 Verify that the power supplies have been removed from the switch.
- 3 At the front of the equipment rack, support the switch while you remove the rack-mounting screws holding the front mounting brackets in place against the rack post ([Figure 91](#)).


**Figure 91: Removing the Front Mounting Screws from a Two-Post Rack**

- 4 Remove the screws holding the front mounting brackets to the sides of the switch, and set the mounting brackets aside.
- 5 Support the front and back of the switch as you slide the switch back, off the rear mounting brackets, and out of the rack ([Figure 92](#)).  
Set the switch on a secure work surface.

**Figure 92: Removing the Switch from a Two-Post Rack**

- 6 Remove the rack-mounting screws and detach the rear mounting brackets from the rack post (Figure 93).

**Figure 93: Removing the Rear Mounting Brackets—Two-Post Rack**




SH\_097

## Removing a Summit X650 Series Switch from a Cabinet or Four-Post Rack

Removing the Summit X650 switch from a cabinet or rack requires two people to maneuver the switch and disconnect the mounting hardware.

To remove the Summit X650 series switch from a cabinet or four-post rack:

- 1 Attach an ESD-preventive wrist strap to your wrist and connect the metal end to an appropriate ground point on the rack.
- 2 Disconnect all power cords from the back of the switch.
- 3 Remove all installed power supplies:
  - a Push the latching tab to the left as you pull the handle to disengage the power supply from its internal connectors.
  - b Carefully slide the power supply out of the switch and set it aside.
- 4 Support the front of the switch while you remove the front rack mounting screws (Figure 94).
- 5 Carefully slide the switch forward out of the cabinet and off the rear mounting brackets.

**Figure 94: Removing the Switch from a Cabinet**

- 6 Set the switch on a secure work surface. Using a #1 Phillips screwdriver, remove the front mounting brackets from the sides of the switch.
- 7 Remove the rear mounting brackets from the rear rack posts.

## Connecting Network Interface Cables

Use the appropriate type of cable to connect the ports of your switch to another switch or router. For connections to the 10GBASE-T ports on the Summit X650-24t switch, see [Table 19](#) for cable types and distances.

**Table 19: Cable Distances for 10GBASE-T Ports**

| Cable Type | Maximum Distance |
|------------|------------------|
| CAT5E      | 55 meters        |
| CAT6       | 55 meters        |
| CAT6A      | 100 meters       |

**NOTE**

Cables used for connection to the 10GBASE-T ports on the Summit X650-24t switch must meet the minimum requirements of the IEEE 802.3an standard.

Working carefully, one port at a time:

- 1 Verify that you have identified the correct cable for the port.
- 2 Use an alcohol wipe or other appropriate cleaning agent to clean the cable connectors; make sure they are free of dust, oil, and other contaminants.
- 3 If you are using optical fiber cable, align the transmit (Tx) and receive (Rx) connectors with the correct corresponding connectors on the switch or the I/O module.
- 4 Press the cable connectors into their mating connectors on the switch or I/O module until the cable connector is firmly seated.
- 5 Repeat steps 1 through 4 for the remaining cables on this or other switches or I/O modules.
- 6 Dress and secure the cable bundle to provide appropriate strain relief and protection against bends and kinks.

## Initial Management Access

When you take your switch from the box and set it up for the first time, you must connect to the console to access the switch and perform initial security configuration. At this time you can also manually configure an IP address for the default VLAN.

## Connecting Equipment to the Console Port

Connection to the console port is used for direct local management. The console port settings are:

- Baud rate—9600
- Data bits—8
- Stop bit—1
- Parity—None
- Flow control—XON/XOFF

The terminal or PC with terminal-emulation software that you connect to an Extreme Networks switch must be configured with these settings. This procedure is described in the documentation supplied with the terminal.

Appropriate cables are available from your local supplier, or you can make your own. To ensure the electromagnetic compatibility of the unit, use only shielded serial cables. For connector pinouts associated with the console port, see [“Console Connector Pinouts” on page 212](#).

## Logging In for the First Time

After your switch has completed all power on self-tests, it is operational. You can log in and configure an IP address for the default VLAN (named *default*).



### NOTE

*The management port is part of the management VLAN by default.*

To manually configure the IP settings:

- 1 Connect a terminal or PC with terminal-emulation software to the console port on the Summit switch.
- 2 At the terminal, press [Return] one or more times until you see the login prompt.
- 3 At the login prompt, enter the default user name *admin* to log on with administrator privileges. For example:

```
login: admin
```

Administrator capabilities allow you to access all switch functions.

- 4 The system will ask a series of questions about the default management settings, which allow all forms of management access for convenience in setting the initial configuration. Answer each question based on the level of security needed for the particular management access type.



### NOTE

*For more information about logging in to the switch and configuring switch management access, see the ExtremeXOS 12.0 Concepts Guide.*

- 5 At the password prompt, press [Return].

The default user name *admin* has no password assigned to it. When you have successfully logged on to the system, the command line prompt displays the system name (for example, *SummitX450>*) in its prompt.



### NOTE

*For more information about how to assign a specific system name, see the ExtremeXOS 12.0 Concepts Guide.*

- 6 Assign an IP address and subnetwork mask for VLAN *default* by typing:  

```
configure vlan default ipaddress 123.45.67.8 255.255.255.0
```

 Your changes take effect immediately.
- 7 Save your configuration changes so that they will be in effect after the next system reboot by typing:  

```
save
```

The configuration is saved to the configuration database of the MSM modules in the switch.



### NOTE

*For more information about saving configuration changes, see the ExtremeXOS 12.0 Concepts Guide.*

- 8 When you are finished with these tasks, log out of the switch by typing:

```
logout
```



This chapter describes how to install external power supplies with the Summit family switches. The chapter includes the following sections:

- [Safety on page 125](#)
- [Installing an EPS-160 External Power Module \(with EPS-T\) on page 126](#)
- [Installing an EPS-LD External Power Supply on page 129](#)
- [Installing an EPS-500 External Power Supply Unit on page 132](#)
- [Installing an EPS-150DC External Power Module \(with EPS-T2\) on page 135](#)
- [Installing an EPS-600LS External Power Module on page 140](#)

Read the information in this chapter thoroughly before you start to install or remove an external power supply.

## Safety

Only trained service personnel should perform service to Extreme Networks switches and their components. Trained service personnel have read all related installation manuals, have the technical training and experience necessary to be aware of the hazards to which they are exposed in performing a task, and are aware of measures to minimize the danger to themselves or other persons.



### NOTE

See [Appendix A, “Safety Information”](#) for additional safety information and [Appendix B, “Technical Specifications”](#) for additional information regarding regulatory compliance certifications.



### CAUTION

*Be sure that proper ESD controls are in use before switch maintenance is performed. This includes but is not limited to wrist straps that are grounded to the switch chassis and earth grounds.*



### CAUTION

*The EPS must be installed or removed only by trained service personnel in accordance with the installation instructions. Before installing or removing any components of the system, or before carrying out any maintenance procedures, read the safety information provided in [Appendix A](#) of this guide. Not following these precautions can result in equipment damage or shock.*



### WARNING!

*Extreme Networks AC PSUs do not have switches for turning the unit on and off. Remove the wall plug from the electrical outlet to disconnect the power to an Extreme Networks AC PSU. Make sure that this connection is easily accessible.*

*When the PSU is outside the chassis (not installed), do not plug the PSU into an electrical outlet. Plugging an uninstalled AC PSU into an electrical outlet exposes you to a hazardous energy and is a potential fire hazard.*

**WARNING!**

*Always be sure that the DC circuit is de-energized before connecting or disconnecting the DC wiring harness at the DC power socket on the rear of the EPS-150DC unit, and before connecting or disconnecting the redundant power cord between the switch and the EPS-150DC unit.*

## Pre-installation Requirements

You need the following tools and equipment to install an external power supply:

- Electrostatic discharge (ESD)-preventive wrist strap
- # 1 Phillips screwdriver
- Rack mount screws suitable for your organization's equipment rack
- Screwdriver suitable for use with your rack-mount screws
- AC power cord

An AC power cord is not included with the external power supply. You must obtain a power supply cord that meets the requirements listed under [“Selecting Power Supply Cords” on page 170](#).

**NOTE**

*When you connect an external power supply, consider all of the equipment that is connected to the power supply circuit to ensure that the circuit is not overloaded. Use proper overcurrent protection, such as a circuit breaker, to prevent overcurrent conditions.*

*The switch and each redundant power supply source should be plugged into separate branch circuits to provide redundancy.*

## Installing an EPS-160 External Power Module (with EPS-T)

You can order the EPS-T chassis with one or two EPS-160 power supplies already installed. You can also order an additional power supply from your Extreme Networks reseller.

The EPS-T can be mounted in a rack or placed free-standing on a tabletop.

## Rack-Mounting the EPS-T


**CAUTION**

*Do not use the rack-mount brackets to suspend the EPS-T from under a table or desk, or to attach the EPS-T to a wall.*

To rack mount the EPS-T:

- 1 Place the EPS-T upright on a stable surface, with the front facing you.
- 2 Remove the mounting bracket kit from the packaging.
- 3 Attach the mounting brackets as follows:
  - a Place a mounting bracket over the mounting holes on one side of the EPS-T (see [Figure 95](#)).
  - b Insert the screws and fully tighten them using a screwdriver.

**Figure 95: Attaching the Mounting Bracket**



- c Repeat steps [a](#) and [b](#) for the other side of the EPS-T.
- 4 Slide the EPS-T into a 19-inch rack and secure it using appropriate rack-mount screws.


## Installing an EPS-160 Power Supply into an EPS-T

To install an EPS-160 power supply into the EPS-T:

- 1 Remove the EPS-160 power supply from the packing material.
- 2 Remove the cover plate from an empty slot on the EPS-T.
- 3 Insert the power supply into the empty slot on the EPS-T.
- 4 Tighten the captive thumbscrews to secure the power supply to the EPS-T.
- 5 Connect the EPS-160 power supply to the Summit switch, following the instructions in the next section, "[Connecting the EPS-160 Power Supply to the Switch](#)."

## Connecting the EPS-160 Power Supply to the Switch

One end of the EPS-160 redundant power cord has a keyed connector to ensure correct alignment of the connector ([Figure 96](#)). The key is a plastic tab on the cord connector housing that fits into the EPS-160 unit to ensure correct alignment of the connector.

**Figure 96: Redundant Power Cord Connector****CAUTION**

Always connect the redundant power supply cord before you attach the AC power cord to the EPS-160 power supply.

To connect the EPS-160 power supply to the switch:


- 1 Connect the keyed end of the redundant power supply cord to the EPS-160 power supply (see [Figure 97](#)).
- 2 Connect the other end of the redundant power supply cord to the Extreme switch (see [Figure 97](#)).  
This connector end can only be inserted into the switch with the end marked TOP facing up.

**NOTE**

If your switch was shipped with a metal cover plate over the redundant power input connector, remove the cover.

**WARNING!**

The redundant power input connector on the rear of the switch contains high energy and is a burn hazard. Use care when connecting the redundant power supply cord to the rear of the switch.

**Figure 97: Redundant Power Connections**

- 3 Connect an appropriate AC power cord to the AC connector on each unit.

**NOTE**

An AC power cord is not provided with the EPS-160 unit. See [“Selecting Power Supply Cords”](#) on page 170 for information about selecting a power cord.

The PSU-E LED on the front of the EPS-160 should light solid green to indicate that it is ready.

Table 20 shows the LED meanings for the EPS-160.

**Table 20: LED Meanings on the EPS-160 Power Supply**

| Power LED    | Indicates  |
|--------------|--|
| Green, solid | The external power supply is operating normally. |
| Off          | The external power supply is not connected.      |

## Removing an EPS-160 Power Supply from an EPS-T

To remove an EPS-160 power supply from an EPS-T:

- 1 Disconnect the AC power by removing the plug from the wall.
- 2 Disconnect the AC power cord from the EPS-160.
- 3 Disconnect the redundant power cord from the EPS-160.
- 4 Loosen the captive retaining screws on the front of the EPS-160 and slide it out of the EPS-T.

## Installing an EPS-LD External Power Supply

The EPS-LD power supply can be mounted in a rack or placed free-standing on a tabletop. You can position the EPS-LD facing either the front or the back of the rack. For this reason, each unit has two sets of mounting holes on each side. Extreme Networks recommends that you position the EPS-LD so that the power output connectors on the EPS-LD unit are on the same side as the external connector on the connecting switch.



### CAUTION

*Do not use the rack-mount brackets to suspend the EPS-LD from under a table or desk, or to attach the unit to a wall.*



### NOTE

*An AC power cord is not provided with the EPS-LD power supply. See “[Selecting Power Supply Cords](#)” on page 170 for information about selecting a power cord.*

## Rack-mounting the EPS-LD Power Supply




### NOTE

*When installing an EPS-LD in a rack, make sure air vents are not restricted. Allow for elevated ambient operating temperatures when the EPS-LD is installed adjacent to other equipment. Be sure you mount the equipment in the rack so that the load is evenly distributed.*

To rack-mount each EPS-LD unit:

- 1 Place the EPS-LD unit upright on a stable surface, with the side you want to face to the front of the switch toward you.
- 2 Remove the mounting bracket kit from the packaging.
- 3 Attach the mounting brackets as follows:
  - a Place a mounting bracket over the mounting holes on one side of the unit (see [Figure 98](#)).
  - b Insert the provided screws and fully tighten them using a screwdriver.

**Figure 98: Attaching the Mounting Bracket**



XM\_054

- c Repeat steps [a](#) and [b](#) for the other side of the EPS-LD unit.
- 4 Slide the EPS-LD into a 19-inch rack and secure it using appropriate rack-mount screws.



#### NOTE

*Extreme Networks recommends that you position the EPS-LD so that the output connectors are on the same side as the external connector on the connecting switch. If you mount the EPS-LD with the connectors facing in the opposite direction from the Summit switch connector, leave at least 1 U between the switch and the EPS-LD through which to slide the power cords. Do not route the power cords around the equipment rack.*

## Connecting the EPS-LD to the Switch




#### CAUTION

*Do not attach the AC power cord to the EPS-LD unit until the unit is properly grounded at the electrical outlet and the redundant power supply cord is connected.*

One end of the EPS-LD cord has a keyed connector to ensure correct alignment of the connector ([Figure 99](#)). The key is a plastic tab on the cord connector housing that fits into the EPS-LD unit to ensure correct alignment of the connector.

**Figure 99: EPS-LD Connector with Key**



XM\_055

To connect the EPS-LD to the switch:

- 1 Connect the keyed end of the cord to the power supply unit (see [Figure 100](#)).
  - 2 Align and tighten the captive retaining screws on the connector.
  - 3 Connect the other end of the EPS-LD cord to the Extreme switch.
- The connector fits in only one direction.



**NOTE**


*If your switch was shipped with a metal cover plate over the redundant power input connector, remove the cover.*



**WARNING!**

*The redundant power input connector on the rear of the switch contains high energy and is a burn hazard. Use care when connecting the redundant power supply cord to the rear of the switch.*

**Figure 100: Connecting an EPS-LD Unit to a Switch**



XM\_053

## Connecting the EPS-LD to Power

An AC input power cord is not provided with the EPS-LD. For information about power cord requirements, see [“Selecting Power Supply Cords” on page 170](#).

Make sure the EPS-LD is connected to the switch before you connect the AC power.

**CAUTION**

*The EPS-LD does not have a switch for turning the unit on and off. You disconnect power to the EPS-LD by removing the plug from the electrical outlet. Make sure that this connection is easily accessible.*

To connect the EPS-LD to power:

- 1 Connect the AC input power cord to the AC connector on the EPS-LD.
- 2 Connect the other end of the AC cord to the electrical outlet.

Make sure the electrical outlet is properly grounded.

The Power LED on the front of the EPS-LD turns solid green to indicate that it is ready.

Table 21 shows the LED meanings for the EPS-LD power supply.

**Table 21: LED Meanings on the EPS-LD**

| Power LED    | Indicates  |
|--------------|--|
| Green, solid | The external power supply is operating normally. |
| Off          | The external power supply is not connected.      |

## Removing an EPS-LD

To remove an EPS-LD power supply:

- 1 Disconnect the AC power by removing the plug from the wall.
- 2 Disconnect the AC power cord from the EPS-LD unit.
- 3 Disconnect the cord between the Extreme switch and the EPS-LD.
- 4 Remove the screws from the EPS-LD mounting brackets.
- 5 Slide the EPS-LD out of the rack.

## Installing an EPS-500 External Power Supply Unit

You can position the EPS-500 facing either the front or the back of the rack. For this reason, each unit has two sets of mounting holes on each side. Extreme Networks recommends that you position the EPS-500 unit so that the power output connectors of the EPS-500 unit are on the same side as the external connector on the connecting switch.

The EPS-500 unit can be mounted in a rack or placed free-standing on a tabletop.

**NOTE**

*An AC power cord is not provided with the EPS-500 unit. See [“Selecting Power Supply Cords”](#) on page 170 for information about selecting a power cord.*



## Rack-mounting an EPS-500 Power Supply



### CAUTION


When installing an EPS-500 in a rack system, make sure that the air vents are not restricted. Allow for elevated ambient operating temperatures when the unit is installed adjacent to other equipment. To avoid hazardous conditions due to uneven mechanical loading, make sure that the equipment is mounted properly in the rack system.

Do not use the rack-mount brackets to suspend the EPS-500 from under a table or desk, or to attach the unit to a wall.

To rack-mount each EPS-500:

- 1 Place the EPS-500 upright on a stable surface, with the side you want to face to the front of the switch toward you.
- 2 Remove the mounting bracket kit from the packaging.
- 3 Attach the mounting brackets as follows:
  - a Place a mounting bracket over the mounting holes on one side of the EPS-500 (see [Figure 101](#)).
  - b Insert the provided screws and fully tighten the screws using a screwdriver.

**Figure 101: Attaching a Mounting Bracket**



XM\_073

- c Repeat steps [a](#) and [b](#) on the opposite side of the EPS-500.
- 4 Slide the EPS-500 into a 19-inch rack and secure it using appropriate rack-mount screws.



### NOTE

Extreme Networks recommends that you position the EPS-500 so that the output connectors are on the same side as the external connector on the connecting switch. If you position the EPS-500 with the connectors facing in the opposite direction from the Summit switch connector, leave at least 1 u between the switch and the EPS-500 through which to slide the power cords. Do not route the power cords around the equipment rack.

## Connecting the EPS-500 Power Supply




### CAUTION

Do not attach the AC power cord to the EPS-500 unit until the unit is properly grounded at the electrical outlet and the redundant power cord is connected.

One end of the EPS-500 cord has a keyed connector to ensure correct alignment of the connector (Figure 102). The key is a plastic tab on the connector housing that fits into the EPS-500 unit to ensure correct alignment of the connector.

**Figure 102: EPS-500 Redundant Power Cord with Connector Key**



XM\_055

- 1 Connect the keyed end of the EPS-500 redundant power cord to the power supply unit (see Figure 103).
- 2 Connect the other end of the redundant power cord to the Extreme switch.  
The connector fits the slot in only one direction.



**NOTE**


*If your switch was shipped with a metal cover plate over the redundant power input connector, remove the cover.*



**WARNING!**

*The redundant power input connector on the rear of the switch contains high energy and is a burn hazard. Use care when connecting the redundant power supply cord to the rear of the switch.*

**Figure 103: Connecting an EPS-500 Unit to a Switch**



XM\_074

- 3 Connect an appropriate AC input power cord to the AC connector on the EPS-500 unit.



#### NOTE

An AC power cord is not provided with the EPS-500 unit. See [“Selecting Power Supply Cords” on page 170](#) for information about selecting a power cord.



#### CAUTION

The EPS-500 unit does not have a switch for turning the unit on and off. Disconnect power to the EPS-500 unit by removing the plug from the electrical outlet. Be sure that this connection is easily accessible to you.

- 4 Connect the other end of the AC power cord to the electrical outlet.

Be sure that the electrical outlet is properly grounded.

The Power LED on the front of the EPS-500 unit turns solid green to indicate that it is ready. [Table 22](#) shows the LED meanings for the power supply.

**Table 22: LED Meanings on the EPS-500 Power Supply**

| Power LED    | Indicates  |
|--------------|--|
| Green, solid | The external power supply is operating normally. |
| Off          | The external power supply is not connected.      |

## Removing an EPS-500 Power Supply

To remove an EPS-500 power supply:

- 1 Disconnect the AC power by removing the plug from the wall.
- 2 Disconnect the AC power cord from the EPS-500 power supply.
- 3 Remove the redundant power cord that connects the switch to the power supply.
- 4 Remove the mounting screws securing the power supply to the rack.
- 5 Slide the power supply out of the rack.

## Installing an EPS-150DC External Power Module (with EPS-T2)

The EPS-150DC power supply is a modular power supply for use in the EPS-T2 External Power System Tray. The EPS-T2 is a rack-mountable chassis or tray that holds one or two EPS-150DC power supplies. Each EPS-150DC provides one-to-one redundancy to an attached Extreme Networks switch. You must install the EPS-150DC power supply in the EPS-T2 tray.



#### NOTE

For centralized DC power connection, this product is intended to be installed in restricted access locations (dedicated equipment rooms, equipment closets, or the like) in accordance with Articles 110-16, 110-17, and 110-18 of the National Electric Code, ANSI/NFPA 70.

**CAUTION**


*Do not use the rack-mount brackets to suspend the EPS-T2 from under a table top or desk, or to attach the EPS-T2 to a wall.*

## Rack-mounting the EPS-T2

To install the EPS-T2:

- 1 Place the EPS-T2 upright on a secure surface, with the front facing you.
- 2 Remove the mounting bracket kit from the packaging.
- 3 Attach the mounting brackets as follows:
  - a Place a mounting bracket over the mounting holes on one side of the EPS-T2 (see [Figure 104](#)).
  - b Insert the provided screws and fully tighten with a screwdriver.

**Figure 104: Attaching the Mounting Bracket**



- c Repeat steps [a](#) and [b](#) for the other side of the EPS-T2.
- 4 Slide the EPS-T2 into a 19-inch rack and secure it using appropriate rack-mount screws.

## Installing an EPS-150DC Power Supply

**NOTE**

*Install the EPS-T2 before you begin installing the EPS-150DC.*

**WARNING!**

*Always be sure that the DC circuit is de-energized before connecting or disconnecting the DC wiring harness at the DC power socket on the rear of the EPS-150DC unit, and before connecting or disconnecting the redundant power cord between the switch and the EPS-150DC unit.*

Installing an EPS-150DC unit consists of the following tasks:

- Connecting the DC wiring harness to the DC source voltage (see [page 137](#)).  
This task must be performed by a licensed, qualified electrician.

- Installing an EPS-150DC unit in an EPS-T2 (see [page 138](#))
- Connecting the DC wiring harness to the DC power socket on the EPS-150DC (see [page 138](#))
- Connecting the EPS-150DC to a switch (see [page 138](#))

Perform these four tasks in the order they are described.

## Connecting the DC Wiring Harness to the DC Source Voltage

The EPS-150DC power module must be connected to a DC power source. A three-wire, 6-foot long DC wiring harness ([Figure 105](#)) is included with the EPS-150DC unit. The DC wiring harness *must* be properly connected to the DC source voltage at your facility by a qualified electrician before the connector on the wiring harness can be attached to the DC power supply socket on the rear of the unit. See [Appendix B, “Technical Specifications”](#) for information about connector pinouts and for DC power specifications to be used in connecting the wiring harness to the DC source voltage.



### WARNING!

*Wiring the EPS-150DC DC wiring harness to your facilities DC source voltage must be performed by a qualified, licensed electrician. After the wiring harness is connected to a permanent DC voltage source by a qualified, licensed electrician, you can remove, replace and maintain the ESP-150DC without further electrician assistance. However, always be sure that the DC circuit is de-energized before connecting or disconnecting the DC power connection at the rear of the EPS-150DC unit.*




### CAUTION

*The DC wiring harness must be properly connected to a DC main circuit breaker or fuse rated no greater than 20 A.*

*Provide proper connection and strain relief on the DC wiring harness in accordance with all local and national electrical codes.*

**Figure 105: Three-wire Cable Harness**



EWUG005



### NOTE

*Each wire on the harness has been properly marked for proper attachment to the DC power source. Leave these labels on each lead wire for future reference.*

## Installing an EPS-150DC Unit into an EPS-T2



### WARNING!

*The EPS-150DC unit and rack must be connected to protective earth ground.*

To install an individual EPS-150DC into an EPS-T2:

- 1 Attach an ESD-preventive wrist strap to your wrist and connect the metal end to the ground receptacle on the top right corner of the switch front panel.
- 2 Remove the EPS-150DC from the packing material.
- 3 Insert the EPS-150DC into the front of the EPS-T2.
- 4 Tighten the provided thumbscrews to secure the power supply to the tray.

## Connecting the DC Wiring Harness to the DC Power Socket on the EPS-150DC

After the DC wiring harness is connected to a permanent DC voltage source by a qualified, licensed electrician, you can remove, replace, and maintain the EPS-150DC unit without further electrician assistance.



### WARNING!


*Always be sure that the DC circuit is de-energized before connecting the DC wiring harness to the DC power socket.*

To connect the DC wiring harness to the EPS-150DC unit:

- 1 Verify that the DC power is turned off at the source.
- 2 Plug the DC cable connector into the DC power supply socket on the rear of the EPS-150DC unit.

The pins must align properly for the cable to completely connect. Do not force the cable into the socket until the keyway is aligned properly. Refer to [Figure 105](#) for the DC wiring harness connector and to [Figure 106](#) for the DC power socket location on the rear of the EPS-150DC unit.

**Figure 106: Connecting the Input Cable to the EPS-150DC Unit**



- 3 Tighten the retainer nut on the connector until it is finger tight.

## Connecting the EPS-150DC to a Switch

If you are connecting the EPS-150DC unit to a Summit X450a-48tDC switch, you must ground the switch before connecting power. For instructions on grounding the switch, see [“Grounding a Summit DC-Powered Switch” on page 99](#).




## WARNING!

Always be sure that the DC circuit is de-energized before connecting the EPS-150DC to the switch.

One end of the EPS-150DC cord has a keyed connector to ensure correct alignment of the connector (Figure 107). The key is a plastic tab on the connector housing that fits into the EPS-150DC unit to ensure correct alignment of the connector.

**Figure 107: EPS-150DC Redundant Power Cord with Connector Key**




XM\_055

To connect the EPS-150DC to a switch:

- 1 Verify that the DC power is turned off at the source.
- 2 Identify the keyed end of the redundant power cable.
- 3 Holding the keyed connector so that the side labeled “Top” is facing up, connect the EPS-150DC redundant power cable to the power supply unit (see Figure 108).
- 4 Align and tighten the connector retaining screws to secure the cable connector to the power supply unit.
- 5 Connect the other end of the redundant power cord to the Extreme switch.  
The connector fits the slot in only one direction.
- 6 Align and tighten the captive retaining screws to secure the cable connector to the switch.

**Figure 108: Connecting an EPS-150DC Unit to a Switch**



EPS-150DC\_002B

## 7 Energize the DC circuit.

The Power LED on the front of the EPS-150DC unit turns solid green to indicate that it is ready. [Table 22](#) shows the LED meanings for the power supply.

**Table 23: LED Meanings on the EPS-150DC Power Supply**

| Power LED    | Indicates  |
|--------------|--|
| Green, solid | The external power module is operating normally. |
| Off          | The external power module is not connected.      |

## Removing an EPS-150DC Power Module



### WARNING!

*Always be sure that the DC circuit is de-energized before disconnecting any cables and attempting to remove an EPS-150DC unit.*



### WARNING!

*Removing the DC wiring harness from your facilities DC source voltage requires the performance of a qualified, licensed electrician.*

To disconnect and remove an EPS-150DC unit:

- 1 Attach the ESD strap to your wrist and connect the metal end to the ground receptacle on the top-right corner of the switch front panel.
- 2 De-energize the DC circuit.
- 3 Remove power from the EPS-150DC power module by unplugging the DC connector from the DC power supply socket on the rear of the EPS-150DC unit.  
Loosen the retainer nut on the DC power connector and unplug the connector from the back of the power unit.
- 4 At each end of the redundant power cable, unscrew the captive retaining screws on the power connector and disconnect the cable from the switch and the EPS-150DC unit.
- 5 Loosen the thumbscrews on the front of the EPS-150DC unit until they are completely free of the EPS-T tray, and slide the EPS-150 unit out of the tray.

## Installing an EPS-600LS External Power Module

You install one, two, or three EPS-600LS power modules (model 10913) in the EPS-C chassis (Model No. 10912) to build an external redundant power system for a Summit PoE-capable switch. A redundant power cable shipped with the EPS-C chassis provides the connection between the external power system and the redundant power input connector on the back of the switch.





## NOTE

An AC power cord is not provided with the EPS-600LS power module. See [“Selecting Power Supply Cords”](#) on page 170 for information about selecting a power cord.

Each EPS-C chassis is shipped with a special redundant power supply cord for connection to the Summit switch. Make sure that the EPS-C chassis is installed in the rack system before installing an EPS-600LS unit.

## Installing an EPS-C Chassis




## CAUTION

Do not use the rack mount brackets to suspend the EPS-C from under a table top or desk, or to attach the EPS-C unit to a wall.


The EPS-C is intended for use only with a Summit X450e-48p or X250e-48p switch. You can install the EPS-C above or below the Summit switch (see [Figure 109](#)).

**Figure 109: EPS-C and Summit Switch**




To rack-mount the EPS-C:

- 1 Place the EPS-C upright on a secure work surface.
- 2 Remove the mounting bracket kit from the packaging.
- 3 Attach the mounting brackets as follows:
  - a Place a rack mount bracket over the mounting holes on one side of the unit.
  - b Insert the provided screws and fully tighten them using a screwdriver (see [Figure 110](#)).

**Figure 110: Attaching the Mounting Bracket**

- c Repeat steps [a](#) and [b](#) for the other side of the EPS-C.
- 4 Slide the EPS-C into a 19-inch rack and secure it using appropriate rack-mount screws.
- 5 Connect the keyed end of the redundant power cord to the EPS-C (see [Figure 111](#)). Verify that the side of the connector marked TOP is facing up.  
The key is a plastic tab on the cable connector housing that fits into the EPS-C to ensure correct alignment of the connector.
- 6 Connect the other end of the redundant power cord to the Summit X450e-48p or X250e-48p switch (see [Figure 111](#)). Be sure that the side of the connector marked TOP is facing up.

**Figure 111: Installing the Redundant Power Cord**

EPS-C\_03A

## Installing an EPS-600LS Power Supply

To install an EPS-600LS unit into an EPS-C:


- 1 If necessary, remove a cover plate from a slot in the EPS-C.
- 2 Slide the EPS-600LS into an empty slot in the EPS-C (see [Figure 112](#)).



### CAUTION


Be sure that empty slots in the EPS-C chassis are always covered by a cover plate when not in use. The EPS-C is shipped with slots 2 and 3 covered and slot 1 open. Extreme Networks recommends that you populate slot 1 with an EPS-600LS unit first, but this is not required. You can install EPS-600LS units into any of the slots in the EPS-C. The installation sequence does not affect the performance of the power supply units, but empty slots must be covered at all times.

**Figure 112: Installing the EPS-600LS Unit in the EPS-C Chassis**



EPS-C\_04A

- 3 Slide the unit completely into the chassis until the front of the EPS-600LS is flush with the surface of the EPS-C (see [Figure 113](#)).
- 4 Tighten the two captive screws on the EPS-600LS unit into the EPS-C (see [Figure 113](#)). This secures the unit in place.

**Figure 113: Securing the EPS-600LS to the EPS-C Chassis**

- 5 Connect an appropriate AC power cord to the AC connector on the EPS-600LS unit (see [Figure 114](#)). Use the cable clip on the EPS-600LS unit to hold the AC power cord in place (see [Figure 114](#)).


**NOTE**

An AC power cord is not provided with the EPS-600LS unit. See [“Selecting Power Supply Cords”](#) on page 170 for information about selecting a power cord.

**CAUTION**

The EPS-600LS unit does not have a switch for turning the unit on and off. Disconnect power to the EPS-600LS unit by removing the plug from the electrical outlet. Make sure that this connection is easily accessible to you.

**Figure 114: Installing the Redundant Power Cord**



EPS-C\_06A

- 6 Connect the other end of the AC power cord to the electrical outlet (see [Figure 114](#)).  
Be sure that the electrical outlet is properly grounded.
- 7 Repeat steps 1 through 6 for each EPS-600LS unit.

## Removing an EPS-600LS Power Module

To manually disconnect an EPS-C or to remove the EPS-600LS modules, the recommended practice is to disconnect the EPS-600LS modules one at a time, pausing two seconds after each EPS-600LS disconnect. This enables a graceful power transition from the external PSUs to the internal PSU.

To remove an EPS-600LS unit:

- 1 Disconnect the AC power by removing the plug from the wall.
- 2 Release the cable clip securing the AC power cord to the EPS-600LS unit.
- 3 Disconnect the AC power cord from the EPS-600LS unit.
- 4 Loosen the captive screws on the EPS-600LS unit securing it to the EPS-C.
- 5 Slide the EPS-600LS unit out of the EPS-C.



## 6 Summit Option Cards

This chapter describes Summit option cards available for use with Summit X350 series, X450 series, X450a series, and X450e series switches. The chapter includes the following sections

- [Overview on page 147](#)
- [Safety Information on page 148](#)
- [Summit XGM-2xn Option Card on page 148](#)
- [Summit XGM2-2xn Option Card on page 149](#)
- [Summit XGM2-2xf Option Card on page 150](#)
- [Summit XGM2-2sf Option Card on page 151](#)
- [Summit XGM2-2bt Option Card on page 151](#)
- [Installing a Summit Port Option Card on page 152](#)



### NOTE

---

*Read the information in this chapter thoroughly before attempting to install or remove a Summit option card.*

## Overview

Five types of Summit port option card are available for the Summit X350, X450, X450a, and X450e series switches:

- Summit XGM-2xn option card: Adds one or two 10-gigabit XENPAK optical transceivers to a Summit X450 series switch.
- Summit XGM2-2xn option card: Adds one or two 10-gigabit XENPAK optical transceivers to a Summit X450a series or X450e series switch.
- Summit XGM2-2xf option card: Adds one or two 10-gigabit XFP modules to a Summit X350 series, X450a series or X450e series switch.
- XGM2-2sf option card: Adds one or two 10-Gigabit SFP+ modules to a Summit X350 series, X450a series, or X450e series switch.
- XGM2-2bt option card: adds one or two fixed 10GBASE-T ports to a Summit X350 series, X450a series, or X450e series switch.

These option cards are installed in an option slot on the rear panel of compatible switches. The option slot is covered by a blank panel if the option card is not installed.

## Safety Information



### CAUTION

*Pluggable optical modules may become very hot after prolonged use. Take care when removing a pluggable optical module from the option card. If the pluggable optical module is too hot to touch, disengage the module and allow it to cool before removing it completely.*

Only trained service personnel should perform service to Extreme Networks switches and their components. Trained service personnel have read all related installation manuals, have the technical training and experience necessary to be aware of the hazards to which they are exposed in performing a task, and are aware of measures to minimize the danger to themselves or other persons.

Before installing a Summit option card into your network:

- Read the latest installation and safety information in this chapter and the section specific to the optic type you are installing.
- See [Appendix A, “Safety Information,”](#) for additional safety information and [Appendix B, “Technical Specifications,”](#) for additional information regarding regulatory compliance certifications.



### WARNING!

*When working with laser optic modules, always take the following precautions to prevent exposure to hazardous radiation:*

- *Never look at the transmit LED/laser through a magnifying device while it is powered on.*
- *Never look directly at a fiber port on the switch or at the ends of a fiber cable when they are powered on.*
- *Invisible laser radiation can occur when the connectors are open. Avoid direct eye exposure to the beam when optic connections are unplugged.*
- *Never alter, modify, or change an optic device in any way other than suggested in this document.*

## Summit XGM-2xn Option Card

The Summit XGM-2xn option card allows you to add up to two 10-gigabit XENPAK modules to the following switches:

- Summit X450-24x switch, running ExtremeXOS 11.2.0 (or later)
- Summit X450-24t switch, running ExtremeXOS 11.2.0 (or later)

The Summit XGM-2xn option card is compatible with the following 10-gigabit XENPAK modules:

- SR XENPAK module, operating in the 850 nm range
- LR XENPAK module, operating in the 1310 nm range
- ER XENPAK module, operating in the 1550 nm range
- ZR XENPAK module, operating in the 1550 nm range
- LX-4 XENPAK module, operating in the 1269-1355 nm range

For more information about these XENPAK modules, refer to the *Extreme Networks Pluggable Interface Modules Installation Guide*.





#### NOTE

The ExtremeXOS software also recognizes standards-based CX-4 XENPAKs; contact your CX-4 module vendor to obtain these.

## Mixing ZR XENPAKs with Other Types

Table 24 lists the supported combinations of XENPAK types using ZR XENPAKs in a Summit X450 series switch. You can either install one ZR XENPAK and leave one slot empty or install one ZR XENPAK and one SR XENPAK; the Summit X450 series switch does not support any other XENPAK combinations when a ZR XENPAK module is installed. You must put the specified modules in the specified slots, as shown in Table 24, for the switch to discover the ZR XENPAK correctly.

**Table 24: Summit X450 ZR XENPAK Combinations**

| Left Slot | Right Slot |
|-----------|------------|
| ZR XENPAK | Empty      |
| ZR XENPAK | SR XENPAK  |

## Summit XGM2-2xn Option Card


The Summit XGM2-2xn option card allows you to add up to two 10-gigabit XENPAK modules to the following switches:

- Summit X450a-24t switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450a-24tDC switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450a-24x switch, running ExtremeXOS 11.6.1 (or later)
- Summit X450a-24xDC switch, running ExtremeXOS 11.6.1 (or later)
- Summit X450a-48t switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450e-24p switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450e-48p switch, running ExtremeXOS 11.6.1 (or later)

The Summit XGM2-2xn option card is compatible with the following 10-gigabit XENPAK modules:

- SR XENPAK module, operating in the 850 nm range
- LR XENPAK module, operating in the 1310 nm range
- ER XENPAK module, operating in the 1550 nm range
- ZR XENPAK module, operating in the 1550 nm range
- LX-4 XENPAK module, operating in the 1269-1355 nm range
- LW XENPAK module, operating in the 1310 nm range

Figure 115 shows the Summit XGM2-2xn option card.

**Figure 115: Summit XGM2-2xn Option Card****NOTE**

Refer to the Extreme Networks Pluggable Interface Modules Installation Guide for more information about XENPAK modules.

Standards-based CX-4 XENPAKs are also recognized by ExtremeXOS; contact your CX-4 module vendor to obtain these.

## Summit XGM2-2xf Option Card

The Summit XGM2-2xf option card allows you to add up to two 10-gigabit XFP modules to the following switches:


- Summit X450a-24t switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450a-24tDC switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450a-24x switch, running ExtremeXOS 11.6.1 (or later)
- Summit X450a-24xDC switch, running ExtremeXOS 11.6.1 (or later)
- Summit X450a-48t switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450e-24p switch, running ExtremeXOS 11.5.0 (or later)
- Summit X450e-48p switch, running ExtremeXOS 11.6.1 (or later)

The Summit XGM2-2xf option card is compatible with the following 10-gigabit XFP modules:

- LR XFP module
- SR XFP module

Figure 116 shows the Summit XGM2-2xf option card.

**Figure 116: Summit XGM2-2xf Option Card**



**NOTE**

Refer to the Extreme Networks Pluggable Interface Modules Installation Guide for more information about XFP modules.

## Summit XGM2-2sf Option Card

The XGM2-2sf option card allows you to add one or two 10-Gigabit SFP+ modules to the following switches:

- Summit X350 series switch, running ExtremeXOS 12.2.1 or later
- Summit X450a series switch, running ExtremeXOS 12.2.1 or later
- Summit X450e series switch, running ExtremeXOS 12.2.1 or later

For current information about compatible SFP+ modules and the minimum required software, refer to the most recent version of the ExtremeXOS release notes.

## Summit XGM2-2bt Option Card

The XGM2-2bt option card allows you to add two fixed 10GBASE-T ports to the following switches:

- Summit X350 series switch, running ExtremeXOS 12.2.1 or later
- Summit X450a series switch, running ExtremeXOS 12.2.1 or later
- Summit X450e series switch, running ExtremeXOS 12.2.1 or later

The 10GBASE-T standard (IEEE 802.3an) allows the use of standard CAT5E, CAT6, or CAT6A cable for connection to the XGM2-2bt ports (see [Table 25](#)).

**Table 25: Cable Distances for the XGM2-2bt Option Card**

| Cable Type | Maximum Distance |
|------------|------------------|
| CAT5E      | 55 meters        |
| CAT6       | 75 meters        |
| CAT6A      | 100 meters       |

## Installing a Summit Port Option Card



### CAUTION

Summit port option cards are not hot-swappable. Disconnect power to the switch before installing or removing a Summit option card. After the Summit port option card is installed in a compatible switch, you can hot-swap pluggable optical modules. Use only optical modules approved by Extreme Networks.

You need the following tools and equipment to install a Summit option card:

- ESD-preventive wrist strap
- # 1 Phillips screwdriver



### CAUTION


Be sure that proper ESD controls are in use before switch maintenance is performed. This includes but is not limited to wrist straps that are grounded to the switch chassis and earth grounds.

All Summit port option cards are installed the same way. The instructions in this section apply to all option cards for the Summit X350, X450a, and X450e series switches.

To install the Summit port option card:


- 1 Disconnect the AC power and any redundant power supply from the Summit switch.
- 2 Attach the ESD-preventive wrist strap to your wrist and connect the metal end to the equipment rack.
- 3 Remove the screws holding the filler panel over the option slot on the back of the switch (Figure 117). Remove the filler panel and set it aside. Save the screws for re-use.

**Figure 117: Option Slot Filler Panel**



- 4 Align the sheet metal edges on the option card with the card guides in the switch housing. Carefully slide the option card into the switch housing until the connectors engage and the card is flush with the back panel of the switch (Figure 118).

**Figure 118: Installing a Summit Port Option Card (XGM-2xn Shown)**



- 5 Using the screws from the cover plate, secure the option card to the back panel of the switch.

For information about installing or replacing the pluggable optical modules in the Summit option card, refer to the *Extreme Networks Pluggable Interface Modules Installation Manual*.



#### NOTE

*If you install only one pluggable optical module in the Summit option card, attach the appropriate cover plate or dust cover over the remaining open optical module slot or cage.*

*Be sure that the switch option slot always has either an installed Summit option card or a faceplate over the opening. An open slot could divert air from the switch and cause overheating.*



## 7

## Maintenance Procedures for Summit X650 Series Switches

This chapter describes how to replace components in a Summit X650 series switch. This chapter includes the following sections:

- [Replacing a Summit X650 AC PSU on page 155](#)
- [Replacing a Summit X650 Fan Module on page 162](#)
- [Replacing a Versatile Interface Module \(VIM\) on page 163](#)

**NOTE**

*Read the information in this chapter thoroughly before attempting to replace one of the listed Summit X650 components.*

### Replacing a Summit X650 AC PSU

In a redundant power configuration, you can replace one Summit X650 AC PSU without powering down the switch.

You need the following tools and materials to replace a Summit X650 AC PSU:


- ESD-preventive wrist strap
- Thermal protective gloves
- AC power cord, if you will not be re-using the cord from the removed power supply

An AC power cord is not included with the Summit X650 AC PSU. You must obtain a power supply cord that meets the requirements listed under [“Selecting Power Supply Cords” on page 170](#).

To replace a Summit X650 AC PSU:

- 1 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate grounding point.
- 2 Disconnect the AC power cord from the wall outlet and from the PSU.
- 3 Push the latching tab to the left as you pull outward on the handle to disengage the PSU internal connectors (see [Figure 119](#)).

**Figure 119: Removing an AC PSU**



- Carefully slide the PSU the rest of the way out of the switch.

**CAUTION**


Power supplies may become very hot during operation. Wear thermal protective gloves when you remove a power supply from an operating switch.

**NOTE**

If you are not installing a replacement PSU, install a cover over the unoccupied power supply bay. Unoccupied bays must always be covered to maintain proper system ventilation and EMI levels.

- Verify that the replacement PSU is right side up, with the latching tab at the right of the unit (see [Figure 120](#)).
- Carefully slide the PSU all the way into the power supply bay (see [Figure 120](#)). Push the PSU in until the latch snaps into place.

**Figure 120: Installing an AC PSU**

**CAUTION**

Do not slam the PSU into the switch.

- Connect the power cord to the PSU and to a grounded AC power outlet.

**WARNING!**

Always be sure that the source outlet is properly grounded before plugging the AC power cord into the AC PSU.



# Replacing a Summit X650 DC Power Supply

In a redundant power configuration, you can replace one Summit X650 DC PSU without powering down the switch.

You need the following tools and materials to replace a Summit X650 DC PSU:

- #1 Phillips screwdriver
- Torque screwdriver and wrench or torque driver with attachments for tightening screws and nuts
- ESD-preventive wrist strap
- Thermal protective gloves (required for removal of a PSU)



## WARNING!


*Be sure to disconnect all power cables before you disconnect the chassis ground wire.*

## Removing the PSU

To remove an installed Summit X650 DC PSU:

- 1 De-energize the DC circuit.
- 2 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate ground point on the rack.
- 3 Disconnect the DC power cables as follows:
  - a Slide the cover off the terminal block.
  - b Loosen the screws that secure the cable terminals to the terminal block.
  - c Slide the wires out from under the captive washers.
- 4 Disconnect the ground wire as follows:
  - a Remove the screw that secures the ground wire to the PSU.
  - b Move the wire away from the PSU.
- 5 Push the latching tab to the left as you pull outward on the handle to disengage the PSU internal connectors (see [Figure 121](#)).

**Figure 121: Removing a DC PSU**



## Installing the Replacement PSU

To install a replacement Summit X650 DC PSU:


- 1 Verify that the PSU is right side up (see [Figure 122](#))
- 2 Carefully slide the PSU all the way into the power supply bay (see [Figure 122](#)). Push the PSU in until the latch snaps into place.



### CAUTION

*Do not slam the PSU into the switch.*

**Figure 122: Installing a Summit X650 DC PSU**




SH\_107

## Connecting the Ground Wire

To connect the ground wire to the Summit X650 DC PSU:

- 1 Verify that the DC circuit is de-energized.
- 2 Identify the grounding point on the front panel of the PSU (see [Figure 123](#)).
- 3 Insert an M3.5 screw (provided) through the ring terminal and into the grounding point on the PSU.
- 4 Tighten the screw to 12.6 inch-pounds.
- 5 Connect the other end of the wire to a known reliable earth ground point at your site.


**Figure 123: Connecting the Ground Wire**



## Connecting the DC Power Cables

To connect the DC power cables to the Summit X650 DC PSU:


- 1 Verify that the DC circuit is de-energized.
- 2 Attach an ESD-preventive wrist strap to your bare wrist and connect the metal end to an appropriate ground point on the rack.
- 3 Slide the cover off the terminal block ([Figure 124](#)).
- 4 Connect the DC power input cables as follows:
  - a On each terminal, loosen the screw enough to allow the spade terminal to slide underneath the captive square washer.
  - b Slide the spade terminal of the **negative** wire (-48 V) under the captive square washer on the **negative** terminal (labeled -48V).
  - c Slide the spade terminal of the **positive** wire (-48 V RTN) under the captive square washer on the **positive** terminal (labeled RTN).

**Figure 124: Connecting the DC Power Cables (Part 1)**

SH\_111

- d Tighten both screws on the terminal block to 11 inch-pounds ([Figure 126](#)).
- 5 Slide the cover into place over the terminal block ([Figure 126](#)).

**Figure 125: Connecting the DC Power Cables (Part 2)**



SH\_112

**6** Energize the DC circuit.

## Replacing a Summit X650 Fan Module

You need the following tools and equipment to replace a Summit X650 series fan module:

- ESD-preventive wrist strap
- 1/2-inch flat-blade screwdriver




### CAUTION

*Be sure to finish the replacement procedure promptly. The switch may overheat if it is left without cooling for an extended period.*

To replace the fan module:


- 1 Completely loosen the captive retaining screws at the lower corners of the fan module ([Figure 126](#)).
- 2 Slide the fan module out of the switch and set it aside.

**Figure 126: Removing a Fan Module**



- 3 Carefully slide the replacement fan module into the switch ([Figure 127](#)).

**Figure 127: Installing a Fan Module**



- 4 Align and fully tighten the captive retaining screws.

# Replacing a Versatile Interface Module (VIM)

You need the following tools and materials to replace a VIM1 module:

- ESD-preventive wrist strap
- #2 Phillips screwdriver




## CAUTION

Summit VIM1 modules are not hot-swappable. Disconnect power to the switch before removing an installed VIM1 module. After a VIM1 module is installed in a compatible switch, you can hot-swap SFP and SFP+ modules. Use only SFP and SFP+ modules approved by Extreme Networks.

To replace a VIM1 module:

- 1 Attach an ESD-preventive wrist strap to your wrist and connect the metal end to an appropriate ground point on the rack.
- 2 Disconnect the switch power.
- 3 Remove the installed VIM1 module ([Figure 128](#)):
  - a Remove the retaining screws at the top corners of the module, and set the screws aside in a safe place.  
Save the retaining screws to secure the new module in the switch.
  - b Rotate the inserter/extractor levers downward to disconnect the internal module connectors.
  - c Carefully slide the module out of the switch and set it on an anti-static surface.


**Figure 128: Removing a VIM1 Module (VIM1-SummitStack Module Shown)**



SH\_092

- 4 Remove the replacement VIM1 module from its anti-static packaging.
- 5 Install the replacement VIM1 module in the switch ([Figure 129](#)):
  - a Make sure the inserter/ejector levers are rotated down.
  - b Carefully slide the module into the switch until the inserter/ejector levers begin to rotate upward.
  - c Simultaneously rotate both levers upward to seat the module internal connectors.
  - d Insert and tighten the retaining screws you removed earlier.

**Figure 129: Installing a VIM1 Module**



SH\_093



---

## 3

## Appendices

---



**WARNING!**

*Read the following safety information thoroughly before installing Extreme Networks products. Failure to follow this safety information can lead to personal injury or damage to the equipment.*

Only trained service personnel should perform service to Extreme Networks switches and their components. Trained service personnel have read all related installation manuals, have the technical training and experience necessary to be aware of the hazards to which they are exposed in performing a task, and are aware of measures to minimize the danger to themselves or other persons.

This appendix includes the following sections:

- [Considerations Before Installing on page 167](#)
- [Installing External Power Supply Units on page 168](#)
- [Maintenance Safety on page 169](#)
- [General Safety Precautions on page 169](#)
- [Cable Routing for LAN Systems on page 169](#)
- [Selecting Power Supply Cords on page 170](#)
- [Battery Replacement and Disposal on page 171](#)
- [Fiber Optic Ports—Optical Safety on page 171](#)

## Considerations Before Installing

Consider the following items before installing equipment.

- The system is designed to operate in a typical environmentally controlled Telco environment. Choose an indoor area that has the following characteristics:
  - Temperature- and humidity-controlled, such that the maximum ambient room temperature shall not exceed 40°C (104°F)
  - Clean and free from airborne materials that can conduct electricity
  - Well ventilated and away from sources of heat including direct sunlight
  - Away from sources of vibration or physical shock
  - Isolated from strong electromagnetic fields produced by electrical devices
  - Secured, enclosed, and restricted-access, ensuring that only trained and qualified service personnel have access to the equipment
- Establish at least 3 inches clearance on all sides for effective ventilation. Do not obstruct the air intake vent on the front, side, or rear ventilation grills. Locate the system away from heat sources.
- Make sure that your equipment is placed in an area that accommodates the power consumption and component heat dissipation specifications.
- Make sure that your power supplies meet the site power or AC power requirements of the all network equipment.

## Installing External Power Supply Units

For the ratings and power requirements of each power supply unit, see [Appendix B, “Technical Specifications”](#) or the data sheet for the power supply at <http://www.extremenetworks.com>.



### WARNING!

*Be sure that the requirements listed in this section are satisfied when installing all Extreme Networks power supplies.*

When you install external power supplies:

- Plug power supplies only into properly grounded electrical outlets to help prevent electrical shock and comply with international safety standards.
- Use only power cords that are certified for use within the country of use. Do not attempt to modify AC power cords.
- Make sure the wall outlet is installed near the equipment and is easily accessible for quick disconnect.
- Make sure the voltage and frequency of your power outlet match the system electrical ratings for the equipment. The building and/or power source must provide overload protection.
- Use a surge suppressor, line conditioner, or uninterruptible power supply to protect the system from momentary increases or decreases in electrical power.
- When inserting a power supply into the bay, do not use excessive force.
- If multiple power supplies are used with a switch, connect each power supply to a different, independent power source. If a single power source fails, it will affect only that power supply to which it is connected. If all the power supplies on a single switch are connected to the same power source, the entire switch is vulnerable to a power failure.



### WARNING!

*Wiring a DC power cord to your facility DC source voltage must be performed by a qualified, licensed electrician.*

*Extreme Networks AC external power supplies do not have switches for turning the unit on and off. Remove the wall plug from the electrical outlet to disconnect the power from an Extreme Networks AC external power supply. Make sure that this connection is easily accessible.*

*Do not connect an EPS-600LS power supply to an electrical outlet when the power supply is not installed in the EPS-C chassis; doing so would expose a hazardous energy and poses a potential shock and fire hazard.*

*Do not put your hand into an open power supply bay when a power supply is not present. Empty power supply bays require a cover plate at all times.*

## Maintenance Safety

When you perform maintenance procedures on Extreme Networks equipment, follow these recommendations:

- Use only original accessories or components approved for use with this system. Failure to follow these instructions may damage the equipment or violate required safety and EMC regulations.
- The chassis cover should only be removed by Extreme Networks personnel. This system contains no customer serviceable components. Repairs to the system must be performed by an Extreme Networks factory service technician.
- In systems that have power-on buttons, the power on button may not turn off all system power. To remove power from the system, you must unplug all power cords from wall outlets. The power cord is the disconnect device to the main power source.
- Disconnect all power cords before working near power supplies, unless otherwise instructed by a maintenance procedure.
- Replace a power cord immediately if it shows any signs of damage.
- When you work with optical devices, power supplies, or other modular accessories, put on an ESD-preventive wrist strap to reduce the risk of electronic damage to the equipment. Connect the other end of the strap to an appropriate grounding point on the equipment rack. Leave the ESD-preventive wrist strap permanently attached to the equipment rack so that it is always available when you need to handle ESD-sensitive components.
- Install all cables in a manner that avoids strain. Use tie wraps or other strain relief devices.

## General Safety Precautions

Follow these guidelines:

- Do not try to lift objects that you think are too heavy for you.
- When you install equipment in a rack, load heavier devices in the lower half of the rack first to avoid making the rack top-heavy.
- For Summit desktop equipment installations, do not place a monitor or other objects on top of the equipment. The chassis cover is not designed to support weight.
- Only use tools and equipment that are in perfect condition. Do not use equipment with visible damage.
- Route cables in a manner that prevents possible damage to the cables and avoids causing accidents, such as tripping.

## Cable Routing for LAN Systems

The Summit family switches meet the requirements for LAN system equipment. LAN systems are designed only for intra-building installations; that is, cable runs between devices must be in the same building as the connected units.

This equipment can be connected between buildings if any one of the following conditions is true:

- Cable runs between buildings are less than 140 feet long.
- Cable runs between buildings are directly buried.
- Cable runs between buildings are in an underground conduit, where a continuous metallic cable shield or a continuous metallic conduit containing the cable is bonded to each building grounding electrode system.



### CAUTION

*Failure to follow these requirements for cable routing conditions may expose the user to electrical shock and expose the unit to errors or damage.*



### WARNING!

*The intra-building ports of the equipment or subassembly are suitable for connection to intrabuilding or unexposed wiring or cabling only. The intra-building port(s) of the equipment or subassembly **MUST NOT** be metalically connected to interfaces that connect to the outside plant (OSP) or its wiring. These interfaces are designed for use as intra-building interfaces only (Type 2 or Type 4 ports as described in GR-1089-CORE, Issue 4) and require isolation from the exposed OSP cabling. The addition of Primary Protectors is not sufficient protection in order to connect these interfaces metalically to OSP wiring.*

## PoE Devices

When connecting power over Ethernet (PoE) devices to a PoE switch, all connections between the PoE device and the switch must remain inside the same building and use a low-voltage power distribution system per IEEE 802.3af.

## Selecting Power Supply Cords

Extreme Networks does not include power input cords in the product box. To purchase a power cord for your product and for your specific country, contact your local Extreme Networks Channel Account Manager or Sales Manager, or purchase a cord from your local supplier.

To locate a Sales Manager or Partner in your region visit:

<http://www.extremenetworks.com/how-to-buy/how-to-buy.aspx>

The following are requirements for power cords used on AC-powered Summit family switches and compatible external power supplies:

- The power cord must be agency-certified for the country of use.
- The power cord must have an IEC320-C13 connector for connection to the switch or external power supply.
- The power cord must have an appropriately rated and approved wall plug applicable to the country of installation.
- For cords up to 6 feet (2 m) long, the wire size must be 18 AWG (.75 mm<sup>2</sup>) minimum; over 6 feet, the minimum wire size is 16 AWG (1.0 mm<sup>2</sup>).



## WARNING!

*When using multiple power supplies, make sure that each power supply is attached to an independent circuit breaker. See the installation instructions for the power supply for proper sizing of circuit breaker.*

*Make sure that the source outlet is properly grounded according to the country's local electrical requirements before plugging the AC supply power cord into a power supply.*

*For specific product input power requirements refer to the data sheet of the product or modular power supply at <http://www.extremenetworks.com> or to [Appendix B](#) of this guide.*



## NOTE

*This equipment is not intended to be directly powered by power distribution systems where phase-phase voltages exceed 240V AC (2P+PE), such as those used in Norway, France, and other countries. For these applications it is recommended that a transformer be used to step down the voltage to < 240V AC from phase-phase, or that you make a connection to a (P+N+PE) power distribution where voltages do not exceed 240V AC.*

*All installations should confirm that the product is reliably grounded according to the country's local electrical codes.*



## NOTE

*Building codes vary worldwide; therefore, Extreme Networks strongly recommends that you consult an electrical contractor to ensure proper equipment grounding and power distribution for your specific installation & country.*

# Battery Replacement and Disposal

Batteries included with Extreme products are encapsulated and must be replaced by qualified Extreme Service personnel only. Contact your Extreme Service personnel for product replacement. Do not attempt to replace the battery. If these instructions are disregarded and replacement of these batteries is attempted, the following guidelines must be followed to avoid danger of explosion:

- Replace with the same or equivalent battery type as recommended by the battery manufacturer.
- Dispose of the battery in accordance with the battery manufacturer's recommendation.

# Fiber Optic Ports—Optical Safety

The following safety warnings apply to all optical devices used in Extreme Networks equipment that are removable or directly installed in an I/O module or chassis system. Such devices include but are not limited to gigabit interface converters (GBICs), small form factor pluggable (SFP) modules (or mini-GBICs), XENPAK transceivers, and XFP laser optic modules.



## WARNING!

*Laser optic modules become very hot after prolonged use. Be careful when removing a laser optic module from the chassis or option card. If the laser optic module is too hot to touch, disengage the laser optic module and allow it to cool before removing it completely.*

**WARNING!**

*When working with laser optic modules, always take the following precautions to avoid exposure to hazardous radiation.*

- *Never look at the transmit LED/laser through a magnifying device while it is powered on.*
- *Never look directly at a fiber port on the switch or at the ends of a fiber cable when they are powered on.*
- *Invisible laser radiation can occur when the connectors are open. Avoid direct eye exposure to the beam when optical connections are unplugged.*
- *Never alter, modify, or change an optical device in any way other than suggested in this document.*

## SFP (Mini-GBIC), XENPAK, and XFP Regulatory Compliance

Extreme Networks pluggable optical modules meet the following regulatory requirements:

- Class 1 Laser Product
- EN60825-1+A2:2001 or later, European laser standard
- FCC 21 CFR Chapter 1, Subchapter J in accordance with FDA & CDRH requirements
- Application of CE Mark in accordance with 89/336/EEC EMC and 73/23/EEC Low Voltage Directives
- UL and/or CSA registered component for North America
- 47 CFR Part 15, Class A when installed into Extreme products

**NOTE**

*Extreme Networks optical modules are tested to work in all supported Extreme Networks switches. We recommend that all customers use Extreme Networks optical modules in their Extreme Networks switches. Extreme Networks assumes no liability for third-party optical modules. Although Extreme Networks does not block third-party optical modules, we cannot ensure that all third-party optical modules operate properly in all Extreme Networks switches. The customer assumes all risks associated with using third-party optical modules in Extreme Networks switches.*



# Sicherheitshinweise



## WARNUNG!

*Vor der Installation der Produkte von Extreme Networks sind die nachfolgenden Sicherheitshinweise aufmerksam zu lesen. Die Nichtbeachtung dieser Sicherheitshinweise kann zu Verletzungen oder Schäden an der Ausrüstung führen.*

Installation, Wartung und Ausbau eines Switch, einer Grundplatte oder einer seiner Komponenten dürfen nur von geschultem und qualifiziertem Servicepersonal durchgeführt werden! Geschulte und qualifizierte Servicetechniker verfügen über die erforderliche technische Ausbildung und Erfahrung, um mögliche Gefahren bei der Durchführung von Servicearbeiten zu erkennen und Maßnahmen zur Minimierung der Gefahr für sich bzw. andere zu treffen.

## Hinweise zur Installation



## WARNUNG!

*Beachten Sie vor der Installation der Ausrüstung folgende Punkte.*

Stellen Sie sicher, dass die nachfolgend aufgeführten Bedingungen erfüllt sind:

- Das System ist für den Einsatz in einer typischen Umgebung gemäß Telco-Vorgaben vorgesehen. Wählen Sie einen Aufstellort mit den folgenden Eigenschaften:
  - Innenbereich mit Temperatur- und Feuchtigkeitsregelung, wobei die maximale Raumtemperatur 40°C (104°F) nicht überschreiten darf.
  - Sauber und frei von elektrisch aufladbaren Teilchen in der Luft.
  - Ausreichende Belüftung und Abstand zu Wärmequellen, einschließlich direktem Sonnenlicht
  - Ausreichender Abstand zu Quellen, die Erschütterungen oder Schläge/Stöße hervorrufen können
  - Isolierung von starken elektromagnetischen Feldern, wie sie durch Elektrogeräte erzeugt werden
  - Sicherer, abgeschlossener Arbeitsbereich mit beschränktem Zugang, sodass nur geschultes und qualifiziertes Servicepersonal Zugriff auf das Gerät hat
  - Die Ausrüstung im unteren Teil des Gestells installieren, um zu vermeiden, dass der obere Teil des Gestells zu schwer wird.
- In für elektrische Stürme anfälligen Gebieten wird empfohlen, das System an einen Spannungsstoßunterdrücker anzuschließen.
- Auf allen Seiten für mindestens 7,5 cm (3") Abstand sorgen, um eine ausreichende Belüftung zu gewährleisten. Die Lufteinlassöffnung an den vorderen, seitlichen und hinteren Entlüftungsgittern nicht blockieren. Das System nicht in der Nähe von Wärmequellen aufstellen.
- Sicherstellen, dass die Ausrüstung in einem Bereich aufgestellt wird, der den Spezifikationen für Leistungsaufnahme und Wärmeabstrahlung der Komponenten entspricht.
- Sicherstellen, dass Ihre Netzteile die Anforderungen an die Strom- oder Wechselstromversorgung vor Ort für alle Netzwerkgeräte erfüllen.
- Bei den Extreme-Produkten handelt es sich um digitale Geräte der Klasse A gemäß Teil 15 der FCC-Richtlinien und anderen internationalen Richtlinien. Der Gerätebetrieb unterliegt den folgenden Voraussetzungen: (1) Das Gerät kann schädliche Interferenzen verursachen, und (2) das Gerät muss

jede empfangene Interferenz zulassen, einschließlich einer Interferenz, die einen unerwünschten Betrieb verursachen kann.

## Installation von Netzteilen



### WARNUNG!

Bei der Installation sämtlicher Netzteile von Extreme Networks muss sichergestellt werden, dass die nachfolgend aufgeführten Anforderungen erfüllt sind. Angaben zu Nennleistung und Leistungsbedarf finden sich in den Installationsanweisungen für das jeweilige Netzteil (Power Supply Unit, PSU).

Folgende Anforderungen müssen unbedingt erfüllt sein:

- Wenn der mit Wechsel- oder Gleichstrom betriebene Switch von Extreme Networks mit einem externen grünen/gelben Erdungskabel ausgestattet ist, dann muss zunächst dieses Erdungskabel zwischen der Grundplatte und einem geeigneten Erdungspunkt angeschlossen werden, bevor andere Verbindungen zum Gerät hergestellt werden; dies gilt auch für den Anschluss an das Wechsel- bzw. Gleichstromnetz. Beim Ausbau des Geräts aus dem Gestell muss das Erdungskabel als letztes getrennt werden.
- Netzteile nur an vorschriftsmäßig geerdete Steckdosen anschließen, um die Gefahr elektrischer Schläge zu vermeiden und die Konformität mit internationalen Sicherheitsnormen zu gewährleisten.
- Nur Stromkabel verwenden, die für den Einsatz in dem jeweiligen Land zugelassen sind. Wechselstromkabel dürfen nicht manipuliert werden.
- Die Wandsteckdose muss in der Nähe der Anlage installiert und leicht zugänglich sein, um eine schnelle Trennung vom Netz zu ermöglichen.
- Spannung und Frequenz der Steckdose müssen den elektrischen Nenndaten des Systems entsprechen. Das Gebäude bzw. die Stromquelle muss mit einem Überlastschutz ausgestattet sein.
- Einen Spannungsstoßunterdrücker, einen Netzfilter oder eine unterbrechungsfreie Stromversorgung verwenden, um das System vor einer vorübergehenden Zu- oder Abnahme der elektrischen Leistung zu schützen.
- Bei laufendem Betrieb austauschbare Netzteile: Das Netzteil vorsichtig, nicht mit Kraft in das Aufnahmefach einsetzen.
- Bei Einsatz mehrerer Netzteile in einem Switch sind die Netzteile jeweils an unterschiedliche, unabhängige Stromquellen anzuschließen. Auf diese Weise ist bei einem Ausfall einer einzelnen Stromquelle nur das daran angeschlossene Netzteil betroffen. Wenn alle Netzteile eines einzelnen Switch an dieselbe Stromquelle angeschlossen sind, ist der gesamte Switch für einen Ausfall der Stromversorgung anfällig.

Leistungsspezifikationen für Netzteile von Extreme Networks finden sich in Anhang B dieses Dokuments oder im Netzteil-Datenblatt unter <http://www.extremenetworks.com>.



### WARNUNG!

Die 325 W DC-Netzteile von Extreme Networks sind nicht mit Ein-/Ausaltern ausgestattet. Vor dem Einstecken des Gleichstromkabels in den Gleichstromanschluss des 325 W DC-Netzteils von Extreme Networks sowie vor dem Abziehen des Kabels sicherstellen, dass der Gleichstromkreis abgeschaltet ist.

Das Gleichstromkabel des 325 W DC-Netzteils muss von einem qualifizierten, zugelassenen Elektriker an die Gleichspannungsquelle in Ihrem Gebäude angeschlossen werden.

Extreme Networks 325 W AC Netzteile haben keinen An- Aus Schalter. Die Stromzufuhr zu einem Extreme Networks

325 W AC Netzteil wird durch das Ziehen des Netzkabels unterbrochen. Es ist sicherzustellen dass diese Verbindung leicht zugänglich ist.

Das Netzteil nicht ausserhalb von dem Gehäuse an das Netz anschliessen da hierdurch gefährliche Spannungen zugänglich werden sowie die Gefahr von einem elektrischem Schlag und/ oder Feuergefahr besteht.

Nicht die Hand in den Netzteilschacht einführen wenn das Netzteil entfernt ist. Leere Netzteilschächte müssen immer mit eine Abdeckplatte bedeckt sein.

## Wartungssicherheit

Folgende Vorsichtsmaßnahmen müssen getroffen werden:

- Nur für den Einsatz mit diesem System zugelassene Originalzubehöerteile bzw. -komponenten verwenden. Die Nichtbeachtung dieser Anweisungen kann zu Schäden an der Ausrüstung oder sogar zu einem Verstoß gegen die erforderlichen Sicherheitsbestimmungen und EMV-Vorschriften führen.
- Die Abdeckung der Grundplatte darf nur durch Personal von Extreme Networks entfernt werden. Das System enthält keine vom Kunden zu wartenden Komponenten. Reparaturen am System sind von einem Werkstechniker von Extreme Networks durchzuführen.
- Der An-/Aus-Schalter des Systems darf nicht die gesamte Stromversorgung zum System unterbrechen. Zur Unterbrechung der Wechselstromversorgung zum System müssen alle Stromkabel aus den Wandsteckdosen gezogen werden. Das Stromkabel dient zur Trennung von der Netzstromversorgung.
- Vor dem Entfernen der Rückwand eines Extreme Networks-Switch muss die gesamte Stromzufuhr unterbrochen werden.
- Vor der Aufnahme von Arbeiten in der Nähe von Stromquellen alle Stromkabel abziehen, sofern nicht im Rahmen eines Wartungsverfahrens anders vorgegeben.
- Beim Umgang mit Modulen, optischen Geräten, Netzteilen oder anderen modularen Zubehörteilen das ESD-Schutzarmband anlegen, um das Risiko einer Beschädigung der Geräte durch elektrostatische Entladungen zu verringern. Das Armband zum Schutz elektrostatisch gefährdeter Bauteile (ESB) grundsätzlich an der Grundplatte befestigt lassen, damit es beim Umgang mit diesen Bauteilen immer zur Hand ist.
- Alle Kabel so verlegen, dass übermäßige Belastungen vermieden werden. Kabelbinder oder Zugentlastungsklemmen verwenden.
- Ein Stromkabel bei Anzeichen von Beschädigungen unverzüglich austauschen.

## Allgemeine Sicherheitsvorkehrungen

Folgende Richtlinien sind unbedingt zu befolgen:

- Keine Gegenstände heben, die möglicherweise zu schwer sind.
- Bei einer Installation in einem Gestell darauf achten, dass schwere Geräte unten im Gestell eingebaut werden, um Gefahren durch Umkippen zu vermeiden.
- Bei Summit Desktop-Switches keinen Monitor oder andere Gegenstände auf die Anlage stellen. Die Abdeckung der Grundplatte ist nicht darauf ausgelegt, Gewicht zu tragen.
- Nur Werkzeuge und Ausrüstung verwenden, die sich in einwandfreiem Zustand befinden. Keine Ausrüstung verwenden, die sichtbare Beschädigungen aufweist.

- Verlegen von Kabeln: Kabel so verlegen, dass keine Schäden entstehen oder Unfälle, z. B. durch Stolpern, verursacht werden können.

## Auswahl der Stromkabel

Je nachdem, welchen Switch Sie erworben haben, werden die Wechselstromnetzteile von Extreme Networks entweder nur mit einem 110-VAC-Kabel oder mit einem 110-VAC-Kabel und einem 208/220-VAC-Kabel geliefert. Die von Extreme Networks gelieferten Stromkabel sind nur für den Einsatz in den Vereinigten Staaten und Kanada ausgelegt und zugelassen. Stromkabel für den Einsatz außerhalb der Vereinigten Staaten und Kanada werden normalerweise von einem Drittanbieter geliefert und müssen die folgenden Anforderungen erfüllen:

- Die Stromkabel müssen offiziell für das Land zugelassen sein, in dem sie verwendet werden sollen.
- Die Stromkabel müssen mit einem für das Einsatzland zugelassenen Wandsteckkontakt mit der geeigneten Nennleistung ausgerüstet sein.
- Die Konfiguration der Steckvorrichtung (die Steckverbindung zur Einheit, nicht zur Wandsteckdose) muss für eine Gerätesteckdose gemäß EN60320/IEC320-C14 ausgeführt sein.
- Die Länge der Stromkabel muss weniger als 5 m (15 Fuß) betragen.
- Die Mindestspezifikation für das flexible Kabel lautet:
  - Nr. 18 AWG (0,823 mm<sup>2</sup>) für Einheiten mit einem Bemessungsstrom von weniger als 10 A, oder
  - Nr. 18 AWG (0,823 mm<sup>2</sup>) bis 2 m Länge für Einheiten mit einem Bemessungsstrom von 10 A oder höher, oder
  - Nr. 16 AWG (1,0 mm<sup>2</sup>) bis 5 m Länge für Einheiten mit einem Bemessungsstrom von 10 A oder höher
- Bei allen Kabeln muss es sich um 3-adrige Kupferleiter vom Typ SVT oder SJT, HAR oder einen äquivalenten Typ handeln.

Verwenden Sie immer ein Wechselstromkabel, das den Vorschriften Ihres Landes entspricht. Erkundigen Sie sich über die örtlichen Vorschriften für Elektroinstallationen und fragen Sie bei den zuständigen Aufsichtsbehörden nach den Anforderungen an Stromkabel. Nähere Angaben zu den Leistungsspezifikationen von Netzteilen finden sich unter <http://www.extremenetworks.com> oder in Anhang B dieses Dokuments.



### **WARNUNG!**

*Vor dem Anschließen des Wechselstromkabels an ein Netzteil muss sichergestellt werden, dass die Steckdose vorschriftsgemäß geerdet ist.*

Für die unten aufgeführten Länder gelten zusätzlich folgende Anforderungen:

- Argentinien: Der Netzstecker muss den argentinischen Standards entsprechen.
- Australien: Versorgungssteckdose, 15 A Minimum, AS 3112 für 110/220-VAC-Netzteile
- Dänemark: Der Netzstecker muss die in Abschnitt 107-2-D1 der Norm DK2-1a oder DK2-5a aufgeführten Bestimmungen erfüllen.

- Japan:
  - Versorgungssteckdose, 15 A, JIS 8303 für 110/220-VAC-Netzteile.
  - Das mit dem Netzteil, dem Switch oder der Grundplatte gelieferte Verbindungskabel ist nur für den Einsatz mit dem spezifischen Produkt von Extreme Networks vorgesehen und darf nicht mit anderen Geräten von Extreme Networks oder anderen Anbietern verwendet werden.
- Nordamerika: Versorgungssteckdose, 15 A, NEMA 5-15 für 110-VAC-Netzteile und NEMA L6-15P für 208/220-VAC-Netzteile
- Schweiz: Der Netzstecker muss der Richtlinie SEV/ASE 1011 entsprechen.
- Großbritannien: Versorgungssteckdose, 15 A, BS 1363 für 110/220-VAC-Netzteile
- International: Versorgungssteckdose, 15 A, CEE 7/7 für 110/220-VAC-Netzteile
- Nur Frankreich und Peru:  
Diese Einheit kann nicht über IT+-Netzteile mit Strom versorgt werden. Wenn Ihre Netzteile vom Typ IT sind, muss dieses Gerät mit 230 V (2P+T) unter Verwendung eines Trenntrafos mit einem Verhältnis von 1:1 versorgt werden. Der zweite Anschlusspunkt muss als neutral definiert und direkt an die Erde angeschlossen werden.

Hinweis: Die Bauvorschriften sind weltweit verschieden; Extreme Networks empfiehlt daher ausdrücklich, einen Elektroinstallateur zu beauftragen, um die sachgemäße Geräteerdung und Stromverteilung für Ihre spezifische Installation sicherzustellen.

## Austauschen und Entsorgen von Batterien

Im Umgang mit Batterien sind folgende Hinweise zu beachten:

- Austauschen der Lithium-Batterie: Die in diesem Gerät enthaltenen Batterien können nicht vom Anwender ausgetauscht werden. Wenden Sie sich für einen Austausch des kompletten Gerätes bitte an die Servicemitarbeiter von Extreme. Sollte der Versuch eines Austausches unternommen werden, sind zur Vermeidung einer Explosionsgefahr folgende Richtlinien zu beachten:
  - a Die Batterie nur durch eine identische oder eine gleichwertige, vom Hersteller empfohlene Batterie ersetzen.
  - b Die Batterie gemäß den Empfehlungen des Herstellers entsorgen.

## Lichtleiteranschlüsse: Optische Sicherheit



### WARNUNG!

Beim Umgang mit Lichtleitermodulen sind folgende Vorsichtsmaßnahmen zu beachten:

- Niemals durch ein Vergrößerungsgerät auf die übertragende LED/den Laser schauen, wenn diese(r) eingeschaltet ist.
- Niemals direkt auf einen Lichtleiteranschluss am Switch oder auf die Enden eines Faserkabels schauen, wenn diese eingeschaltet sind.
- Bei offenen Anschlüssen kann es zu unsichtbarer Laserstrahlung kommen. Direkter Augenkontakt mit dem Strahl ist zu vermeiden.
- Ein optisches Gerät niemals auf andere Weise verändern oder modifizieren als in diesem Dokument angegeben.

## **Einhaltung behördlicher Vorschriften durch SFP (Mini-GBIC), XENPAK und XFP**

- Laserprodukt der Klasse 1
- EN60825-1+A2:2001 oder jünger, Europäische Richtlinie für Lasersysteme
- Anwendung der CE-Kennzeichnung gemäß der Richtlinien 89/336/EWG EMV und 73/23/EWG für Niederspannungsgeräte

## B Technical Specifications

This appendix includes the following specifications for Summit switch series and related components:

- [Summit X150 Series Switches on page 179](#)
- [Summit X250e Series Switches on page 183](#)
- [Summit X350 Series Switches on page 189](#)
- [Summit X450 Series Switches on page 192](#)
- [Summit X450a Series Switches on page 194](#)
- [Summit X450e Series Switches on page 198](#)
- [Summit X650 Series Switches on page 201](#)
- [Summit External Power Supplies on page 207](#)
- [Console Connector Pinouts on page 212](#)



### NOTE

*In this appendix, all references to specific switch model numbers also apply to the equivalent TAA-compliant switch versions.*

## Summit X150 Series Switches

The Summit X150 series includes the following switches:

- Summit X150-24t switch
- Summit X150-24p switch
- Summit X150-48t switch

**Table 26: Summit X150 Series Switch Technical Specifications**

### Physical Dimensions

|                        |                               |
|------------------------|-------------------------------|
| Summit X150-24t switch | Height: 1.73 inches (4.4 cm)  |
| Summit X150-24p switch | Width: 17.35 inches (44.1 cm) |
|                        | Depth: 12.13 inches (30.8 cm) |
| Summit X150-48t switch | Height: 1.73 inches (4.4 cm)  |
|                        | Width: 17.35 inches (44.1 cm) |
|                        | Depth: 15.28 inches (38.8 cm) |

### Weight

|                        |                    |
|------------------------|--------------------|
| Summit X150-24t switch | 12.01 lb (5.46 kg) |
| Summit X150-24p switch | 14.9 lb (6.8 kg)   |
| Summit X150-48t switch | 15.1 lb (6.9 kg)   |

**Table 26: Summit X150 Series Switch Technical Specifications (Continued)****Packaged Dimensions**

|                        |                             |
|------------------------|-----------------------------|
| Summit X150-24t switch | Height: 12.6 inches (32 cm) |
| Summit X150-24p switch | Width: 23.6 inches (60 cm)  |
|                        | Depth: 18.5 inches (47 cm)  |
| Summit X150-48t switch | Height: 12.2 inches (31 cm) |
|                        | Width: 22.8 inches (58 cm)  |
|                        | Depth: 22 inches (56 cm)    |

**Packaged Weight**

|                        |                  |
|------------------------|------------------|
| Summit X150-24t switch | 13.2 lb (6.0 kg) |
| Summit X150-24p switch | 14.9 lb (6.8 kg) |
| Summit X150-48t switch | 15.1 lb (6.9 kg) |

**Summit X150-24t Power**

|                           |  |
|---------------------------|--|
| Operational voltage range | 90 to 264 V ~  |
| Nominal input ratings     | 100 to 240 V ~ , 50/60 Hz, 1.0 A   |
| Input current             | 0.5 A @ 115 V ~ (low-line)<br>0.25 A @ 230 V ~ (high-line)   |
| Line frequency range      | 47 to 63 Hz  |
| Inrush current            | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type    | AC   |
| Power supply input socket | IEC 320 C14  |
| Power cord input plug     | IEC 320 C13  |
| Power cord wall plug      | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge   | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                | 83%  |
| Heat dissipation (BTU)    | 122.8  |
| Heat dissipation (Watts)  | 36   |
| Power consumption (BTU)   | 122.8  |
| Power consumption (Watts) | 36   |

**Summit X150-24p Power**

|                           |  |
|---------------------------|--|
| Operational voltage range | 90 to 264 V ~  |
| Nominal input ratings     | 100 to 240 V ~ , 50/60 Hz, 5.25 A  |
| Input current             | 4.4 A @ 115 V ~ (low-line)<br>2.2 A @ 230 V ~ (high-line)  |
| Line frequency range      | 47 to 63 Hz  |
| Inrush current            | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type    | AC   |
| Power supply input socket | IEC 320 C14  |
| Power cord input plug     | IEC 320 C13  |
| Power cord wall plug      | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge   | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                | 81%  |
| Heat dissipation (BTU)    | 204.7  |
| Heat dissipation (Watts)  | 60   |
| Power consumption (BTU)   | 1706   |



**Table 26: Summit X150 Series Switch Technical Specifications (Continued)**

|                                  |   |
|----------------------------------|---|
| Power consumption (Watts)        | 500   |
| <b>Summit X150-48t Power</b>     |   |
| Operational voltage range        | 90 to 264 V ~   |
| Nominal input ratings            | 100 to 240 V ~ , 50/60 Hz, 1.0 A  |
| Input current                    | 0.6 A @ 115 V ~ (low-line)<br>0.3 A @ 230 V ~ (high-line)   |
| Line frequency range             | 47 to 63 Hz   |
| Inrush current                   | 30 A @ 115 V, 60 A @ 230 V  |
| Power supply cord type           | AC  |
| Power supply input socket        | IEC 320 C14   |
| Power cord input plug            | IEC 320 C13   |
| Power cord wall plug             | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>  |
| Power supply cord gauge          | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet  |
| Efficiency                       | 83%   |
| Heat dissipation (BTU)           | 170.6   |
| Heat dissipation (Watts)         | 50  |
| Power consumption (BTU)          | 170.6   |
| Power consumption (Watts)        | 50  |
| <b>Safety Standards</b>          |   |
| North American Safety of ITE     | UL 60950-1:2003 1st Ed., Listed Device (US)<br>CSA 22.2#60950-1-03 1st Ed.(Canada)<br>Complies with FCC 21CFR 1040.10 (US Laser Safety)<br>CDRH Letter of Approval (US FDA Approval)<br>IEEE 802.3af 6-2003 Environment A for PoE Applications  |
| European Safety of ITE           | EN 60950-1:2001+A11<br>EN 60825-1+A2:2001 (Lasers Safety)<br>TUV-R GS Mark by German Notified Body<br>73/23/EEC Low Voltage Directive   |
| International Safety of ITE      | CB Report & Certificate per IEC 60950-1:2001 Country Deviations<br>AS/NZX 60950-1 (Australia /New Zealand)  |
| <b>EMI/EMC Standards</b>         |   |
| North America EMC for ITE        | FCC CFR 47 part 15 Class A (USA)<br>ICES-003 Class A (Canada)   |
| European EMC standards           | EN 55022:1998 Class A<br>EN 55024:1998 Class A includes IEC 61000-4-2, 3, 4, 5, 6, 8, 11<br>EN 61000-3-2,3 (Harmonics & Flicker)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>89/336/EEC EMC Directive   |
| International EMC certifications | CISPR 22:1997 Class A (International Emissions)<br>CISPR 24:1997 Class A (International Immunity)<br>IEC/EN 61000-4-2 Electrostatic Discharge, 8kV Contact, 15kV Air, Criteria A<br>IEC/EN 61000-4-3 Radiated Immunity 10V/m, Criteria A<br>IEC/EN 61000-4-4 Transient Burst, 1kV, Criteria A<br>IEC/EN 61000-4-5 Surge, 2kV L-L, 2kV L-G, Level 3, Criteria A<br>IEC/EN 61000-4-6 Conducted Immunity, 0.15-80MHz, 10V/m unmod. RMS, Criteria A<br>IEC/EN 61000-4-11 Power Dips & Interruptions, >30%, 25 periods, Criteria C |

**Table 26: Summit X150 Series Switch Technical Specifications (Continued)**

|  |   |
|--|---|
| Country-specific                               | VCCI Class A (Japan Emissions)<br>AS/NZS 3548 ACA (Australia Emissions)<br>CNS 13438:1997 Class A (BSMI-Taiwan)<br>MIC Mark, EMC Approval (Korea)   |
| <b>Telecom Standards</b>                       | ETSI EN 300 386:2001 (EMC Telecommunications)<br>ETSI EN 300 019 (Environmental for Telecommunications)   |
| <b>IEEE 802.3 Media Access Standards</b>       | IEEE 802.3ab 1000BASE-T   |
| <b>Environmental Data</b>                      |   |
| Environmental Standards                        | EN/ETSI 300 019-2-1 v2.1.2 - Class 1.2 Storage<br>EN/ETSI 300 019-2-2 v2.1.2 - Class 2.3 Transportation<br>EN/ETSI 300 019-2-3 v2.1.2 - Class 3.1e Operational<br>EN/ETSI 300 753 (1997-10) - Acoustic Noise<br>ASTM D3580 Random Vibration Unpackaged 1.5G   |
| Operating conditions                           | Temperature range: 0° C to 40° C (32° F to 104° F)<br>Humidity: 95% relative humidity, non-condensing<br>Altitude: 0 to 3,000 meters (9,850 feet)<br>Shock (half sine): 30 m/s <sup>2</sup> (3 g), 11 ms, 60 shocks<br>Random vibration: 3 to 500 MHz @ 1.5g rms  |
| Storage & transportation conditions (packaged) | Temperature: -40° C to 70° C (-40° F to 158° F)<br>Humidity: 60% to 95% relative humidity, non-condensing<br>Packaged shock (half sine): 180 m/s <sup>2</sup> (18 g), 6 ms, 600 shocks<br>Packaged sine vibration: 5 to 62 Hz @ velocity 5 mm/s,<br>62 to 500 Hz @ 0.2 G<br>Packaged random vibration: 5 to 20 Hz @ 1.0 ASD w/-3 dB/oct.<br>from 20 to 200 Hz<br>14 drops minimum on sides & corners @ 42" (<15 kg box) |
| Acoustic noise (in dBA per ISO 7779)           | Summit X150-24t:45 (high fan speed)<br>37 (low fan speed)<br>Summit X150-24p:44 (high fan speed)<br>39 (low fan speed)<br>Summit X150-48t:47 (high fan speed)<br>37 (low fan speed)   |

# Summit X250e Series Switches

The Summit X250e series includes the following switches:

- Summit X250e-24t switch
- Summit X250e-24tDC switch
- Summit X250e-24p switch
- Summit X250e-24x switch
- Summit X250e-24xDC switch
- Summit X250e-48t switch
- Summit X250e-48tDC switch
- Summit X250e-48p switch

**Table 27: Summit X250e Series Switch Technical Specifications**

## Physical Dimensions

|                           |                               |
|---------------------------|-------------------------------|
| Summit X250e-24t switch   | Height: 1.73 inches (4.4 cm)  |
| Summit X250e-24tDC switch | Width: 17.35 inches (44.1 cm) |
| Summit X250e-24p switch   | Depth: 12.13 inches (30.8 cm) |
| Summit X250e-24x switch   |                               |
| Summit X250e-24xDC switch |                               |
| Summit X250e-48t switch   | Height: 1.73 inches (4.4 cm)  |
| Summit X250e-48tDC        | Width: 17.35 inches (44.1 cm) |
| Summit X250e-48p switch   | Depth: 15.28 inches (38.8 cm) |

## Weight

|                           |                    |
|---------------------------|--------------------|
| Summit X250e-24t switch   | 12.01 lb (5.46 kg) |
| Summit X250e-24tDC        | 9.99 lb (4.49 kg)  |
| Summit X250e-24p switch   | 14.9 lb (6.8 kg)   |
| Summit X250e-24x          | 10.21 lb (4.64 kg) |
| Summit X250e-24xDC        | 9.97 lb (4.53 kg)  |
| Summit X250e-48t switch   | 15.1 lb (6.9 kg)   |
| Summit X250e-48tDC switch | 12.14 lb (5.52 kg) |
| Summit X250e-48p switch   | 17.0 lb (7.7 kg)   |

## Packaged Dimensions

|                           |                             |
|---------------------------|-----------------------------|
| Summit X250e-24t switch   | Height: 12.6 inches (32 cm) |
| Summit X250e-24tDC switch | Width: 23.6 inches (60 cm)  |
| Summit X250e-24p switch   | Depth: 18.5 inches (47 cm)  |
| Summit X250e-24x switch   |                             |
| Summit X250e-24xDC switch |                             |
| Summit X250e-48t switch   | Height: 12.2 inches (31 cm) |
| Summit X250e-48tDC switch | Width: 22.8 inches (58 cm)  |
| Summit X250e-48p switch   | Depth: 22 inches (56 cm)    |

## Packaged Weight

|                           |                  |
|---------------------------|------------------|
| Summit X250e-24t switch   | 13.2 lb (6.0 kg) |
| Summit X250e-24x switch   |                  |
| Summit X250e-24tDC switch | 13.1 lb (6.0 kg) |
| Summit X250e-24xDC switch | 13.2 lb (6.0 kg) |

**Table 27: Summit X250e Series Switch Technical Specifications (Continued)**

|                               |  |
|-------------------------------|--|
| Summit X250e-24p switch       | 14.9 lb (6.8 kg)   |
| Summit X250e-48t switch       | 15.1 lb (6.9 kg)   |
| Summit X250e-48tDC switch     | 15.5 lb (7.0 kg)   |
| Summit X250e-48p switch       | 17.0 lb (7.7 kg)   |
| <b>Summit X250e-24t Power</b> |  |
| Operational voltage range     | 90 to 264 V ~  |
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 1.0 A   |
| Input current                 | 0.5 A @ 115 V ~ (low-line)<br>0.25 A @ 230 V ~ (high-line)   |
| Line frequency range          | 47 to 63 Hz  |
| Inrush current                | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type        | AC   |
| Power supply input socket     | IEC 320 C14  |
| Power cord input plug         | IEC 320 C13  |
| Power cord wall plug          | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge       | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                    | 83%  |
| Heat dissipation (Watts)      | 36   |
| Heat dissipation (BTU/hr)     | 122.8  |
| Power consumption (Watts)     | 36   |
| Power consumption (BTU/hr)    | 122.8  |
| <b>Summit X250e-24p Power</b> |  |
| Operational voltage range     | 90 to 264 V ~  |
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 5.25 A  |
| Input current                 | 4.4 A @ 115 V ~ (low-line)<br>2.2 A @ 230 V ~ (high-line)  |
| Line frequency range          | 47 to 63 Hz  |
| Inrush current                | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type        | AC   |
| Power supply input socket     | IEC 320 C14  |
| Power cord input plug         | IEC 320 C13  |
| Power cord wall plug          | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge       | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                    | 81%  |
| Heat dissipation (Watts)      | 60   |
| Heat dissipation (BTU/hrs)    | 204.7  |
| Power consumption (Watts)     | 500  |
| Power consumption (BTU/hrs)   | 1706   |
| <b>Summit X250e-24x Power</b> |  |
| Operational voltage range     | 90 to 264 V ~  |
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 1.0 A   |

**Table 27: Summit X250e Series Switch Technical Specifications (Continued)**

|                            |  |
|----------------------------|--|
| Input current              | 0.6 A @ 115 V ~ (low-line)<br>0.3 A @ 230 V ~ (high-line)  |
| Line frequency range       | 47 to 63 Hz  |
| Inrush current             | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type     | AC   |
| Power supply input socket  | IEC 320 C14  |
| Power cord input plug      | IEC 320 C13  |
| Power cord wall plug       | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.                                       |
| Power supply cord gauge    | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                 | 80%  |
| Heat dissipation (Watts)   | 46   |
| Heat dissipation (BTU/hr)  | 157  |
| Power consumption (Watts)  | 46   |
| Power consumption (BTU/hr) | 157  |

**Summit X250e-24xDC Power & Acoustic Sound**

|                            |   |
|----------------------------|---|
| Operational voltage range  | -40 to -57.6 V <sub>DC</sub>  |
| Nominal input ratings      | -48 V <sub>DC</sub> , 2.0 A   |
| Input current              | 1.25 A @ -40 V <sub>DC</sub> (low-line)<br>0.75 A @ -57.6 V <sub>DC</sub> (high-line) |
| Inrush current             | 20 A at 48 V<br>30 A at 72 V  |
| Power supply cord type     | DC  |
| Power supply input socket  | TYCO 206061-1   |
| Power cord input plug      | TYCO 206060-1   |
| Power cord wall plug       | None provided   |
| Power supply cord gauge    | 14 AWG (2.0 mm <sup>2</sup> )   |
| Efficiency                 | 83%   |
| Heat dissipation (Watts)   | 42  |
| Heat dissipation (BTU/hr)  | 143.3   |
| Power consumption (Watts)  | 42  |
| Power consumption (BTU/hr) | 143.3   |

**Summit X250e-24tDC Power**

|                           |   |
|---------------------------|---|
| Operational voltage range | -40 to -57.6 V <sub>DC</sub>  |
| Nominal input ratings     | -48 V <sub>DC</sub> , 2.0 A   |
| Input current             | 0.5 A @ -40 V <sub>DC</sub> (low-line)<br>0.5 A @ -57.6 V <sub>DC</sub> (high-line) |
| Inrush current            | 20 A at 48 V, 30 A at 72 V  |
| Power supply cord type    | DC  |
| Power supply input socket | TYCO 206061-1   |
| Power cord input plug     | TYCO 206060-1   |
| Power cord wall plug      | None provided   |
| Power supply cord gauge   | 14 AWG (2.0 mm <sup>2</sup> )   |

**Table 27: Summit X250e Series Switch Technical Specifications (Continued)**

|                               |  |
|-------------------------------|--|
| Efficiency                    | 78%  |
| Heat dissipation (Watts)      | 31   |
| Heat dissipation (BTU/hr)     | 105.8  |
| Power consumption (Watts)     | 31   |
| Power consumption (BTU/hr)    | 105.8  |
| <b>Summit X250e-48t Power</b> |  |
| Operational voltage range     | 90 to 264 V ~  |
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 1.0 A   |
| Input current                 | 0.6 A @ 115 V ~ (low-line)<br>0.3 A @ 230 V ~ (high-line)  |
| Line frequency range          | 47 to 63 Hz  |
| Inrush current                | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type        | AC   |
| Power supply input socket     | IEC 320 C14  |
| Power cord input plug         | IEC 320 C13  |
| Power cord wall plug          | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge       | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                    | 83%  |
| Heat dissipation (Watts)      | 50   |
| Heat dissipation (BTU/hr)     | 170.6  |
| Power consumption (Watts)     | 50   |
| Power consumption (BTU/hr)    | 170.6  |
| <b>Summit X250e-48p Power</b> |  |
| Operational voltage range     | 90 to 264 V ~  |
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 5.5 A   |
| Input current                 | 4.5 A @ 115 V ~ (low-line)<br>2.25 A @ 230 V ~ (high-line)   |
| Line frequency range          | 47 to 63 Hz  |
| Inrush current                | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type        | AC   |
| Power supply input socket     | IEC 320 C14  |
| Power cord input plug         | IEC 320 C13  |
| Power cord wall plug          | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge       | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                    | 78%  |
| Heat dissipation (Watts)      | 75   |
| Heat dissipation (BTU/hr)     | 255.9  |
| Power consumption (Watts)     | 525  |
| Power consumption (BTU/hr)    | 1791.4   |

**Summit X250e-48tDC Power**

**Table 27: Summit X250e Series Switch Technical Specifications (Continued)**

|                                  |   |
|----------------------------------|---|
| Operational voltage range        | -40 to -57.6 V <sub>DC</sub>  |
| Nominal input ratings            | -48 V <sub>DC</sub> , 2.0 A   |
| Input current                    | 1.25 A @ -40 V <sub>DC</sub> (low-line)<br>0.75 A @ -57.6 V <sub>DC</sub> (high-line)   |
| Inrush current                   | 20 A @ 48 V, 30 A @ 72 V  |
| Power supply cord type           | DC  |
| Power supply input socket        | TYCO 206061-1   |
| Power cord input plug            | TYCO 206060-1   |
| Power cord wall plug             | None provided   |
| Power supply cord gauge          | 14 AWG (2.0 mm <sup>2</sup> )   |
| Efficiency                       | 78%   |
| Heat dissipation (Watts)         | 47  |
| Heat dissipation (BTU/hr)        | 160.4   |
| Power consumption (Watts)        | 47  |
| Power consumption (BTU/hr)       | 160.4   |
| <b>Safety Standards</b>          |   |
| North American Safety of ITE     | UL 60950-1:2003 1st Ed., Listed Device (US)<br>CSA 22.2#60950-1-03 1st Ed.(Canada)<br>Complies with FCC 21CFR 1040.10 (US Laser Safety)<br>CDRH Letter of Approval (US FDA Approval)<br>IEEE 802.3af 6-2003 Environment A for PoE Applications  |
| European Safety of ITE           | EN 60950-1:2001+A11<br>EN 60825-1+A2:2001 (Lasers Safety)<br>TUV-R GS Mark by German Notified Body<br>73/23/EEC Low Voltage Directive   |
| International Safety of ITE      | CB Report & Certificate per IEC 60950-1:2001 Country Deviations<br>AS/NZS 60950-1 (Australia /New Zealand)  |
| <b>EMI/EMC Standards</b>         |   |
| North America EMC for ITE        | FCC CFR 47 part 15 Class A (USA)<br>ICES-003 Class A (Canada)   |
| European EMC standards           | EN 55022:1998 Class A<br>EN 55024:1998 Class A includes IEC 61000-4-2, 3, 4, 5, 6, 8, 11<br>EN 61000-3-2,3 (Harmonics & Flicker)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>89/336/EEC EMC Directive   |
| International EMC certifications | CISPR 22:1997 Class A (International Emissions)<br>CISPR 24:1997 Class A (International Immunity)<br>IEC/EN 61000-4-2 Electrostatic Discharge, 8kV Contact, 15kV Air, Criteria A<br>IEC/EN 61000-4-3 Radiated Immunity 10V/m, Criteria A<br>IEC/EN 61000-4-4 Transient Burst, 1kV, Criteria A<br>IEC/EN 61000-4-5 Surge, 2kV L-L, 2kV L-G, Level 3, Criteria A<br>IEC/EN 61000-4-6 Conducted Immunity, 0.15-80MHz, 10V/m unmod. RMS, Criteria A<br>IEC/EN 61000-4-11 Power Dips & Interruptions, >30%, 25 periods, Criteria C |
| Country-specific                 | VCCI Class A (Japan Emissions)<br>AS/NZS 3548 ACA (Australia Emissions)<br>CNS 13438:1997 Class A (BSMI-Taiwan)<br>MIC Mark, EMC Approval (North Korea)   |

**Table 27: Summit X250e Series Switch Technical Specifications (Continued)**

|  |  |
|--|--|
| <b>Telecom Standards</b>                       | ETSI EN 300 386:2001 (EMC Telecommunications)<br>ETSI EN 300 019 (Environmental for Telecommunications)  |
| <b>IEEE 802.3 Media Access Standards</b>       | IEEE 802.3ab 1000BASE-T  |
| <b>Environmental Data</b>                      |  |
| Environmental Standards                        | EN/ETSI 300 019-2-1 v2.1.2 - Class 1.2 Storage<br>EN/ETSI 300 019-2-2 v2.1.2 - Class 2.3 Transportation<br>EN/ETSI 300 019-2-3 v2.1.2 - Class 3.1e Operational<br>EN/ETSI 300 753 (1997-10) - Acoustic Noise<br>ASTM D3580 Random Vibration Unpackaged 1.5G  |
| Operating conditions                           | Temperature range: 0° C to 40° C (32° F to 104° F)<br>Humidity: 95% relative humidity, non-condensing<br>Altitude: 0 to 3,000 meters (9,850 feet)<br>Shock (half sine): 30 m/s <sup>2</sup> (3 g), 11 ms, 60 shocks<br>Random vibration: 3 to 500 Hz @ 1.5g rms  |
| Storage & transportation conditions (packaged) | Storage temperature: -40° C to 85° C (-40° F to 185° F)<br>Storage and transportation humidity: 60% to 95% relative humidity, non-condensing<br>Packaged shock (half sine): 180 m/s <sup>2</sup> (18 g), 6 ms, 600 shocks<br>Packaged sine vibration: 5 to 62 Hz @ velocity 5 mm/s, 62 to 500 Hz @ 0.2 G<br>Packaged random vibration: 5 to 20 Hz @ 1.0 ASD w/-3 dB/oct. from 20 to 200 Hz<br>14 drops minimum on sides & corners @ 42" (<15 kg box)   |
| Acoustic noise (in dBA per ISO 7779)           | Summit X250e-24t:45 (high fan speed)<br>37 (low fan speed)<br>Summit X250e-24p:44 (high fan speed)<br>39 (low fan speed)<br>Summit X250e-24x:42 (high fan speed)<br>35 (low fan speed)<br>Summit X250e-24xDC:45 (high fan speed)<br>37 (low fan speed)<br>Summit X250e-24tDC:45 (high fan speed)<br>37 (low fan speed)<br>Summit X250e-48t:47 (high fan speed)<br>37 (low fan speed)<br>Summit X250e-48p:46 (high fan speed)<br>39 (low fan speed)<br>Summit X250e-48tDC:47 (high fan speed)<br>37 (low fan speed) |



# Summit X350 Series Switches

The Summit X350 series includes the following switches:

- Summit X350-24t
- Summit X350-48t

**Table 28: Summit X350 Series Switch Technical Specifications**

## Physical Dimensions

|                        |   |
|------------------------|---|
| Summit X350-24t switch | Height: 1.73 inches (4.4 cm)<br>Width: 17.35 inches (44.1 cm)<br>Depth: 15.3 inches (38.9cm)  |
| Summit X350-48t switch | Height: 1.73 inches (4.4 cm)<br>Width: 17.35 inches (44.1 cm)<br>Depth: 17.0 inches (43.2 cm) |

## Weight

|                        |                    |
|------------------------|--------------------|
| Summit X350-24t switch | 13.75 lb (6.24 kg) |
| Summit X350-48t switch | 15.75 lb (7.14 kg) |

## Packaged Dimensions

|                        |   |
|------------------------|---|
| Summit X350-24t switch | Height: 5.9 inches (15 cm)                              |
| Summit X350-48t switch | Width: 22.4 inches (57cm)<br>Depth: 21.7 inches (55 cm) |

## Packaged Weight

|                        |                  |
|------------------------|------------------|
| Summit X350-24t switch | 18.7 lb (8.5 kg) |
| Summit X350-48t switch | 20.4 lb (9.3kg)  |

## Summit X350-24t Power

|                           |  |
|---------------------------|--|
| Operational voltage range | 90 to 264 V ~  |
| Nominal input ratings     | 100 to 240 V ~ , 50/60 Hz, 1.0 A   |
| Input current             | 0.75 A @ 115 V ~ (low-line)<br>0.4A @ 230 V ~ (high-line)  |
| Line frequency range      | 47 to 63 Hz  |
| Inrush current            | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type    | AC   |
| Power supply input socket | IEC 320 C14  |
| Power cord input plug     | IEC 320 C13  |
| Power cord wall plug      | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.   |
| Power supply cord gauge   | 18 AWG (0.75 mm <sup>2</sup> ) (up to 6 feet or 2 meters)<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                | 77%  |
| Heat dissipation (BTU)    | 255.9  |
| Heat dissipation (Watts)  | 75   |
| Power consumption (BTU)   | 255.9  |
| Power consumption (Watts) | 75   |

## Summit X350-48t Power

|                           |                                  |
|---------------------------|----------------------------------|
| Operational voltage range | 90 to 264 V ~                    |
| Nominal input ratings     | 100 to 240 V ~ , 50/60 Hz, 1.0 A |

**Table 28: Summit X350 Series Switch Technical Specifications (Continued)**

|                                  |   |
|----------------------------------|---|
| Input current                    | 1.45 A @ 115 V ~ (low-line)<br>0.65 A @ 230 V ~ (high-line)   |
| Line frequency range             | 47 to 63 Hz   |
| Inrush current                   | 30 A @ 115 V, 60 A @ 230 V  |
| Power supply cord type           | AC  |
| Power supply input socket        | IEC 320 C14   |
| Power cord input plug            | IEC 320 C13   |
| Power cord wall plug             | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.  |
| Power supply cord gauge          | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet  |
| Efficiency                       | 81%   |
| Heat dissipation (BTU)           | 392.4   |
| Heat dissipation (Watts)         | 115   |
| Power consumption (BTU)          | 170.6   |
| Power consumption (Watts)        | 392.4   |
| <b>Safety Standards</b>          |   |
| North American Safety of ITE     | UL 60950-1:2003 1st Ed., Listed Device (US)<br>CSA 22.2#60950-1-03 1st Ed.(Canada)<br>Complies with FCC 21CFR 1040.10 (US Laser Safety)<br>CDRH Letter of Approval (US FDA Approval)<br>IEEE 802.3af 6-2003 Environment A for PoE Applications  |
| European Safety of ITE           | EN 60950-1:2001+A11<br>EN 60825-1+A2:2001 (Lasers Safety)<br>TUV-R GS Mark by German Notified Body<br>73/23/EEC Low Voltage Directive   |
| International Safety of ITE      | CB Report & Certificate per IEC 60950-1:2001 Country Deviations<br>AS/NZS 60950-1 (Australia /New Zealand)  |
| <b>EMI/EMC Standards</b>         |   |
| North America EMC for ITE        | FCC CFR 47 part 15 Class A (USA)<br>ICES-003 Class A (Canada)   |
| European EMC standards           | EN 55022:1998 Class A<br>EN 55024:1998 Class A includes IEC 61000-4-2, 3, 4, 5, 6, 8, 11<br>EN 61000-3-2,3 (Harmonics & Flicker)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>89/336/EEC EMC Directive   |
| International EMC certifications | CISPR 22:1997 Class A (International Emissions)<br>CISPR 24:1997 Class A (International Immunity)<br>IEC/EN 61000-4-2 Electrostatic Discharge, 8kV Contact, 15kV Air, Criteria A<br>IEC/EN 61000-4-3 Radiated Immunity 10V/m, Criteria A<br>IEC/EN 61000-4-4 Transient Burst, 1kV, Criteria A<br>IEC/EN 61000-4-5 Surge, 2kV L-L, 2kV L-G, Level 3, Criteria A<br>IEC/EN 61000-4-6 Conducted Immunity, 0.15-80MHz, 10V/m unmod. RMS, Criteria A<br>IEC/EN 61000-4-11 Power Dips & Interruptions, >30%, 25 periods, Criteria C |
| Country-specific                 | VCCI Class A (Japan Emissions)<br>AS/NZS 3548 ACA (Australia Emissions)<br>CNS 13438:1997 Class A (BSMI-Taiwan)<br>MIC Mark, EMC Approval (Korea)   |
| <b>Telecom Standards</b>         |   |
|                                  | ETSI EN 300 386:2001 (EMC Telecommunications)<br>ETSI EN 300 019 (Environmental for Telecommunications)   |

**Table 28: Summit X350 Series Switch Technical Specifications (Continued)**

|  |  |
|--|--|
| <b>IEEE 802.3 Media Access Standards</b>       | IEEE 802.3ab 1000BASE-T  |
| <b>Environmental Data</b>                      |  |
| Environmental Standards                        | EN/ETSI 300 019-2-1 v2.1.2 - Class 1.2 Storage<br>EN/ETSI 300 019-2-2 v2.1.2 - Class 2.3 Transportation<br>EN/ETSI 300 019-2-3 v2.1.2 - Class 3.1e Operational<br>EN/ETSI 300 753 (1997-10) - Acoustic Noise<br>ASTM D3580 Random Vibration Unpackaged 1.5G  |
| Operating conditions                           | Temperature range: 0° C to 40° C (32° F to 104° F)<br>Humidity: 95% relative humidity, non-condensing<br>Altitude: 0 to 3,000 meters (9,850 feet)<br>Shock (half sine): 30 m/s <sup>2</sup> (3 g), 11 ms, 60 shocks<br>Random vibration: 3 to 500 MHz @ 1.5g rms   |
| Storage & transportation conditions (packaged) | Storage temperature: -40° C to 70° C (-40° F to 158° F)<br>Storage and transportation humidity: 60% to 95% relative humidity, non-condensing<br>Packaged shock (half sine): 180 m/s <sup>2</sup> (18 g), 6 ms, 600 shocks<br>Packaged sine vibration: 5 to 62 Hz @ velocity 5 mm/s, 62 to 500 Hz @ 0.2 G<br>Packaged random vibration: 5 to 20 Hz @ 1.0 ASD w/-3 dB/oct. from 20 to 200 Hz<br>14 drops minimum on sides & corners @ 42" (<15 kg box) |
| Acoustic noise (in dBA per ISO 7779)           | Summit X150-24t:45 (high fan speed)<br>37 (low fan speed)<br>Summit X150-24p:44 (high fan speed)<br>39 (low fan speed)<br>Summit X150-48t:47 (high fan speed)<br>37 (low fan speed)  |

## Summit X450 Series Switches

The Summit X450 series includes the following switches:

- Summit X450-24t switch
- Summit X450-24x switch

**Table 29: Summit X450 Series Switch Technical Specifications**

### Physical Dimensions

|                        |                               |
|------------------------|-------------------------------|
| Summit X450-24t switch | Height: 1.73 inches (4.4 cm)  |
| Summit X450-24x switch | Width: 17.35 inches (44.1 cm) |
|                        | Depth: 16.38 inches (41.6 cm) |

### Weight

|                        |                   |
|------------------------|-------------------|
| Summit X450-24t switch | 14 lb (6.35 kg)   |
| Summit X450-24x switch | 13.8 lb (6.26 kg) |

### Power

|                                |  |
|--------------------------------|--|
| Summit switch                  | Auto-ranging 100 V to 240 V AC, 50/60 Hz                             |
| Min voltage/associated current | 1.5 A at 100 V   |
| Max voltage/associated current | 1 A at 240 V AC  |
| Line frequency                 | 50 to 60 Hz  |
| Heat dissipation, Watts/BTU    | 160 W/546 BTU/hr   |
| Power supply cord selection    | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170. |

### Safety Standards

|                              |   |
|------------------------------|---|
| North American Safety of ITE | UL 60950-1:2003 1st Ed., Listed Device (US)<br>CSA 22.2#60950-1-03 1st Ed.(Canada)<br>Complies with FCC 21CFR 1040.10 (US Laser Safety)<br>CDRH Letter of Approval (US FDA Approval)<br>NOM/NYCE (Mexico)<br>IEEE 802.3af 6-2003 Environment A for PoE Applications |
| European Safety of ITE       | EN 60950-1:2001+A11<br>EN 60825-1+A2:2001 (Lasers Safety)<br>TUV-R GS Mark by German Notified Body<br>73/23/EEC Low Voltage Directive   |
| International Safety of ITE  | CB Report & Certificate per IEC 60950-1:2001 Country Deviations<br>AS/NZX 60950-1 (Australia /New Zealand)  |

### EMI/EMC Standards

|                                  |  |
|----------------------------------|--|
| North America EMC for ITE        | FCC CFR 47 part 15 Class A (USA)<br>ICES-003 Class A (Canada)  |
| European EMC standards           | EN 55022:1998 Class A<br>EN 55024:1998 Class A includes IEC 61000-4-2, 3, 4, 5, 6, 8, 11<br>EN 61000-3-2,3 (Harmonics & Flicker)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>89/336/EEC EMC Directive  |
| International EMC certifications | CISPR 22:1997 Class A (International Emissions)<br>CISPR 24:1997 Class A (International Immunity)<br>IEC/EN 61000-4-2 Electrostatic Discharge, 8kV Contact, 15kV Air, Criteria A<br>IEC/EN 61000-4-3 Radiated Immunity 10V/m, Criteria A<br>IEC/EN 61000-4-4 Transient Burst, 1kV, Criteria A<br>IEC/EN 61000-4-5 Surge, 2kV, 4kV, Criteria A<br>IEC/EN 61000-4-6 Conducted Immunity, 0.15-80MHz, 10V/m unmod. RMS, Criteria A<br>IEC/EN 61000-4-11 Power Dips & Interruptions, >30%, 25 periods, Criteria C |

**Table 29: Summit X450 Series Switch Technical Specifications (Continued)**

|  |  |
|--|--|
| Country-specific   | VCCI Class A (Japan Emissions)<br>AS/NZS 3548 ACA (Australia Emissions)<br>CNS 13438:1997 Class A (BSMI-Taiwan)<br>MIC Mark, EMC Approval (North Korea)  |
| <b>Telecom Standards</b>                                   | ETSI EN 300 386:2001 (EMC Telecommunications)<br>ETSI EN 300 019 (Environmental for Telecommunications)  |
| <b>Environmental Data</b>                                  |  |
| Environmental standards                                    | EN/ETSI 300 019-2-1 v2.1.2 - Class 1.2 Storage<br>EN/ETSI 300 019-2-2 v2.1.2 - Class 2.3 Transportation<br>EN/ETSI 300 019-2-3 v2.1.2 - Class 3.1e Operational<br>EN/ETSI 300 753 (1997-10) - Acoustic Noise<br>ASTM D3580 Random Vibration Unpackaged 1.5G  |
| Operating conditions                                       | Temperature range 0 °C to 40 °C (32 °F to 104 °F)<br>Humidity: 10% to 95% relative humidity, non-condensing<br>Shock (half sine): 30 m/s <sup>2</sup> (3g), 11ms, 18 shocks<br>Random vibration: 3 to 500 Hz @ 1.5 g rms   |
| Storage & transportation conditions (packaged)             | Transportation temperature: -40° C to 70° C (-40° F to 158° F)<br>Storage and transportation humidity: 10% to 95% relative humidity, non-condensing<br>Packaged shock (half sine): 100 m/s <sup>2</sup> (6 g), 6 ms, 600 shocks<br>Packaged random vibration: 5 to 200 Hz @ 1.0 ASD (1m <sup>2</sup> /s <sup>2</sup> ), w/-3 dB/octave<br>14 drops minimum on sides & corners @ 36" (<15 kg box) |
| <b>Acoustic Sound</b> (Summit X450-24t and SummitX450-24x) |  |
| Sound power in accordance with EN 300 753 (10-1997)        | Sound power: 61 dBA per ISO 7779<br>Declared sound power: 6.3 belsA per ISO 7779 & ISO 9296  |
| Sound pressure in accordance with NEBS GR-63 Issue 2       | Bystander sound pressure: 49 dBA rear @ 0.6m   |

## Summit X450a Series Switches

The Summit X450a series includes the following switches:

- Summit X450a-24t switch
- Summit X450a-24tDC switch
- Summit X450a-24x switch
- Summit X450a-24xDC switch
- Summit X450a-48t switch

**Table 30: Summit X450a Series Switch Technical Specifications**

### Physical Dimensions

|                           |                               |
|---------------------------|-------------------------------|
| Summit X450a-24t switch   | Height: 1.73 inches (4.4 cm)  |
| Summit X450a-24tDC switch | Width: 17.35 inches (44.1 cm) |
| Summit X450a-24x switch   | Depth: 15.30 inches (38.9 cm) |
| Summit X450a-24xDC switch |                               |
| Summit X450a-48t switch   | Height: 1.73 inches (4.4 cm)  |
| Summit X450a-48tDC switch | Width: 17.35 inches (44.1 cm) |
|                           | Depth: 17 inches (43.2 cm)    |

### Weight

|                           |                    |
|---------------------------|--------------------|
| Summit X450a-24t switch   | 13.75 lb (6.24 kg) |
| Summit X450a-24tDC switch | 12.25 lb (5.57 kg) |
| Summit X450a-24x switch   | 13 lb (5.9 kg)     |
| Summit X450a-24xDC switch | 12.50 lb (5.67 kg) |
| Summit X450a-48t switch   | 15.75 lb (7.14 kg) |
| Summit X450a-48tDC switch | 14.25 lb (6.50 kg) |

### Packaged Dimensions

|                           |                            |
|---------------------------|----------------------------|
| Summit X450a-24t switch   | Height: 5.9 inches (15 cm) |
| Summit X450a-24tDC switch | Width: 22.4 inches (57 cm) |
| Summit X450a-24x switch   | Depth: 21.7 inches (55 cm) |
| Summit X450a-24xDC switch |                            |
| Summit X450a-48t switch   |                            |
| Summit X450a-48tDC switch |                            |

### Packaged Weight

|                           |                   |
|---------------------------|-------------------|
| Summit X450a-24t switch   | 18.7 lb (8.5 kg)  |
| Summit X450a-24tDC switch | 16.8 lb (7.7 kg)  |
| Summit X450a-24x switch   | 18.7 lb (8.5 kg)  |
| Summit X450a-24xDC switch | 16.8 lb (7.7 kg)  |
| Summit X450a-48t switch   | 20.4 lb (9.3 kg)  |
| Summit X450a-48tDC switch | 17.75 lb (8.0 kg) |

### Summit X450a-24t Power

|                           |   |
|---------------------------|---|
| Operational voltage range | 90 to 264 V ~   |
| Nominal input ratings     | 100 to 240 V ~ , 50/60 Hz, 1.0 A                          |
| Input current             | 1.0 A @ 115 V ~ (low-line)<br>0.5 A @ 230 V ~ (high-line) |
| Line frequency range      | 47 to 63 Hz   |
| Inrush current            | 30 A @ 115 V, 60 A @ 230 V                                |
| Power supply cord type    | AC  |

**Table 30: Summit X450a Series Switch Technical Specifications (Continued)**

|  |  |
|--|--|
| Power supply input socket                          | IEC 320 C14  |
| Power cord input plug                              | IEC 320 C13  |
| Power cord wall plug                               | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge                            | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Heat dissipation, Watts/BTU                        | 100 W/341.2 BTU/hr   |
| Power consumption, Watts/BTU                       | 100 W/341.2 BTU/hr   |
| <b>Summit X450a-24tDC Power</b>                    |  |
| Operational voltage range                          | –36 to –72 V <sub>DC</sub>   |
| Nominal input ratings                              | –48 V <sub>DC</sub> , 2.0 A  |
| Nominal input current                              | 2.0 A @ –36 V <sub>DC</sub> (low-line)<br>1.0 A @ –72 V <sub>DC</sub> (high-line)                          |
| Inrush current                                     | 20 A @ 48 V, 30 A @ 72 V   |
| Power supply cord type                             | DC   |
| Power supply input socket                          | TYCO PN 206061-1   |
| Power cord input plug                              | TYCO PN 206060-1   |
| Power cord wall plug                               | None provided  |
| Power supply cord gauge                            | 14 AWG (2.0 mm <sup>2</sup> )  |
| Heat dissipation, Watts, BTU                       | 75 W, 368.5 BTU/hr   |
| Power consumption, Watts, BTU                      | 75 W, 368.5 BTU/hr   |
| <b>Summit X450a-48t Power &amp; Acoustic Sound</b> |  |
| Operational voltage range                          | 90 to 264 V <sub>AC</sub>  |
| Nominal input ratings                              | 100 to 240 V <sub>AC</sub> , 50/60 Hz, 1.5 A   |
| Nominal input current                              | 1.45 A @ 115 V <sub>AC</sub> (low-line)<br>0.65 A @ 230 V <sub>AC</sub> (high-line)                        |
| Line frequency range                               | 47 to 63 Hz  |
| Inrush current                                     | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type                             | AC   |
| Power supply input socket                          | IEC 320 C14  |
| Power cord input plug                              | IEC 320 C13  |
| Power cord wall plug                               | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge                            | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Heat dissipation, Watts, BTU                       | 160 W, 511.8 BTU/hr  |
| Power consumption, Watts, BTU                      | 160 W, 511.8 BTU/hr  |
| <b>Summit X450a-48tDC Power</b>                    |  |
| Operational voltage range                          | –36 to –72 V <sub>DC</sub>   |
| Nominal input voltage                              | –48 V <sub>DC</sub> , 4.5 A  |
| Input current                                      | 4.0 A @ –36 V DC (low-line)<br>2.0 A @ –72 V DC (high-line)  |
| Inrush current                                     | 29 A @ 48 V, 30 A @ 72 V   |
| Input wire harness                                 | Extreme part number 250088   |
| Power supply cord gauge                            | 14 AWG (2.0 mm <sup>2</sup> )  |
| Power cord input plug                              | TYCO PN 206060-1   |

**Table 30: Summit X450a Series Switch Technical Specifications (Continued)**

|  |  |
|--|--|
| Power supply input socket                          | TYCO PN 206061-1   |
| <b>Summit X450a-24x Power &amp; Acoustic Sound</b> |  |
| Operational voltage range                          | 90 to 264 V ~  |
| Nominal input ratings                              | 100 to 240 V ~ , 50/60 Hz, 1.0 A   |
| Nominal input current                              | 1.0 A @ 115 V ~ (low-line)<br>0.5 A @ 230 V ~ (high-line)  |
| Line frequency range                               | 47 to 63 Hz  |
| Inrush current                                     | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type                             | AC   |
| Power supply input socket                          | IEC 320 C14  |
| Power cord input plug                              | IEC 320 C13  |
| Power cord wall plug                               | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>   |
| Power supply cord gauge                            | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet   |
| Heat dissipation, Watts, BTU                       | 98 W, 334.4 BTU/hr   |
| Power consumption, Watts, BTU                      | 98 W, 334.4 BTU/hr   |
| <b>Summit X450a-24xDC Power</b>                    |  |
| Operational voltage range                          | -36 to -72 V ==  |
| Nominal input ratings                              | -48 V == , 2.5 A   |
| Input current                                      | 2.5 A @ -36 V == (low-line)<br>1.25 A @ -72 V == (high-line)   |
| Power supply cord type                             | DC   |
| Power supply input socket                          | TYCO PN 206061-1   |
| Power cord input plug                              | TYCO PN 206060-1   |
| Power cord wall plug                               | None provided  |
| Power supply cord gauge                            | 14 AWG (2.0 mm <sup>2</sup> )  |
| Heat dissipation, Watts, BTU                       | 98 W, 334.4 BTU/hr   |
| Power consumption, Watts, BTU                      | 98 W, 334.4 BTU/hr   |
| <b>Safety Standards</b>                            |  |
| North American Safety of ITE                       | UL 60950-1:2003 1st Ed., Listed Device (US)<br>CSA 22.2#60950-1-03 1st Ed.(Canada)<br>Complies with FCC 21CFR 1040.10 (US Laser Safety)<br>CDRH Letter of Approval (US FDA Approval)<br>IEEE 802.3af 6-2003 Environment A for PoE Applications |
| European Safety of ITE                             | EN 60950-1:2001+A11<br>EN 60825-1+A2:2001 (Lasers Safety)<br>TUV-R GS Mark by German Notified Body<br>73/23/EEC Low Voltage Directive  |
| International Safety of ITE                        | CB Report & Certificate per IEC 60950-1:2001 Country Deviations<br>AS/NZS 60950-1 (Australia /New Zealand)   |
| <b>EMI/EMC Standards</b>                           |  |
| North America EMC for ITE                          | FCC CFR 47 part 15 Class A (USA)<br>ICES-003 Class A (Canada)  |
| European EMC standards                             | EN 55022:1998 Class A<br>EN 55024:1998 Class A includes IEC 61000-4-2, 3, 4, 5, 6, 8, 11<br>EN 61000-3-2,3 (Harmonics & Flicker)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>89/336/EEC EMC Directive                                  |



**Table 30: Summit X450a Series Switch Technical Specifications (Continued)**

|  |   |
|--|---|
| International EMC certifications   | CISPR 22:1997 Class A (International Emissions)<br>CISPR 24:1997 Class A (International Immunity)<br>IEC/EN 61000-4-2 Electrostatic Discharge, 8kV Contact, 15kV Air, Criteria A<br>IEC/EN 61000-4-3 Radiated Immunity 10V/m, Criteria A<br>IEC/EN 61000-4-4 Transient Burst, 1kV, Criteria A<br>IEC/EN 61000-4-5 Surge, 2kV L-L, 2kV L-G, Level 3, Criteria A<br>IEC/EN 61000-4-6 Conducted Immunity, 0.15-80MHz, 10V/m unmod. RMS, Criteria A<br>IEC/EN 61000-4-11 Power Dips & Interruptions, >30%, 25 periods, Criteria C |
| Country-specific   | VCCI Class A (Japan Emissions)<br>AS/NZS 3548 ACA (Australia Emissions)<br>CNS 13438:1997 Class A (BSMI-Taiwan)<br>MIC Mark, EMC Approval (North Korea)   |
| <b>Telecom Standards</b>   | ETSI EN 300 386:2001 (EMC Telecommunications)<br>ETSI EN 300 019 (Environmental for Telecommunications)   |
| <b>IEEE 802.3 Media Access Standards</b>   | IEEE 802.3ab 1000BASE-T   |
| <b>Environmental Data</b>  |   |
| Environmental standards  | EN/ETSI 300 019-2-1 v2.1.2 - Class 1.2 Storage<br>EN/ETSI 300 019-2-2 v2.1.2 - Class 2.3 Transportation<br>EN/ETSI 300 019-2-3 v2.1.2 - Class 3.1e Operational<br>EN/ETSI 300 753 (1997-10) - Acoustic Noise<br>ASTM D3580 Random Vibration Unpackaged 1.5G   |
| Operating conditions   | Temperature range: 0° C to 40° C (32° F to 104° F)<br>Humidity: 10% to 93% relative humidity, non-condensing<br>Altitude: 0 to 3,000 meters (9,850 feet)<br>Shock (half sine): 30 m/s <sup>2</sup> (3 g), 11 ms, 60 shocks<br>Random vibration: 3 to 500 Hz @ 1.5 g rms   |
| Storage & transportation conditions (packaged)   | Transportation temperature: -40° C to 70° C (-40° F to 158° F)<br>Storage and transportation humidity: 60% to 95% relative humidity, non-condensing<br>Packaged shock (half sine): 180 m/s <sup>2</sup> (18 g), 6 ms, 600 shocks<br>Packaged sine vibration: 5 to 62 Hz @ velocity 5 mm/s, 62 to 500 Hz @ 0.2 G<br>Packaged random vibration: 5 to 20 Hz @ 1.0 ASD w/-3 dB/oct. from 20 to 200 Hz<br>14 drops minimum on sides & corners @ 42" (<15 kg box)   |
| Sound power in accordance with EN 300 753 (10-1997)<br>Summit X450a-24t and X450a-48t            | Sound power: 62 dBA per ISO 7779<br>Declared sound power: 6.4 belsA per ISO 7779 & ISO 9296   |
| Bystander sound pressure in accordance with NEBS GR-63 Issue 2<br>Summit X450a-24t and X450a-48t | Bystander sound pressure: 54 dBA right side @ 0.6m  |

## Summit X450e Series Switches

The Summit X450e series includes the following switches:

- Summit X450e-24p switch
- Summit X450e-48p switch

**Table 31: Summit X450e Series Switch Technical Specifications**

### Physical Dimensions

|                         |  |
|-------------------------|--|
| Summit X450e-24p switch | Height: 1.73 inches (4.4 cm)<br>Width: 17.35 inches (44.1 cm)<br>Depth: 15.30 inches (38.9 cm) |
| Summit X450e-48p switch | Height: 1.73 inches (4.4 cm)<br>Width: 17.35 inches (44.1 cm)<br>Depth: 17 inches (43.2 cm)    |

### Weight

|                         |                   |
|-------------------------|-------------------|
| Summit X450e-24p switch | 14 lb (6.35 kg)   |
| Summit X450e-48p switch | 16.25 lb (7.4 kg) |

### Packaged Dimensions

|                         |  |
|-------------------------|--|
| Summit X450e-24p switch | Height: 5.9 inches (15 cm)                               |
| Summit X450e-48p switch | Width: 22.4 inches (57 cm)<br>Depth: 21.7 inches (55 cm) |

### Packaged Weight

|                         |                  |
|-------------------------|------------------|
| Summit X450e-24p switch | 18.9 lb (8.6 kg) |
| Summit X450e-48p switch | 21 lb (9.6 kg)   |

### Summit X450e-24p Power

|                               |  |
|-------------------------------|--|
| Operational voltage range     | 90 to 264 V ~  |
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 5.25 A  |
| Input current                 | 4.25 A @ 115 V ~ (low-line)<br>2.0 A @ 230 V ~ (high-line)   |
| Line frequency range          | 47 to 63 Hz  |
| Inrush current                | 30 A @ 115 V, 60 A @ 230 V   |
| Power supply cord type        | AC   |
| Power supply input socket     | IEC 320 C14  |
| Power cord input plug         | IEC 320 C13  |
| Power cord wall plug          | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.                                       |
| Power supply cord gauge       | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Heat dissipation, Watts, BTU  | 120 W, 409.5 BTU/hr  |
| Power consumption, Watts, BTU | 500 W, 1706.1 BTU/hr   |

### Summit X450e-48p Power

|                           |  |
|---------------------------|--|
| Operational voltage range | 90 to 264 V ~  |
| Nominal input ratings     | 100 to 240 V ~ , 50/60 Hz, 6 A                             |
| Nominal input current     | 5.25 A @ 115 V ~ (low-line)<br>2.5 A @ 230 V ~ (high-line) |
| Line frequency range      | 47 to 63 Hz  |
| Inrush current            | 30 A @ 115 V, 60 A @ 230 V                                 |

**Table 31: Summit X450e Series Switch Technical Specifications (Continued)**

|  |   |
|--|---|
| Power supply cord type                   | AC  |
| Power supply input socket                | IEC 320 C14   |
| Power cord input plug                    | IEC 320 C13   |
| Power cord wall plug                     | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.  |
| Power supply cord gauge                  | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet  |
| Heat dissipation, Watts/BTU              | 180 W/614.2 BTU/hr  |
| Power consumption, Watts/BTU             | 603 W/2057.5 BTU/hr   |
| <b>Safety Standards</b>                  |   |
| North American Safety of ITE             | UL 60950-1:2003 1st Ed., Listed Device (US)<br>CSA 22.2#60950-1-03 1st Ed.(Canada)<br>Complies with FCC 21CFR 1040.10 (US Laser Safety)<br>CDRH Letter of Approval (US FDA Approval)<br>IEEE 802.3af 6-2003 Environment A for PoE Applications  |
| European Safety of ITE                   | EN 60950-1:2001+A11<br>EN 60825-1+A2:2001 (Lasers Safety)<br>TUV-R GS Mark by German Notified Body<br>73/23/EEC Low Voltage Directive   |
| International Safety of ITE              | CB Report & Certificate per IEC 60950-1:2001 Country Deviations<br>AS/NZS 60950-1 (Australia /New Zealand)  |
| <b>EMI/EMC Standards</b>                 |   |
| North America EMC for ITE                | FCC CFR 47 part 15 Class A (USA)<br>ICES-003 Class A (Canada)   |
| European EMC standards                   | EN 55022:1998 Class A<br>EN 55024:1998 Class A includes IEC 61000-4-2, 3, 4, 5, 6, 8, 11<br>EN 61000-3-2,3 (Harmonics & Flicker)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>89/336/EEC EMC Directive   |
| International EMC certifications         | CISPR 22:1997 Class A (International Emissions)<br>CISPR 24:1997 Class A (International Immunity)<br>IEC/EN 61000-4-2 Electrostatic Discharge, 8kV Contact, 15kV Air, Criteria A<br>IEC/EN 61000-4-3 Radiated Immunity 10V/m, Criteria A<br>IEC/EN 61000-4-4 Transient Burst, 1kV, Criteria A<br>IEC/EN 61000-4-5 Surge, 2kV L-L, 2kV L-G, Level 3, Criteria A<br>IEC/EN 61000-4-6 Conducted Immunity, 0.15-80MHz, 10V/m unmod. RMS, Criteria A<br>IEC/EN 61000-4-11 Power Dips & Interruptions, >30%, 25 periods, Criteria C |
| Country-specific                         | VCCI Class A (Japan Emissions)<br>AS/NZS 3548 ACA (Australia Emissions)<br>CNS 13438:1997 Class A (BSMI-Taiwan)<br>MIC Mark, EMC Approval (North Korea)   |
| <b>Telecom Standards</b>                 |   |
| <b>IEEE 802.3 Media Access Standards</b> |   |
| <b>Environmental Data</b>                |   |
| Environmental standards                  | EN/ETSI 300 019-2-1 v2.1.2 - Class 1.2 Storage<br>EN/ETSI 300 019-2-2 v2.1.2 - Class 2.3 Transportation<br>EN/ETSI 300 019-2-3 v2.1.2 - Class 3.1e Operational<br>EN/ETSI 300 753 (1997-10) - Acoustic Noise<br>ASTM D3580 Random Vibration Unpackaged 1.5G   |

**Table 31: Summit X450e Series Switch Technical Specifications (Continued)**

|  |   |
|--|---|
| Operating conditions                           | Temperature range: 0° C to 40° C (32° F to 104° F)<br>Humidity: 10% to 93% relative humidity, non-condensing<br>Altitude: 0 to 3,000 meters (9,850 feet)<br>Shock (half sine): 30 m/s <sup>2</sup> (3 g), 11 ms, 60 shocks<br>Random vibration: 3 to 500 Hz @ 1.5 g rms   |
| Storage & transportation conditions (packaged) | Transportation temperature: -40° C to 70° C (-40° F to 158° F)<br>Storage and transportation humidity: 60% to 95% relative humidity, non-condensing<br>Packaged shock (half sine): 180 m/s <sup>2</sup> (18 g), 6 ms, 600 shocks<br>Packaged sine vibration: 5 to 62 Hz @ velocity 5 mm/s, 62 to 500 Hz @ 0.2 G<br>Packaged random vibration: 5 to 20 Hz @ 1.0 ASD w/-3 dB/oct. from 20 to 200 Hz<br>14 drops minimum on sides & corners @ 42"(<15kg box) |

# Summit X650 Series Switches

The Summit X650 series includes the following switches:

- Summit X650e-24t switch
- Summit X650-24x switch

**Table 32: Summit X650 Series Switch Technical Specifications**

## Physical Dimensions

|                        |                               |
|------------------------|-------------------------------|
| Summit X650-24t switch | Height: 1.73 inches (4.4 cm)  |
| Summit X650-24x switch | Width: 17.35 inches (44.1 cm) |
|                        | Depth: 15.30 inches (38.9 cm) |

## Weight

|                        |                   |
|------------------------|-------------------|
| Summit X650-24t switch | 50.7 lb (23 kg)   |
| Summit X650-24x switch | 46.1 lb (20.9 kg) |

## Packaged Dimensions

|                        |                            |
|------------------------|----------------------------|
| Summit X650-24t switch | Height: 5.9 inches (15 cm) |
| Summit X650-24x switch | Width: 22.4 inches (57 cm) |
|                        | Depth: 21.7 inches (55 cm) |

## Packaged Weight

|                        |                   |
|------------------------|-------------------|
| Summit X650-24t switch | 52.9 lb (24 kg)   |
| Summit X650-24x switch | 48.3 lb (21.9 kg) |

## Power: Summit X650-24t (Manufacturing part number 800246-00)

### Summit X650-24t with VIM1-SummitStack Module (AC Power Supply)

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 8.0 A                          |
| Input current                 | 6.9 A @ 100 V ~ (low-line)<br>2.9 A @ 240 V ~ (high-line) |
| Heat dissipation, Watts, BTU  | 689 W, 2,351 BTU/hr                                       |
| Power consumption, Watts, BTU | 689 W, 2,351 BTU/hr                                       |

### Summit X650-24t with VIM1-SummitStack Module (DC Power Supply)

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 48 to 60 V $\equiv$ , 24 A  |
| Input current                 | 12.8 A @ 48 V $\equiv$ (low-line)<br>10.6 A @ 60 V $\equiv$ (high-line) |
| Heat dissipation, Watts, BTU  | 617 W, 2,105 BTU/hr   |
| Power consumption, Watts, BTU | 617 W, 2,105 BTU/hr   |

### Summit X650-24t with VIM1-10G8X Module (AC Power Supply)

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 8.0 A                          |
| Input current                 | 7.8 A @ 100 V ~ (low-line)<br>3.8 A @ 240 V ~ (high-line) |
| Heat dissipation, Watts, BTU  | 780 W, 2,661 BTU/hr                                       |
| Power consumption, Watts, BTU | 780 W, 2,661 BTU/hr                                       |

### Summit X650-24t with VIM1-10G8X Module (DC Power Supply)

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 48 to 60 V $\equiv$ , 24 A  |
| Input current                 | 14.6 A @ 48 V $\equiv$ (low-line)<br>12.3 A @ 60 V $\equiv$ (high-line) |
| Heat dissipation, Watts, BTU  | 701 W, 2,393 BTU/hr   |
| Power consumption, Watts, BTU | 701 W, 2,393 BTU/hr   |

**Table 32: Summit X650 Series Switch Technical Specifications (Continued)****Summit X650-24t with VIM1-SummitStack512 Module (AC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 8.0 A                          |
| Input current                 | 8.0 A @ 100 V ~ (low-line)<br>3.8 A @ 240 V ~ (high-line) |
| Heat dissipation, Watts, BTU  | 798 W, 2,723 BTU/hr                                       |
| Power consumption, Watts, BTU | 798 W, 2,723 BTU/hr                                       |

**Summit X650-24t with VIM1-SummitStack512 Module (DC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 48 to 60 V $\equiv$ , 24 A  |
| Input current                 | 14.8 A @ 48 V $\equiv$ (low-line)<br>12.5 A @ 60 V $\equiv$ (high-line) |
| Heat dissipation, Watts, BTU  | 708 W, 2,416 BTU/hr   |
| Power consumption, Watts, BTU | 708 W, 2,416 BTU/hr   |

**Power: Summit X650-24t (Manufacturing part number 800320-00)****Summit X650-24t with VIM1-SummitStack Module (AC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 8.0 A                          |
| Input current                 | 4.6 A @ 100 V ~ (low-line)<br>1.6 A @ 240 V ~ (high-line) |
| Heat dissipation, Watts, BTU  | 463 W, 1,580 BTU/hr                                       |
| Power consumption, Watts, BTU | 463 W, 1,580 BTU/hr                                       |

**Summit X650-24t with VIM1-SummitStack Module (DC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 48 to 60 V $\equiv$ , 24 A  |
| Input current                 | 8.7 A @ 48 V $\equiv$ (low-line)<br>7.1 A @ 60 V $\equiv$ (high-line) |
| Heat dissipation, Watts, BTU  | 418 W, 1,426 BTU/hr   |
| Power consumption, Watts, BTU | 418 W, 1,426 BTU/hr   |

**Summit X650-24t with VIM1-10G8X Module (AC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 8.0 A                          |
| Input current                 | 5.5 A @ 100 V ~ (low-line)<br>2.5 A @ 240 V ~ (high-line) |
| Heat dissipation, Watts, BTU  | 552 W, 1,884 BTU/hr                                       |
| Power consumption, Watts, BTU | 552 W, 1,884 BTU/hr                                       |

**Summit X650-24t with VIM1-10G8X Module (DC Power Supply)**

|                               |  |
|-------------------------------|--|
| Nominal input ratings         | 48 to 60 V $\equiv$ , 24 A   |
| Input current                 | 10.4 A @ 48 V $\equiv$ (low-line)<br>8.8 A @ 60 V $\equiv$ (high-line) |
| Heat dissipation, Watts, BTU  | 500 W, 1,706 BTU/hr  |
| Power consumption, Watts, BTU | 500 W, 1,706 BTU/hr  |

**Summit X650-24t with VIM1-SummitStack512 Module (AC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V ~ , 50/60 Hz, 8.0 A                          |
| Input current                 | 5.7 A @ 100 V ~ (low-line)<br>2.7 A @ 240 V ~ (high-line) |
| Heat dissipation, Watts, BTU  | 565 W, 1,928 BTU/hr                                       |
| Power consumption, Watts, BTU | 565 W, 1,928 BTU/hr                                       |

**Table 32: Summit X650 Series Switch Technical Specifications (Continued)****Summit X650-24t with VIM1-SummitStack512 Module (DC Power Supply)**

|                               |  |
|-------------------------------|--|
| Nominal input ratings         | 48 to 60 V <sub>DC</sub> , 24 A  |
| Input current                 | 10.4 A @ 48 V <sub>DC</sub> (low-line)<br>8.8 A @ 60 V <sub>DC</sub> (high-line) |
| Heat dissipation, Watts, BTU  | 501 W, 1,709 BTU/hr  |
| Power consumption, Watts, BTU | 501 W, 1,709 BTU/hr  |

**Power: Summit X650-24x with VIM1-SummitStack Module (all manufacturing part numbers)****Summit X650-24x with VIM1-SummitStack Module (AC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V <sub>AC</sub> , 50/60 Hz, 4.75 A                                     |
| Input current                 | 2.9 A @ 100 V <sub>AC</sub> (low-line)<br>1.2 A @ 240 V <sub>AC</sub> (high-line) |
| Heat dissipation, Watts, BTU  | 291 W, 992 BTU/hr   |
| Power consumption, Watts, BTU | 291 W, 992 BTU/hr   |

**Summit X650-24x with VIM1-SummitStack Module (DC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 48 to 60 V <sub>DC</sub> , 9 A  |
| Input current                 | 5.9 A @ 48 V <sub>DC</sub> (low-line)<br>4.8 A @ 60 V <sub>DC</sub> (high-line) |
| Heat dissipation, Watts, BTU  | 287 W, 979 BTU/hr   |
| Power consumption, Watts, BTU | 287 W, 979 BTU/hr   |

**Summit X650-24x with VIM1-10G8X Module (AC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V <sub>AC</sub> , 50/60 Hz, 4.75 A                                     |
| Input current                 | 3.7 A @ 100 V <sub>AC</sub> (low-line)<br>1.5 A @ 240 V <sub>AC</sub> (high-line) |
| Heat dissipation, Watts, BTU  | 371 W, 1,402 BTU/hr   |
| Power consumption, Watts, BTU | 371 W, 1,402 BTU/hr   |

**Summit X650-24x with VIM1-10G8X Module (DC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 48 to 60 V <sub>DC</sub> , 9 A  |
| Input current                 | 7.5 A @ 48 V <sub>DC</sub> (low-line)<br>6.1 A @ 60 V <sub>DC</sub> (high-line) |
| Heat dissipation, Watts, BTU  | 364 W, 1,242 BTU/hr   |
| Power consumption, Watts, BTU | 364 W, 1,242 BTU/hr   |

**Summit X650-24x with VIM1-SummitStack512 Module (AC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 100 to 240 V <sub>AC</sub> , 50/60 Hz, 4.75 A                                     |
| Input current                 | 3.8 A @ 100 V <sub>AC</sub> (low-line)<br>1.6 A @ 240 V <sub>AC</sub> (high-line) |
| Heat dissipation, Watts, BTU  | 383 W, 1,307 BTU/hr   |
| Power consumption, Watts, BTU | 383 W, 1,307 BTU/hr   |

**Summit X650-24x with VIM1-SummitStack512 Module (DC Power Supply)**

|                               |   |
|-------------------------------|---|
| Nominal input ratings         | 48 to 60 V <sub>DC</sub> , 9 A  |
| Input current                 | 7.7 A @ 48 V <sub>DC</sub> (low-line)<br>6.2 A @ 60 V <sub>DC</sub> (high-line) |
| Heat dissipation, Watts, BTU  | 372 W, 1,269 BTU/hr   |
| Power consumption, Watts, BTU | 372 W, 1,269 BTU/hr   |

**Table 32: Summit X650 Series Switch Technical Specifications (Continued)**
**Safety Standards**

|                              |  |
|------------------------------|--|
| North American Safety of ITE | UL 60950-1:2003 1st Ed., Listed Device (US)<br>CSA 22.2#60950-1-03 1st Ed.(Canada)<br>Complies with FCC 21CFR 1040.10 (US Laser Safety)<br>CDRH Letter of Approval (US FDA Approval)<br>IEEE 802.3af 6-2003 Environment A for PoE Applications |
| European Safety of ITE       | EN 60950-1:2001+A11<br>EN 60825-1+A2:2001 (Lasers Safety)<br>TUV-R GS Mark by German Notified Body<br>73/23/EEC Low Voltage Directive  |
| International Safety of ITE  | CB Report & Certificate per IEC 60950-1:2001 Country Deviations<br>AS/NZX 60950-1 (Australia /New Zealand)   |

**EMI/EMC Standards**

|                                  |   |
|----------------------------------|---|
| North America EMC for ITE        | FCC CFR 47 part 15 Class A (USA)<br>ICES-003 Class A (Canada)   |
| European EMC standards           | EN 55022:1998 Class A<br>EN 55024:1998 Class A includes IEC 61000-4-2, 3, 4, 5, 6, 8, 11<br>EN 61000-3-2,3 (Harmonics & Flicker)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>89/336/EEC EMC Directive   |
| International EMC certifications | CISPR 22:1997 Class A (International Emissions)<br>CISPR 24:1997 Class A (International Immunity)<br>IEC/EN 61000-4-2 Electrostatic Discharge, 8kV Contact, 15kV Air, Criteria A<br>IEC/EN 61000-4-3 Radiated Immunity 10V/m, Criteria A<br>IEC/EN 61000-4-4 Transient Burst, 1kV, Criteria A<br>IEC/EN 61000-4-5 Surge, 2kV L-L, 2kV L-G, Level 3, Criteria A<br>IEC/EN 61000-4-6 Conducted Immunity, 0.15-80MHz, 10V/m unmod. RMS, Criteria A<br>IEC/EN 61000-4-11 Power Dips & Interruptions, >30%, 25 periods, Criteria C |
| Country-specific                 | VCCI Class A (Japan Emissions)<br>AS/NZS 3548 ACA (Australia Emissions)<br>CNS 13438:1997 Class A (BSMI-Taiwan)<br>MIC Mark, EMC Approval (North Korea)<br>ETSI EN 300 386:2001 (EMC Telecommunications)<br>ETSI EN 300 019 (Environmental for Telecommunications)  |

**Telecom Standards**

**IEEE 802.3 Media Access Standards** IEEE 802.3ab 1000BASE-T

**Environmental Data**

|                         |   |
|-------------------------|---|
| Environmental standards | EN/ETSI 300 019-2-1 v2.1.2 - Class 1.2 Storage<br>EN/ETSI 300 019-2-2 v2.1.2 - Class 2.3 Transportation<br>EN/ETSI 300 019-2-3 v2.1.2 - Class 3.1e Operational<br>EN/ETSI 300 753 (1997-10) - Acoustic Noise<br>ASTM D3580 Random Vibration Unpackaged 1.5G             |
| Operating conditions    | Temperature range: 0° C to 40° C (32° F to 104° F)<br>Humidity: 10% to 93% relative humidity, non-condensing<br>Altitude: 0 to 3,000 meters (9,850 feet)<br>Shock (half sine): 30 m/s <sup>2</sup> (3 g), 11 ms, 60 shocks<br>Random vibration: 3 to 500 Hz @ 1.5 g rms |



**Table 32: Summit X650 Series Switch Technical Specifications (Continued)**

|  |   |
|--|---|
| Storage & transportation conditions (packaged) | Transportation temperature: -40° C to 70° C (-40° F to 158° F)<br>Storage and transportation humidity: 60% to 95% relative humidity, non-condensing<br>Packaged shock (half sine): 180 m/s <sup>2</sup> (18 g), 6 ms, 600 shocks<br>Packaged sine vibration: 5 to 62 Hz @ velocity 5 mm/s, 62 to 500 Hz @ 0.2 G<br>Packaged random vibration: 5 to 20 Hz @ 1.0 ASD w/-3 dB/oct. from 20 to 200 Hz<br>14 drops minimum on sides & corners @ 42"(<15kg box) |
|--|---|

## Summit X650 Power Supplies

The Summit X650 power supplies can be used in the Summit X650-24t switch and the Summit X650-24x switch.

Two Summit X650 power supplies are available:

- Summit X650 AC PSU
- Summit X650 DC PSU

**Table 33: Summit X650 AC PSU (Model 10914)**

For use with the Summit X650-24t and X650-24x switches

|                                     |   |
|-------------------------------------|---|
| Voltage input range                 | 90 to 264 V ~   |
| Nominal input ratings               | 100 to 240 V ~ , 50 to 60 Hz, 10 A  |
| Nominal input current at full loads | 12 A @ 90 V ~ (low-line)<br>5 A @ 230 V ~ (high-line)   |
| Line frequency range                | 47 to 63 Hz   |
| Maximum inrush current              | 100 A   |
| Output                              | 12 V $\equiv$ , 70 A max, 840 Watts<br>3.3 V $\equiv$ , 6 A max, 19.8 Watts<br>Maximum continuous DC output shall not exceed 850 Watts. |
| Power supply cord type              | AC  |
| Power supply input socket           | IEC 320 C14   |
| Power cord input plug               | IEC 320 C13   |
| Power cord wall plug                | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.  |
| Power supply cord gauge             | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet                              |
| Efficiency                          | 80% with 60% to 100% load   |

**Table 34: Summit X650 DC PSU (Model 10915)**

For use with the Summit X650-24t and X650-24x switches

|                         |  |
|-------------------------|--|
| Nominal Input           | -48 to -60 V $\equiv$  |
| DC Voltage Input Range  | -39 to -72 V $\equiv$  |
| Maximum Input Amperages | 26 A @ 40 V $\equiv$<br>22 A @ 48 V $\equiv$<br>15 A @ 72 V $\equiv$   |
| Minimum wire size       | 12 AWG (3.3 mm <sup>2</sup> ) copper stranded  |
| DC Output               | 12 V $\equiv$ , 70 A/3.3 V $\equiv$ , 6 A  |
| DC Output Power (W)     | 850 W  |
| Operating temperature   | 0°C to 40°C (normal operation)<br>Short-term operation is permitted at -5°C to 0°C and 40°C to 50°C,<br>for no more than 96 consecutive hours and a total of not more than<br>15 days in 1 year. |
| Storage temperature     | -40°C to 85°C  |
| Operating humidity      | 20% to 95% relative humidity, non-condensing   |
| Operational shock       | 30 m/s <sup>2</sup> (3g)   |

# Summit External Power Supplies

The following external power supplies are available for use with Summit X159 series, X250e series, X450 series, X450a series, and X450e series switches:

- EPS-LD external power supply ([Table 35](#))
- EPS-160 external power module (used with EPS-T chassis) ([Table 36](#))
- EPS-500 external power supply ([Table 38](#))
- EPS-600LS external power module (used with EPS-C chassis) ([Table 39](#))
- EPS-150DC external power supply (used with EPS-T2 chassis) ([Table 40](#))

**Table 35: EPS-LD External Power Supply (Model 45019)**

For use with the Summit X450a-24t and X450e-24p switches

|  |  |
|--|--|
| Operational voltage range                                | 90 to 264 V ~  |
| Nominal input ratings                                    | 100 to 240 V ~ , 50 to 60 Hz, 10 A   |
| Input Current  | 6 A at 100 V ~ , 2.5 A at 240 V ~  |
| Line frequency range                                     | 47 to 63 Hz  |
| Maximum inrush current                                   | 30 A at 115 V ~ , 60 A at 230 V ~  |
| Output   | -50 V = , 7.5 A max, 375 Watts<br>12 V = , 7.5 A max, 90 Watts   |
| Power supply cord type                                   | AC   |
| Power supply input socket                                | IEC 320 C14  |
| Power cord input plug                                    | IEC 320 C13  |
| Power cord wall plug                                     | Refer to “ <a href="#">Selecting Power Supply Cords</a> ” on page 170.                                     |
| Power supply cord gauge                                  | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency   | >75% at 100% load  |
| Heat dissipation, Watts, BTU/hr                          | 123 W, 419.7 BTU/hr  |
| Power consumption, Watts, BTU/hr                         | 588 W, 2006.3 BTU/hr   |
| Ambient operating temperature                            | 0° C to 40° C (32° F to 104° F)  |
| Maximum continuous DC output shall not exceed 465 Watts. |  |

**Table 36: EPS-160 External Power Module (Model 10907)**

For use with the Summit X150-24t, X150-48t, X250e-24t, X250e-24x, X250e-48t, X450-24t, and X450-24x switches


|                           |                                     |
|---------------------------|-------------------------------------|
| Operational voltage range | 90 to 264 V ~                       |
| Nominal input ratings     | 100 to 250 V, 4 to 2 A, 47 to 63 Hz |
| Line frequency range      | 47 to 63 Hz                         |
| Input current             | 2 A at 100 V<br>1 A at 240 V        |
| Line frequency            | 50 to 60 Hz                         |
| Maximum inrush current    | 30 A at 115 V ~ , 50 A at 230 V ~   |

**Table 36: EPS-160 External Power Module (Model 10907) (Continued)**

|                                  |  |
|----------------------------------|--|
| Output                           | 12 V <sub>DC</sub> , 11 A<br>5 V <sub>DC</sub> , 1.5 A   |
| Power supply cord type           | AC   |
| Power supply input socket        | IEC 320 C14  |
| Power supply input plug          | IEC 320 C13  |
| Power cord wall plug             | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.                                       |
| Power supply cord gauge          | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| Efficiency                       | 80% at 100% load   |
| Heat dissipation, Watts/BTU      | 38.5 W, 131.4 BTU/hr   |
| Power consumption, Watts, BTU/hr | 178 W, 607.4 BTU/hr  |
| Ambient operating temperature    | 0° C to 40° C (32° F to 104° F)  |

[Table 37](#) shows the wire-to-pin connections for the connector on the rear panel of the EPS-160 power supply.

**Table 37: Pinouts for the Redundant Power Supply Connector**

| Connector  | Pin Number | Wire Label | Pin Number | Wire Label |
|--|------------|------------|------------|------------|
|  | 1          | NC         | 8          | RS+        |
|  | 2          | GND        | 9          | GND        |
|  | 3          | GND        | 10         | INT PG     |
|  | 4          | GND        | 11         | EXT_CON    |
|  | 5          | GND        | 12         | EXT_PG     |
|  | 6          | +12 V      | 13         | +5 V       |
|  | 7          | +12 V      | 14         | +12 V      |

**Table 38: EPS-500 External Power Supply (Model 109110)**

For use with the Summit X150-24p, X250e-24p, X450a-24t, X450a-24x, X450a-48t, and X450e-24p switches

|                           |  |
|---------------------------|--|
| Operational voltage range | 90 to 264 V <sub>AC</sub>  |
| Nominal input ratings     | 100 to 240 V <sub>AC</sub> , 50 to 60 Hz, 10 A   |
| Nominal input current     | 5.75 A @ 115 V <sub>AC</sub> (low-line)<br>2.80 A @ 230 V <sub>AC</sub> (high-line)  |
| Line frequency range      | 47 to 63 Hz  |
| Maximum inrush current    | 30 A @ 115 V, 60 A @ 220 V <sub>AC</sub>   |
| Output                    | -50 V <sub>DC</sub> , 7.5 A max, 375 Watts<br>12 V <sub>DC</sub> , 10.5 A max, 126 Watts<br>Maximum continuous DC output shall not exceed 500 Watts. |
| Power supply cord type    | AC   |
| Power supply input socket | IEC 320 C14  |
| Power cord input plug     | IEC 320 C13  |
| Power cord wall plug      | Refer to <a href="#">“Selecting Power Supply Cords”</a> on page 170.   |
| Power supply cord gauge   | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet   |
| Efficiency                | >70% @ 100% load   |

**Table 38: EPS-500 External Power Supply (Model 109110)**

|                                  |                                 |
|----------------------------------|---------------------------------|
| Heat dissipation, Watts, BTU/hr  | 158 W, 539.1 BTU/hr             |
| Power consumption, Watts, BTU/hr | 659 W, 2248.6 BTU/hr            |
| Ambient operating temperature    | 0° C to 40° C (32° F to 104° F) |

**Table 39: EPS-600LS External Power Module (Model 10913)**

For use with the Summit X450e-48p and X250e-48p switches  
Must be installed in the EPS-C chassis (Model 10912)

|                                  |  |
|----------------------------------|--|
| Operational voltage range        | 90 to 264 V ~  |
| Nominal input ratings            | 100-250 V ~ , 50-60 Hz, 10 A   |
| Nominal input current            | 7 A @ 115 V ~ (low-line)<br>3.5 A @ 230 V ~ (high-line)  |
| Line frequency range             | 47 to 63 Hz  |
| <b>Maximum inrush current</b>    | 17 A @ 115 V/60 Hz, maximum load   |
| Output power                     | 600 W  |
| Power supply cord type           | AC   |
| Power supply input socket        | IEC 320 C14  |
| Power cord input plug            | IEC 320 C13  |
| Power cord wall plug             | Refer to <a href="#">“Selecting Power Supply Cords” on page 170.</a>                                       |
| Power supply cord gauge          | 18 AWG (0.75 mm <sup>2</sup> ) up to 6 feet or 2 meters<br>or<br>16 AWG (1.0 mm <sup>2</sup> ) over 6 feet |
| <b>Efficiency</b>                | 85% nominal  |
| Heat dissipation, Watts, BTU/hr  | 219 W, 747.3 BTU/hr  |
| Power consumption, Watts, BTU/hr | 801 W, 2733.1 BTU/hr   |
| Ambient operating temperature    | 0° C to 40° C (32° F to 104° F)  |

**Output Ratings for EPS-C chassis with 1, 2, or 3 installed EPS-600LS units**

|                               |   |
|-------------------------------|---|
| One EPS-600-LS unit           | 582 W output: –48 V/9 A (432 W), 12 V/12.5 A  |
| Two EPS-600-LS units          | 1116 W output: –48 V/18 A (864 W), 12 V/21 A  |
| <b>Three EPS-600-LS units</b> | 1260 W output: –48 V/21 A (1008 W), 12 V/21 A |

**Table 40: EPS-150DC External Power Module (Model 10909)**


For use with the Summit X450a-24tDC and Summit X450a-24xDC switches

|  |   |
|--|---|
| Operational voltage range              | –36 to –72 V <sub>DC</sub>  |
| Nominal input ratings                  | –36 to –72 V <sub>DC</sub> , 6 A maximum  |
| Input current                          | 5.5 A @ –36 V <sub>DC</sub> (low-line)<br>2.6 A @ –72 V <sub>DC</sub> (high-line) |
| Line frequency range                   | 47 to 63 Hz   |
| Inrush current                         | 20 A @ 48 V, 40 A @ 72 V <sub>DC</sub>  |
| Input wire harness                     | Extreme part number 250088-00   |
| Power supply input socket              | TYCO PN 206061-1  |
| Power cord input plug                  | TYCO PN 206060-1  |
| Power cord wall plug                   | None provided   |
| Power supply cord gauge                | 14 AWG (2.0 mm <sup>2</sup> )   |
| Input wire harness                     | Extreme part number 250088-00   |
| Efficiency                             | > 75% at 100% load  |
| Heat dissipation, Watts, BTU/hr        | 45 W, 153.5 BTU/hr  |
| Power consumption, Watts, BTU/hr       | 195 W, 665.4 BTU/hr   |
| Ambient operating temperature          | 0° C to 40° C   |
| Storage and transportation temperature | –40° C to 70° C   |

[Table 41](#) provides the wire-to-pin connection specifications for the DC wiring harness shipped with the EPS-150DC power supply. [Figure 130](#) shows the connector.

**Table 41: Wire-to-Pin Connection Specifications**

| Pin Number | Wire Color   | Circuit Connection |
|------------|--------------|--------------------|
| 1          | Green/yellow | Chassis ground     |
| 2          | Red          | Return             |
| 3          | Black        | –48 V              |
| 4          | unused       |                    |

**Figure 130: Three-wire Wiring Harness**

EWUG005

## Console Connector Pinouts

This section provides connector pinouts for the console port and associated cables.

Table 42 describes the pinouts for a DB-9 console plug connector.

**Table 42: Pinouts for the DB-9 Console Connector**

| Function                  | Pin Number | Direction |
|---------------------------|------------|-----------|
| DCD (data carrier detect) | 1          | In        |
| RXD (receive data)        | 2          | In        |
| TXD (transmit data)       | 3          | Out       |
| DTR (data terminal ready) | 4          | Out       |
| GND (ground)              | 5          | -         |
| DSR (data set ready)      | 6          | In        |
| RTS (request to send)     | 7          | Out       |
| CTS (clear to send)       | 8          | In        |

Figure 131 shows the pinouts for a 9-pin to 25-pin (RS-232) null-modem cable.

**Figure 131: Null-Modem Cable Pinouts**

### Switch

Cable connector: 9-pin female

|        |       |   |
|--------|-------|---|
| Screen | Shell | ● |
| TxD    | 3     | ● |
| RxD    | 2     | ● |
| Ground | 5     | ● |
| RTS    | 7     | ● |
| CTS    | 8     | ● |
| DSR    | 6     | ● |
| DCD    | 1     | ● |
| DTR    | 4     | ● |

### PC/Terminal

Cable connector: 25-pin male/female


|   |    |        |
|---|----|--------|
| ● | 1  | Screen |
| ● | 3  | RxD    |
| ● | 2  | TxD    |
| ● | 7  | Ground |
| ● | 4  | RTS    |
| ● | 20 | DTR    |
| ● | 5  | CTS    |
| ● | 6  | DSR    |
| ● | 8  | DCD    |

25pin



Figure 132 shows the pinouts for a 9-pin to 9-pin (PC-AT) null-modem serial cable.

Figure 132: PC-AT Serial Null-modem Cable Pinouts



25pin



## Numerics

10GBASE-T ports, 121

## A

amperage, calculating for UPS, 86

ANSI standards, 87

automatic failover, setting up, 17

## B

bend radius, 81, 82

BICSI standards, 80

building codes, 76

Building Industry Consulting Service International. *See* BICSI

bundling cable, 81

## C

cable

category 5, 81

for 10GBASE-T ports, 121

installing

fiber optic, 82

recommendations, 81

labeling, 81

types and distances, 83

cable connections, 121

cable slack, 81

cabling standards

ANSI, 87

BICSI, 80

category 5 cable, 81

combination ports, 17

commercial building standards, 87

connecting fiber optic cable, 122

connector jackets, RJ-45, 84

connector pinouts

DB-9 console connector, 212

DC wiring harness, 211

null-modem cable, 212

null-modem serial cable, 213

redundant power connector, 208

console port

in a stacked configuration, 95

settings, 122

Summit X150 series, 18

Summit X250e series, 23

Summit X350 series, 35

Summit X450 series, 40

Summit X450a series, 40

Summit X450e series, 40

Summit X650 series, 58

conventions, text, 10

## D

DB-9 pinouts, 212

DC power, connecting

EPS-150DC, 137

Summit X650 DC PSU, 114

DC wiring harness

connecting to DC source, 137

connecting to EPS-150DC, 138

specifications, 211

DC-powered switches

removing, 102

Summit X250e-24tDC, 25

Summit X450a-24tDC, 46

Summit X450a-48tDC, 51

design standards, 87

dual 10-Gigabit uplinks

in Summit X450 switches, 40

installing, 147

## E

electrical codes, 76

electrostatic discharge. *See* ESD

environmental requirements

building codes, 76

electrical codes, 76

humidity, 78

temperature, 77

wiring closet, 77

EPS-150DC power supply

features, 68

installing, 135

specifications, 211

with Summit X250e-24tDC switch, 25

with Summit X450a-24tDC switch, 46

with Summit X450a-24xDC switch, 29, 49

with Summit X450a-48tDC switch, 31, 52

EPS-160 power supply

- features, 66
  - installing, 126
  - specifications, 207
  - with EPS-T, 67
  - with Summit X450-24t switch, 42
  - with Summit X450-24x switch, 43
- EPS-500 power supply
  - features, 68
  - installing, 132
  - specifications, 208
  - with Summit X350-24t switch, 37
  - with Summit X350a-48t switch, 38
  - with Summit X450a-48t switch, 51
  - with Summit X450e-24p switch, 54
- EPS-600LS power supply
  - features, 69
  - installing, 140
  - specifications, 210
  - with Summit X250e-48p switch, 32
  - with Summit X450e-48p switch, 55
- EPS-C chassis (with EPS-600LS), 140
- EPS-LD power supply
  - features, 67
  - installing, 129
  - specifications, 207
  - with Summit X450a-24t switch, 45
  - with Summit X450a-24x switch, 48
  - with Summit X450e-24p switch, 54
- EPS-T2 (with EPS-150DC), 68, 135
- equipment rack
  - grounding, 79
  - mechanical recommendations, 79
  - mounting holes, 79
  - securing, 80
  - service access, 79
  - space requirements, 79
- ESD
  - discharge from cable, 81
  - system protection, 78

## F

- Fan LED, Summit X450a series switches, 57
- fiber optic cable
  - bend radius, 82
  - connections, 122
- first switch login, 123

## G

- grounding
  - DC-powered switch, 99
  - racks, 79
  - requirements, 87

- Summit X650 DC PSU, 113
- wiring closet, 77

## H

- humidity, 78

## I

- industry standards, 87
- initial switch login, 123
- installation
  - 10-gigabit uplinks, 147
  - DC-powered switch, 98
  - Summit family switch, 96
  - Summit X650 AC power supply, 109
  - Summit X650 DC power supply, 110
  - Summit X650 series switch, 103
  - Summit XGM2-2xf option card, 150
  - SummitStack configuration, 90
- IP settings, configuring, 123

## L

- labeling system for cables, 81
- labels, cable, 81
- LEDs
  - EPS-150DC power supply, 140
  - EPS-160 power supply, 129, 132
  - EPS-500 power supply, 135
  - stack number indicator, 63
  - stacking port, 96
  - Summit X150 series switches, 22
  - Summit X250e series switches, 34
  - Summit X350 switches, 39
  - Summit X450 switches, 57
  - Summit X650 switches, 63
- local management connection, 122
- logging in to the switch, 123

## M

- management port
  - in a stacked configuration, 96
  - Summit X150 series switches, 18
  - Summit X250e series switches, 23
  - Summit X350 series switches, 35
  - Summit X450 switches, 40
  - Summit X650 series switches, 58
- maximum cable distances, 83

## N

- network interface connections, 121
- null-modem cable pinouts, 212

## O

- operating environment requirements, 77
- option cards
  - XGM2-2xf, 150
  - XGM2-2xn, 149
  - XGM-2bt, 151
  - XGM-2sf, 151
  - XGM-2xn, 148

## P

- PC-AT serial null-modem cable pinouts, 213
- physical layer problems, 84
- pinouts
  - DB-9 console connector, 212
  - DC wiring harness, 211
  - null-modem cable, 212
  - PC-AT serial null-modem cable, 213
  - redundant power connector, 208
- plenum-rated cable, 82
- PoE devices, power requirements, 85
- ports
  - combination, 17
  - console port settings, 122
- power requirements
  - PoE devices, 85
  - power cable, 170
  - power supplies, 85
- power supply unit (PSU)
  - EPS-150DC, 68, 135, 211
  - EPS-160, 66, 126, 207
  - EPS-500, 68, 132, 208
  - EPS-600LS, 69, 140, 210
  - EPS-LD, 67, 129, 207
  - Summit X650, 206
  - Summit X650 AC, 109, 206
  - Summit X650 DC, 110

## R

- rack installation
  - EPS-500 power supply, 133
  - EPS-C chassis, 141
  - EPS-LD power supply, 129
  - EPS-T chassis, 126
  - EPS-T2 chassis, 136
  - Summit X650 switch, 103
  - switch, 97
- rack specifications
  - grounding, 79
  - mechanical recommendations, 78, 79
  - mounting holes, 78, 79
  - securing to floor, 80

- space requirements, 79
- standards, 78
- radio frequency interference. *See* RF interference
- redundant uplink ports, 17
- related publications, 10
- removing
  - EPS-150DC power supply, 140
  - EPS-160 power supply, 129
  - EPS-600LS power module, 145
  - EPS-LD power supply, 132
  - Summit switch, 98
  - Summit X450a-48t switch, 102
  - Summit X650 AC PSU, 155
  - Summit X650 DC PSU, 157
  - Summit X650 fan module, 162
  - Summit X650 series switch
    - four-post rack (cabinet), 120
    - two-post rack, 118
  - VIM1 module, 163
- replacement
  - Summit X650 AC PSU, 155
  - Summit X650 DC PSU, 157
- requirements
  - power cable, 170
- RF interference
  - patch panel installation, 81
  - preventing, 84
- RJ-45 cable, 84
- rules for redundant uplink ports, 18

## S

- safety requirements. *See* environmental requirements
- service access to the rack, 79
- signal quality and RF interference, 84
- site planning process, 75
- slack in cable, 81
- slot number in a stack, 90
- space requirements, rack, 79
- specifications
  - EPS-150DC power supply, 211
  - EPS-160 power supply, 207
  - EPS-500 power supply, 208
  - EPS-600LS power supply, 210
  - EPS-LD power supply, 207
  - Summit X150 series switches, 179
  - Summit X250e series switch, 183
  - Summit X450 series switches, 192
  - Summit X450a series switches, 194
  - Summit X450e series switches, 198
  - Summit X650 AC power supply, 206
  - Summit X650 DC power supply, 206
  - Summit X650 series switches, 201

- stack master, 91
- stacking
  - connecting 128G cables, 95
  - connecting 40G cables, 94
  - connection order, 92
  - redundancy, 91
  - slot number, 90
- stacking LEDs, 63
- standards
  - cabling, 80, 87
  - commercial building, 87
  - grounding, 87
- Summit family switches
  - DC-powered, 102
  - desktop mounting, 98
  - installation summary, 96
  - LEDs
    - Summit X150 series, 22
    - Summit X250e series, 34
    - Summit X350 series, 39
    - Summit X450, 450a, 450e series, 57
    - Summit X650 series, 63
  - rack-mounting, 97
  - removing, 98
  - See also* specific series names
  - XGM-2xn option card, 148
- Summit option cards
  - types, 147
  - XGM2-2xf, 150
  - XGM2-2xn, 149
  - XGM-2bt, 151
  - XGM-2sf, 151
  - XGM-2xn, 148
- Summit X150 series switches
  - features, 18
  - LEDs, 22
  - specifications, 179
  - Summit X150-24p switch, 20
  - Summit X150-48t switch, 21
  - Summit X210-24t switch, 19
- Summit X250e series switches
  - features, 23
  - LEDs, 34
  - specifications, 183
  - Summit X250e-24p switch, 26
  - Summit X250e-24t switch, 24
  - Summit X250e-24tDC switch, 25
  - Summit X250e-24x switch, 27, 28
  - Summit X250e-48p switch, 32
  - Summit X250e-48t switch, 29, 30
- Summit X350 series switches
  - features, 35
  - LEDs, 39
  - Summit X350-24t switch, 36
  - Summit X350-48t switch, 37
- Summit X450 series switches
  - features, 41
  - LEDs, 57
  - specifications, 192
  - Summit X450-24t switch, 41
  - Summit X450-24x switch, 42
- Summit X450a series switches
  - features, 44
  - LEDs, 57
  - specifications, 194
  - Summit X450a-24t switch, 44
  - Summit X450a-24tDC switch, 46
  - Summit X450a-24x switch, 47
  - Summit X450a-24xDC switch, 49
  - Summit X450a-48t switch, 50
  - Summit X450a-48tDC switch, 51
- Summit X450a-48t switch, removing, 102
- Summit X450e series switches
  - features, 53
  - LEDs, 57
  - specifications, 198
  - Summit X450e-24p switch, 53
  - Summit X450e-48p switch, 55
- Summit X650 AC power supply
  - installation, 109
  - specifications, 206
- Summit X650 DC power supply
  - installation, 110
  - specifications, 206
- Summit X650 power supply
  - features, 71
- Summit X650 series switches
  - features, 58
  - LEDs, 63
  - specifications, 201
  - Summit X650 24t switch, 59
  - Summit X650-24x switch, 60
- Summit XGM2-2bt option card, 151
- Summit XGM2-2sf option card, 151
- Summit XGM2-2xf option card, 150
- Summit XGM2-2xn option card, 149
- Summit XGM-2xn option card, 148
- SummitStack 128G cable, 95
- SummitStack configuration, 90
- switch, initial login, 123

## T

- TAA. *See* Trade Agreements Act
- technical specifications
  - Summit X150 series switches, 179
  - Summit X250e series switch, 183
  - Summit X450 series switches, 192

- Summit X450a series switches, 194
- Summit X450e series switch, 183
- Summit X450e series switches, 198
- Summit X650 series switches, 201
- Telco environment, 167
- temperature, wiring closet, 77
- text conventions, 10
- tools for installing equipment
  - external power supply, 126
  - Summit option card, 152
  - Summit switch, 97
- Trade Agreements Act, 15
- transition time, UPS, 87

## U

- unshielded twisted pair. *See* UTP
- uplink redundancy
  - on Summit switches, 17
  - setting up, 17
- UPS (uninterruptible power supply), 86
- UTP cable
  - bend radius, 81
  - category 5, 81
  - discharge ESD, 81
  - RF interference, 84

## V

- versatile interface module, 58
- VIM
  - replacing, 163
  - using stacking ports, 93
- VIM1-10G8X module, 61
- VIM1-SummitStack module, 61
- VIM1-SummitStack512 module, 62
  - using stacking ports, 94

## W

- wiring closet
  - electrostatic discharge, 78
  - floor coverings, 77
  - grounding, 77
  - humidity, 78
  - rack, securing, 80
  - temperature, 77
- wiring terminals, 79

## X

- XENPAK modules, 148
- XGM2-2bt option card, 151
- XGM2-2sf option card, 151
- XGM2-2xf option card, 150

- XGM2-2xn option card, 149
- XGM-2xn option card, 148

