

MK Biamp settings

November 13, 2001



MK2264 biamp

MK2294 biamp

OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

Low	Hi
0.0	0.0
0.96	0.00
Positive	Negative
55	1778
24	18
Butterworth	Butterworth
972	thru
24	
Butterworth	
649	1585
-4.0	-3.5
Parametric	Parametric
4.73	2.82
0.21	0.35
447	3868
3.0	-3.5
Parametric	Parametric
4.73	4.73
0.21	0.21
	3073
	-9.0
	Parametric
	0.94
	1.26
	17783
	-3.5
	Parametric
	3.76
	0.27

Low	Hi
0.0	0.0
0.94	0.00
Positive	Negative
55	1778
24	18
Butterworth	Butterworth
1000	thru
24	
Butterworth	
649	1585
-4.0	-3.5
Parametric	Parametric
4.73	2.82
0.21	0.35
447	2985
2.0	-3.0
Parametric	Parametric
4.73	4.73
0.21	0.21
	3073
	-7.5
	Parametric
	0.94
	1.16

MK Biamp settings

November 13, 2001



MK5264 biamp

MK5294 biamp

OUTPUT	Name
GAIN	(dB)
DELAY	(ms)
POLARITY	
HPF	Freq (Hz)
	Slope (dB)
	Shape
LPF	Freq (Hz)
	Slope (dB)
	Shape
PEQ1	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ2	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ3	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ4	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)
PEQ5	Freq (Hz)
	Level (dB)
	Type
	Q
	(Bandwidth)

Low	Hi
1.0	0.0
1.02	0.00
Positive	Positive
55	1631
24	24
Butterworth	Butterworth
1189	thru
18	
Butterworth	
546	2818
-4.0	-10.0
Parametric	Parametric
2.00	0.79
0.50	1.59

Low	Hi
1.0	0.0
0.92	0.00
Positive	Positive
55	1778
24	24
Butterworth	Butterworth
1189	thru
18	
Butterworth	
546	2661
-4.0	-10.5
Parametric	Parametric
2.00	0.79
0.50	1.64