

KF761 Array Processor Settings

October 2, 2002



KF761 triamp

OUTPUT	Name	Low	Mid	Hi
GAIN	(dB)	3.5	0.0	6.0
DELAY	(ms)	0.00	3.88	2.38
POLARITY		Positive	Positive	Positive
HPF	Freq (Hz)	40	229	1334
	Slope (dB)	24	24	24
	Shape	Butterworth	Butterworth	Butterworth
LPF	Freq (Hz)	173	1454	thru
	Slope (dB)	24	24	
	Shape	Butterworth	Butterworth	
PEQ1	Freq (Hz)	55	382	1540
	Level (dB)	6.0	-7.5	-9.5
	Type	Parametric	Parametric	Parametric
	Q	1.58	1.79	2.00
	(Bandwidth)	0.63	0.61	0.61
PEQ2	Freq (Hz)	119	602	2661
	Level (dB)	-5.0	-4.6	-8.5
	Type	Parametric	Parametric	Parametric
	Q	2.51	2.51	1.58
	(Bandwidth)	0.40	0.40	0.73
PEQ3	Freq (Hz)	237	944	5464
	Level (dB)	-9.0	1.0	-6.0
	Type	Parametric	Parametric	Parametric
	Q	2.24	2.98	1.58
	(Bandwidth)	0.53	0.34	0.63
PEQ4	Freq (Hz)	168		10902
	Level (dB)	6.0		2.0
	Type	Parametric		Parametric
	Q	2.11		2.00
	(Bandwidth)	0.47		0.50
PEQ5	Freq (Hz)			
	Level (dB)			
	Type			
	Q			
	(Bandwidth)			

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth).